

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

H.845.8

(01/2015)

SERIES H: AUDIOVISUAL AND MULTIMEDIA SYSTEMS

E-health multimedia services and applications –
Interoperability compliance testing of personal health
systems (HRN, PAN, LAN, TAN and WAN)

**Conformance of ITU-T H.810 personal health
devices: PAN/LAN/TAN interface Part 5H:
Independent living activity hub: Agent**

Recommendation ITU-T H.845.8

ITU-T H-SERIES RECOMMENDATIONS
AUDIOVISUAL AND MULTIMEDIA SYSTEMS

CHARACTERISTICS OF VISUAL TELEPHONE SYSTEMS	H.100–H.199
INFRASTRUCTURE OF AUDIOVISUAL SERVICES	
General	H.200–H.219
Transmission multiplexing and synchronization	H.220–H.229
Systems aspects	H.230–H.239
Communication procedures	H.240–H.259
Coding of moving video	H.260–H.279
Related systems aspects	H.280–H.299
Systems and terminal equipment for audiovisual services	H.300–H.349
Directory services architecture for audiovisual and multimedia services	H.350–H.359
Quality of service architecture for audiovisual and multimedia services	H.360–H.369
Telepresence	H.420–H.429
Supplementary services for multimedia	H.450–H.499
MOBILITY AND COLLABORATION PROCEDURES	
Overview of Mobility and Collaboration, definitions, protocols and procedures	H.500–H.509
Mobility for H-Series multimedia systems and services	H.510–H.519
Mobile multimedia collaboration applications and services	H.520–H.529
Security for mobile multimedia systems and services	H.530–H.539
Security for mobile multimedia collaboration applications and services	H.540–H.549
Mobility interworking procedures	H.550–H.559
Mobile multimedia collaboration inter-working procedures	H.560–H.569
BROADBAND, TRIPLE-PLAY AND ADVANCED MULTIMEDIA SERVICES	
Broadband multimedia services over VDSL	H.610–H.619
Advanced multimedia services and applications	H.620–H.629
Ubiquitous sensor network applications and Internet of Things	H.640–H.649
IPTV MULTIMEDIA SERVICES AND APPLICATIONS FOR IPTV	
General aspects	H.700–H.719
IPTV terminal devices	H.720–H.729
IPTV middleware	H.730–H.739
IPTV application event handling	H.740–H.749
IPTV metadata	H.750–H.759
IPTV multimedia application frameworks	H.760–H.769
IPTV service discovery up to consumption	H.770–H.779
Digital Signage	H.780–H.789
E-HEALTH MULTIMEDIA SERVICES AND APPLICATIONS	
Interoperability compliance testing of personal health systems (HRN, PAN, LAN, TAN and WAN)	H.820–H.859
Multimedia e-health data exchange services	H.860–H.869

For further details, please refer to the list of ITU-T Recommendations.

Recommendation ITU-T H.845.8

Conformance of ITU-T H.810 personal health devices: PAN/LAN/TAN interface Part 5H: Independent living activity hub: Agent

Summary

Recommendation ITU-T H.845.8 is a transposition of Continua Test Tool DG2013, Test Suite Structure & Test Purposes, PAN-LAN-TAN Interface; Part 5H: Device Specializations. Agent (Activity Hub) (Version 1.5, 2014-01-24), that was developed by the Continua Health Alliance. A number of versions of this specification existed before transposition.

This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

History

Edition	Recommendation	Approval	Study Group	Unique ID*
1.0	ITU-T H.845.8	2015-01-13	16	11.1002/1000/112269

* To access the Recommendation, type the URL <http://handle.itu.int/> in the address field of your web browser, followed by the Recommendation's unique ID. For example, <http://handle.itu.int/11.1002/1000/11830-en>.

FOREWORD

The International Telecommunication Union (ITU) is the United Nations specialized agency in the field of telecommunications, information and communication technologies (ICTs). The ITU Telecommunication Standardization Sector (ITU-T) is a permanent organ of ITU. ITU-T is responsible for studying technical, operating and tariff questions and issuing Recommendations on them with a view to standardizing telecommunications on a worldwide basis.

The World Telecommunication Standardization Assembly (WTSA), which meets every four years, establishes the topics for study by the ITU-T study groups which, in turn, produce Recommendations on these topics.

The approval of ITU-T Recommendations is covered by the procedure laid down in WTSA Resolution 1.

In some areas of information technology which fall within ITU-T's purview, the necessary standards are prepared on a collaborative basis with ISO and IEC.

NOTE

In this Recommendation, the expression "Administration" is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

Compliance with this Recommendation is voluntary. However, the Recommendation may contain certain mandatory provisions (to ensure, e.g., interoperability or applicability) and compliance with the Recommendation is achieved when all of these mandatory provisions are met. The words "shall" or some other obligatory language such as "must" and the negative equivalents are used to express requirements. The use of such words does not suggest that compliance with the Recommendation is required of any party.

INTELLECTUAL PROPERTY RIGHTS

ITU draws attention to the possibility that the practice or implementation of this Recommendation may involve the use of a claimed Intellectual Property Right. ITU takes no position concerning the evidence, validity or applicability of claimed Intellectual Property Rights, whether asserted by ITU members or others outside of the Recommendation development process.

As of the date of approval of this Recommendation, ITU had not received notice of intellectual property, protected by patents, which may be required to implement this Recommendation. However, implementers are cautioned that this may not represent the latest information and are therefore strongly urged to consult the TSB patent database at <http://www.itu.int/ITU-T/ipr/>.

© ITU 2015

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without the prior written permission of ITU.

Table of Contents

	Page
1 Scope.....	1
2 References.....	2
3 Definitions	2
3.1 Terms defined elsewhere	2
3.2 Terms defined in this Recommendation.....	2
4 Abbreviations and acronyms	2
5 Conventions	3
6 Test suite structure (TSS)	4
7 Electronic attachment	6
Annex A – Test purposes (TPs).....	7
A.1 TP definition conventions.....	7
A.2 Subgroup 1.3.8: Activity hub (HUB)	8
Bibliography.....	46

Electronic attachment: Protocol implementation conformance statements (PICS) and protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

Introduction

This Recommendation is a transposition of Continua Test Tool DG2013, Test Suite Structure & Test Purposes, PAN-LAN-TAN Interface; Part 5H: Device Specializations. Agent (Activity Hub) (Version 1.5, 2014-01-24), that was developed by the Continua Health Alliance. A number of versions of this specification existed before transposition and these can be found in the table below.

Version	Date	Revision history
1.2	2012-10-05	Initial release for Test Tool DG2011. This is the same version as "TSS&TP_1.5_PAN-LAN_PART_3H_v1.3.doc" because new features included in [b-CDG 2011] do not affect the test procedures specified in this document.
1.3	2013-05-24	Initial release for Test Tool DG2012. This uses "TSS&TP_DG2011_PAN-LAN_PART_5H_v1.3.doc" as a baseline and adds new features included in [b-CDG 2012]: Max APDU size for GM, BCA and ECG.
1.4	2014-01-24	Initial release for Test Tool DG2013. This uses "TSS&TP_DG2012_PAN-LAN_PART_5H_v1.4.doc" as a baseline and adds new features included in [ITU-T H.810]: <ul style="list-style-type: none">• Adds glucose meter BLE• Adds BLE SSP support• Adds NFC new transport• Adds INR device specialization

Recommendation ITU-T H.845.8

Conformance of ITU-T H.810 personal health devices: PAN/LAN/TAN interface Part 5H: Independent living activity hub: Agent

1 Scope

The scope of this Recommendation¹ is to provide a test suite structure and the test purposes (TSS AND TP) for the PAN/LAN/TAN interface based on the requirements defined in the Continua Design Guidelines (CDG) [ITU-T H.810]. The objective of this test specification is to provide a high probability of air interface interoperability between different devices.

The TSS and TP for the PAN/LAN/TAN Interface document have been divided into ten parts. Each part is listed below:

- **Part 1:** Optimized exchange protocol [ISO/IEEE 11073-20601A] Agent
- **Part 2:** Optimized exchange protocol [ISO/IEEE 11073-20601A] Manager
- **Part 3:** Continua design guidelines. Agent
- **Part 4:** Continua design guidelines. Manager
- **Part 5:** Device specializations. Agent. This document is divided in 14 subparts:
 - **Part 5A:** Weighing scales
 - **Part 5B:** Glucose meter
 - **Part 5C:** Pulse oximeter
 - **Part 5D:** Blood pressure monitor
 - **Part 5E:** Thermometer
 - **Part 5F:** Cardiovascular fitness and activity monitor
 - **Part 5G:** Strength fitness equipment
 - **Part 5H:** Independent living activity hub
 - **Part 5I:** Adherence monitor
 - **Part 5J:** Insulin pump (Future development)
 - **Part 5K:** Peak flow
 - **Part 5L:** Body composition analyser
 - **Part 5M:** Basic electrocardiograph
 - **Part 5N:** International normalized ratio monitor
- **Part 6:** Device specializations. Manager
- **Part 7:** Continua design guidelines. Agent BLE
- **Part 8:** Continua design guidelines. Manager BLE
- **Part 9:** Personal health devices transcoding white paper. Agent
- **Part 10:** Personal health devices transcoding white paper. Manager

¹ This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

2 References

The following ITU-T Recommendations and other references contain provisions which, through reference in this text, constitute provisions of this Recommendation. At the time of publication, the editions indicated were valid. All Recommendations and other references are subject to revision; users of this Recommendation are therefore encouraged to investigate the possibility of applying the most recent edition of the Recommendations and other references listed below. A list of the currently valid ITU-T Recommendations is regularly published. The reference to a document within this Recommendation does not give it, as a stand-alone document, the status of a Recommendation.

- [ITU-T H.810] Recommendation ITU-T H.810 (2013), *Interoperability design guidelines for personal health systems*.
- [ISO/IEEE 11073-20601A] ISO/IEEE 11073-20601:2010, *Health informatics – Personal health device communication – Part 20601: Application profile – Optimized exchange protocol*, including ISO/IEEE 11073-20601:2010 Amd 1:2015.
<http://www.iso.org/iso/home/store/catalogue_tc/catalogue_detail.htm?csnumber=54331>
with
<http://www.iso.org/iso/home/store/catalogue_tc/catalogue_detail.htm?csnumber=63972>
- [ISO/IEEE 11073-104xx] ISO/IEEE 11073-104xx (in force), *Health informatics – Personal health device communication – Device specialization*.
NOTE – Shorthand is used to refer to the collection of device specialization standards that utilize [ISO/IEEE 11073-20601A], where xx can be any number from 01 to 99, inclusive.
- [ISO/IEEE 11073-10471] ISO/IEEE 11073-10471-2008, *Health informatics – Personal health device communication – Part 10471: Device specialization – Independent living activity hub*.

3 Definitions

3.1 Terms defined elsewhere

This Recommendation uses the following terms defined elsewhere:

3.1.1 agent [ISO/IEEE 11073-20601A]: A node that collects and transmits personal health data to an associated manager.

3.1.2 manager [ISO/IEEE 11073-20601A]: A node receiving data from one or more agent systems. Some examples of managers include a cellular phone, health appliance, set top box, or a computer system.

3.2 Terms defined in this Recommendation

None.

4 Abbreviations and acronyms

This Recommendation uses the following abbreviations and acronyms:

ATS	Abstract Test Suite
DUT	Device Under Test
CDG	Continua Design Guidelines
GUI	Graphical User Interface

INR	International Normalized Ratio
IUT	Implementation Under Test
MDS	Medical Device System
NFC	Near Field Communication
PAN	Personal Area Network
PCT	Protocol Conformance Testing
PCO	Point of Control and Observation
PHD	Personal Healthcare Device
PHDC	Personal Healthcare Device Class
PHM	Personal Health Manager
PICS	Protocol Implementation Conformance Statement
PIXIT	Protocol Implementation extra Information for Testing
SDP	Service Discovery Protocol
SOAP	Simple Object Access Protocol
TCRL	Test Case Reference List
TCWG	Test and Certification Working Group
TP	Test Purpose
TSS	Test Suite Structure
USB	Universal Serial Bus
WDM	Windows Driver Model

5 Conventions

The key words "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "MAY", "MAY NOT" in this document are to be interpreted as in [b-ETSI SR 001 262].

- SHALL is equivalent to 'must' or 'it is required to'.
- SHALL NOT is equivalent to 'must not' or 'it is not allowed'.
- SHOULD is equivalent to 'it is recommended to'.
- SHOULD NOT is equivalent to 'it is not recommended to'.
- MAY is equivalent to 'is permitted'.
- MAY NOT is equivalent to 'it is not required that'.

NOTE – The above-mentioned key words are capitalized for illustrative purposes only and they do not appear capitalized within this Recommendation.

Reference is made in the ITU-T H.800-series of Recommendations to different versions of the Continua Design Guidelines (CDG) by a specific designation. The list of terms that may be used in this Recommendation is provided in Table 1.

Table 1 – List of designations associated to the various versions of the CDG

CDG name	Transposed as	Version	Description	Designation
2013 plus errata	ITU-T H.810	4.1	CDG 2013 plus errata noting all ratified bugs.	–
2013	–	4.0	Release 2013 of the CDG including maintenance updates of CDG 2012 and additional guidelines that cover new functionalities.	Endorphin
2012 plus errata	–	3.1	CDG 2012 plus errata noting all ratified bugs [b-CDG 2012].	–
2012	–	3.0	Release 2012 of the CDG including maintenance updates of CDG 2011 and additional guidelines that cover new functionalities.	Catalyst
2011 plus errata	–	2.1	CDG 2011 integrated with identified errata.	–
2011	–	2.0	Release 2011 of the CDG including maintenance updates of CDG 2010 and additional guidelines that cover new functionalities [b-CDG 2011].	Adrenaline
2010 plus errata	–	1.6	CDG 2010 integrated with identified errata.	–
2010	–	1.5	Release 2010 of the CDG with maintenance updates of CDG Version 1 and additional guidelines that cover new functionalities [b-CDG 2010].	1.5
1.0	–	1.0	First released version of the CDG [b-CDG 1.0].	–

6 Test suite structure (TSS)

The test purposes (TPs) for the PAN/LAN/TAN interface have been divided into the main subgroups specified below. Annex A describes the TPs for subgroup 1.3.8 (shown in bold).

- Group 1: Agent (AG)
 - Group 1.1: Transport (TR)
 - Subgroup 1.1.1: Design guidelines: common (DGC)
 - Subgroup 1.1.2: USB design guidelines (UDG)
 - Subgroup 1.1.3: Bluetooth design guidelines (BDG)
 - Subgroup 1.1.4: Pulse oximeter design guidelines (PODG)
 - Subgroup 1.1.5: Cardiovascular design guidelines (CVDG)
 - Subgroup 1.1.6: Activity hub design guidelines (HUBDG)
 - Subgroup 1.1.7: ZigBee design guidelines (ZDG)
 - Subgroup 1.1.8: Glucose meter design guidelines (GLDG)
 - Subgroup 1.1.9: Bluetooth low energy design guidelines (BLEDG)
 - Subgroup 1.1.10: Basic electrocardiograph design guidelines (ECGDG)
 - Subgroup 1.1.11: NFC design guidelines (NDG)
 - Group 1.2: Optimized exchange protocol (OXP)
 - Subgroup 1.2.1: PHD domain information model (DIM)

- Subgroup 1.2.2: PHD service model (SER)
- Subgroup 1.2.3: PHD communication model (COM)
- Group 1.3: Devices class specializations (CLASS)
 - Subgroup 1.3.1: Weighing scales (WEG)
 - Subgroup 1.3.2: Glucose meter (GL)
 - Subgroup 1.3.3: Pulse oximeter (PO)
 - Subgroup 1.3.4: Blood pressure monitor (BPM)
 - Subgroup 1.3.5: Thermometer (TH)
 - Subgroup 1.3.6: Cardiovascular (CV)
 - Subgroup 1.3.7: Strength (ST)
 - **Subgroup 1.3.8: Activity hub (HUB)**
 - Subgroup 1.3.9: Adherence monitor (AM)
 - Subgroup 1.3.10: Insulin pump (IP) (Future development)
 - Subgroup 1.3.11: Peak flow (PF)
 - Subgroup 1.3.12: Body composition analyser (BCA)
 - Subgroup 1.3.13: Basic electrocardiograph (ECG)
 - Subgroup 1.3.14: International normalized ratio (INR)
- Group 1.4: Personal health device transcoding whitepaper (PHDTW)
 - Subgroup 1.4.1: Whitepaper general requirements (GEN)
 - Subgroup 1.4.2: Whitepaper thermometer requirements (TH)
 - Subgroup 1.4.3: Whitepaper blood pressure requirements (BPM)
 - Subgroup 1.4.4: Whitepaper heart rate requirements (HR)
 - Subgroup 1.4.5: Whitepaper glucose meter requirements (GL)
- Group 2: Manager (MAN)
 - Group 2.1: Transport (TR)
 - Subgroup 2.1.1: Design guidelines: common (DGC)
 - Subgroup 2.1.2: USB design guidelines (UDG)
 - Subgroup 2.1.3: Bluetooth design guidelines (BDG)
 - Subgroup 2.1.4: Cardiovascular design guidelines (CVDG)
 - Subgroup 2.1.5: Activity hub design guidelines (HUBDG)
 - Subgroup 2.1.6: ZigBee design guidelines (ZDG)
 - Subgroup 2.1.7: Bluetooth low energy design guidelines (BLEDG)
 - Subgroup 2.1.8: NFC design guidelines (NDG)
 - Group 2.2: 20601: Optimized exchange protocol (OXP)
 - Subgroup 2.2.1: General (GEN)
 - Subgroup 2.2.2: PHD domain information model (DIM)
 - Subgroup 2.2.3: PHD service model (SER)
 - Subgroup 2.2.4: PHD communication model (COM)
 - Group 2.3: Devices class specializations (CLASS)

- Subgroup 2.3.1: Weighing scales (WEG)
- Subgroup 2.3.2: Glucose meter (GL)
- Subgroup 2.3.3: Pulse oximeter (PO)
- Subgroup 2.3.4: Blood pressure monitor (BPM)
- Subgroup 2.3.5: Thermometer (TH)
- Subgroup 2.3.6: Cardiovascular (CV)
- Subgroup 2.3.7: Strength (ST)
- Subgroup 2.3.8: Activity hub (HUB)
- Subgroup 2.3.9: Adherence monitor (AM)
- Subgroup 2.3.10: Insulin pump (IP) (Future development)
- Subgroup 2.3.11: Peak flow (PF)
- Subgroup 2.3.12: Body composition analyser (BCA)
- Subgroup 2.3.13: Basic electrocardiograph (ECG)
- Subgroup 2.3.14: International normalized ratio (INR)
- Group 2.4: Personal health device transcoding whitepaper (PHDTW)
 - Subgroup 2.4.1: Whitepaper general requirements (GEN)
 - Subgroup 2.4.2: Whitepaper thermometer requirements (TH)
 - Subgroup 2.4.3: Whitepaper blood pressure measurement requirements (BPM)
 - Subgroup 2.4.4: Whitepaper heart rate requirements (HR)
 - Subgroup 2.4.5: Whitepaper glucose meter requirements (GL)

7 Electronic attachment

The protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of this Annex can be downloaded from <http://handle.itu.int/11.1002/2000/12067>.

In the electronic attachment, letters "C" and "I" in the column labelled "Mandatory" are used to distinguish between "PICS" and "PIXIT" respectively during testing. If the cell is empty, the corresponding PICS is "independent". If the field contains a "C", the corresponding PICS is dependent on other PICS, and the logical expression is detailed in the "SCR_Expression" field. The static conformance review (SCR) is used in the test tool to assert whether the PICS selection is consistent.

Annex A

Test purposes (TPs)

(This annex forms an integral part of this Recommendation.)

A.1 TP definition conventions

The test purposes are defined according to the following rules:

- **TP Id:** This is a unique identifier (TP/<TT>/<DUT>/<GR>/<SGR>/<XX> – <NNN>). It is specified according to the naming convention defined below:
 - Each test purpose identifier is introduced by the prefix "TP".
 - <TT>: This is the test tool that will be used in the test case:
 - PAN: Personal area network (Bluetooth or USB)
 - LAN: Local area network (ZigBee)
 - PAN-LAN: Personal area network (Bluetooth or USB) – Local area network (ZigBee)
 - LP-PAN: Low power personal area network (Bluetooth low energy)
 - TAN: Touch area network (NFC)
 - PLT: Personal area network (Bluetooth or USB) – Local area network (ZigBee) – Touch area network (NFC)
 - <DUT>: This is the device under test:
 - AG: PAN/LAN Agent
 - MAN: PAN/LAN Manager
 - <GR>: This identifies a group of test cases.
 - <SGR>: This identifies a subgroup of test cases.
 - <XX>: This identifies the type of testing:
 - BV: Valid behaviour test
 - BI: Invalid behaviour test
 - <NNN>: This is a sequential number that identifies the test purpose.
- **TP label:** This is the TP's title.
 - **Coverage:** This contains the specification reference and clause to be checked by the TP.
 - Spec: This indicates the earliest version of the specification from which the testable items to be checked by the TP were included.
 - Testable item: This contains testable items to be checked by the TP.
 - **Test purpose:** This is a description of the requirements to be tested.
 - **Applicability:** This contains the PICS items that define if the test case is applicable or not for a specific device. When a TP contains an "ALL" in this field it means that it applies to the device under test within that scope of the test (specialization, transport used, etc.).
 - **Initial condition:** This indicates the state to which the DUT needs to be moved at the beginning of TC execution.
 - **Test procedure:** This describes the steps to be followed in order to execute the test case.
 - **Pass/Fail criteria:** This provides criteria to decide whether the DUT passes or fails the test case.

A.2 Subgroup 1.3.8: Activity hub (HUB)

TP Id		TP/PLT/AG/CLASS/HUB/BV-000		
TP label		Get MDS Object for Activity Hub specialization: Mandatory, Conditional and Optional Attributes		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	MDSAttr 1; M	MDSAttr 2; M	MDSAttr 3; M
		MDSAttr 4; M	MDSAttr 5; O	MDSAttr 6; O
		MDSAttr 7; R	MDSAttr 8; R	MDSAttr 9; R
		MDSAttr 10; M	MDSAttr 11; M	MDSAttr 12; M
OperaProc1;M				
Applicability		C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the operating state.		
Test procedure		<p>1. The simulated manager issues a "roiv-cmip-get" command with the handle set to 0 (to request for an MDS object) and an attribute-id-list set to 0 to indicate all attributes.</p> <p>2. The agent responds with a "rors-cmip-get" service message in which the attribute-list contains a list of all implemented attributes of the MDS object:</p> <p>MDS Attributes:</p> <ul style="list-style-type: none"> a. Mandatory attribute System-model <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_MODEL <input type="checkbox"/> attribute-type = SystemModel <input type="checkbox"/> attribute-value.length =<variable> <input type="checkbox"/> attribute-value = {Manufacturer, Model} b. Mandatory attribute Dev-Configuration-Id <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_DEV_CONFIG_ID <input type="checkbox"/> attribute-type = ConfigId <input type="checkbox"/> attribute-value.length = 2 bytes <input type="checkbox"/> attribute-value = <between 0x4000 and 0x7FFF> c. Mandatory attribute Date-and-Time <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length =<variable> d. Optional attribute Relative-Time <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_REL <input type="checkbox"/> attribute-type = RelativeTime (INT-U32) <input type="checkbox"/> attribute-value.length = 4 bytes e. Optional attribute HiRes-Relative-Time <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_REL_HI_RES <input type="checkbox"/> attribute-type = HighResRelativeTime <input type="checkbox"/> attribute-value.length =<variable> 		

	<p>f. Recommended attribute Power-Status</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_POWER_STAT <input type="checkbox"/> attribute-type = PowerStatus (BITS-16) <input type="checkbox"/> attribute-value.length = 2 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> IF C_AG_HUB_034= TRUE THEN attribute-value = ON_MAINS (0x8000) and the rest of the bits must not be set ELSE attribute-value = ON_BATTERY(0x4000) Only one of the following may be active: <ul style="list-style-type: none"> • chargingFull(8), • chargingTrickle(9), • chargingOff(10). • The rest of the bits must not be set <p>g. Recommended attribute Battery-Level</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_VAL_BATT_CHARGE <input type="checkbox"/> attribute-type = INT-U16 <input type="checkbox"/> attribute-value.length = 2 bytes <input type="checkbox"/> attribute-value = <undefined if value>100 > <p>h. Recommended attribute Remaining-Battery-Time</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_BATT_REMAIN <input type="checkbox"/> attribute-type = BatMeasure <input type="checkbox"/> attribute-value.length = <variable> <input type="checkbox"/> attribute-value = <units shall be set to one of: MDC_DIM_MIN, MDC_DIM_HR, MDC_DIM_DAY > <p>i. Mandatory attribute System-Type-Spec_List</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_SYS_TYPE_SPEC_LIST <input type="checkbox"/> attribute-type = TypeVerList <input type="checkbox"/> attribute-value.length = 4 bytes attribute-value = MDC_DEV_SPEC_PROFILE_AI_ACTIVITY_HUB, 1 <input type="checkbox"/> Attribute System-Type must not be present.
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-000_A		
TP label	Extended Configurations		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	DIM 2; M	
Applicability	C_AG_OXP_176 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the unassociated state.		

Test procedure	<ol style="list-style-type: none"> 1. The agent under test sends an Association Request to the simulated manager. The expected fields sent by the agent are: <ol style="list-style-type: none"> a. dev-config-id <ul style="list-style-type: none"> <input type="checkbox"/> field-type = ConfigId <input type="checkbox"/> field-length = 2 bytes <input type="checkbox"/> field- value = <between 0x4000 and 0x7FFF> b. Data-Req-Mode-Capab: <ul style="list-style-type: none"> <input type="checkbox"/> field-length = 4 bytes <input type="checkbox"/> field- value = 0xXX 0x01 0xXX (Agent initiated) 2. The simulated manager responses with an accepted-unknown-config. 3. The agent sends a configuration event report, with the following fields: dev-config-id <ul style="list-style-type: none"> <input type="checkbox"/> field-type = ConfigId <input type="checkbox"/> field-length = 2 bytes <input type="checkbox"/> field- value = <between 0x4000 and 0x7FFF> 4. The simulated manager responds with a unsupported-configuration. 5. The agent sends a new configuration event report with a new configuration (if it has more). 6. Repeat the last two steps checking all the ConfigId-values until the agent sends a ReleaseRequest with the reason "no-more-configurations".
Pass/Fail criteria	All Dev-config-id values are between 0x4000 and 0x7FFF.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-001		
TP label	RTC, Set time command and internal clock for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	MDSMethod 3; M	
Applicability	C_AG_OXP_176 AND C_AG_OXP_006 AND C_AG_HUB_034 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the configuring state.		
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager issues a "roiv-cmip-get" command with the handle set to 0 (to request for an MDS object) and the attribute-id-list set to 0 to indicate all attributes. 2. The agent responds with a "rors-cmip-get" service message in which the attribute-list contains a list of all implemented attributes of the MDS object: <ol style="list-style-type: none"> a. IF Recommended attribute Power-Status is present <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_POWER_STAT <input type="checkbox"/> attribute-type = PowerStatus (BITS-16) <input type="checkbox"/> attribute-value.length = 2 bytes <input type="checkbox"/> attribute-value = ON_MAINS (0x8000) b. Mandatory attribute Mds-Time-Info <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_MDS_TIME_INFO <input type="checkbox"/> attribute-type = MdsTimeInfo <input type="checkbox"/> attribute-value.length = 		

	<ul style="list-style-type: none"> <input type="checkbox"/> Sequence of of: <ul style="list-style-type: none"> ▪ Mds-time-cap-state <ul style="list-style-type: none"> – field-type = MdsTimeCapState – field-length =2 bytes – field-value = Bit 0 (mds-time-capab-real-time-clock) and Bit 1 (mds-time-capab-set-clock) must be set ▪ Time-sync-protocol <ul style="list-style-type: none"> – field-type = TimeProtocolId – field-length =OID-Type(INT-U16)
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-002		
TP label	MDS Configuration objects events for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	MDSEvent 1; M	ConfProc1; M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the configuring state.		
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager: <ol style="list-style-type: none"> a. APDU Type <ul style="list-style-type: none"> <input type="checkbox"/> field- type = PrstApdu <input type="checkbox"/> field-length =2 bytes <input type="checkbox"/> field-value =0xE7 0x00 b. invoke-id <ul style="list-style-type: none"> <input type="checkbox"/> field- type = InvokeIDType <input type="checkbox"/> field-length =INT-U16 <input type="checkbox"/> field- value=<Not relevant for this test> c. message <ul style="list-style-type: none"> <input type="checkbox"/> field- type = roiv-cmip-confirmed-event-report <input type="checkbox"/> field-length =two bytes <input type="checkbox"/> field- value=0x01 (EventReportArgumentSimple) d. obj-handle (EventReportArgumentSimple) <ul style="list-style-type: none"> <input type="checkbox"/> field- type = HANDLE <input type="checkbox"/> field-length =INT-U16 e. event-time (EventReportArgumentSimple) <ul style="list-style-type: none"> <input type="checkbox"/> field- type = Relative Time <input type="checkbox"/> field-length =INT-U32 		

	<ul style="list-style-type: none"> <input type="checkbox"/> field-value = <ul style="list-style-type: none"> • IF NOT C_AG_OXP_010 THEN value = 0xFF 0xFF 0xFF 0xFF f. event-type (EventReportArgumentSimple) <ul style="list-style-type: none"> <input type="checkbox"/> field- type = OID-Type <input type="checkbox"/> field-length =INT-U16 <input type="checkbox"/> field- value=0x 0D 0x 1C (MDC_NOTI_CONFIG) g. config-report-id (ConfigReport) <ul style="list-style-type: none"> <input type="checkbox"/> field- type = ConfigId <input type="checkbox"/> field-length = INT-U16 <input type="checkbox"/> field- value = <Between 0x40 0x00 and 0x7F 0xFF> h. obj-class (ConfigReport → ConfigObjectList (ConfigObject)) <ul style="list-style-type: none"> <input type="checkbox"/> field- type = OID-Type <input type="checkbox"/> field-length = INT-U16 <input type="checkbox"/> field- value = One or more of MDC_MOC_VMO_METRIC_ENUM must appear
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-003			
TP label	MDS objects events Activity Hub			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	MDSEvent 3; M	MDSEvent 4; M	MDSEvent 5; M
		MDSEvent 6; M	ServiceModel1; M	ServiceModel2; M
		OperaProc4; M		
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000 AND (C_AG_OXP_182 OR C_AG_OXP_183 OR C_AG_OXP_184 OR C_AG_OXP_189)			
Initial condition	The simulated manager and the agent under test are in the operating state.			
Test procedure	<ol style="list-style-type: none"> 1. Take measurements for every supported object in the agent under test. 2. Wait to receive every event report and check: <ol style="list-style-type: none"> a. message <ul style="list-style-type: none"> <input type="checkbox"/> field- type = Event Report <input type="checkbox"/> field-length = 2 bytes <input type="checkbox"/> field- value=0x01 0x01 (EventReportArgumentSimple, confirmed). This field identifies the type of message sent by the agent, for the confirmed event configuration, roiv-cmip-confirmed-event-report. 			
Pass/Fail criteria	Check that every received report is one of the following Data APDU and that it is confirmed: <ul style="list-style-type: none"> • MDC_NOTI_SCAN_REPORT_FIXED • MDC_NOTI_SCAN_REPORT_MP_FIXED • MDC_NOTI_SCAN_REPORT_VAR • MDC_NOTI_SCAN_REPORT_MP_VAR 			
Notes				

TP Id		TP/PLT/AG/CLASS/HUB/BV-005		
TP label		Get activity data Enumeration Object attributes for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 12; R	EnumObj 13; O
		EnumObj 14; O	EnumObj 15; R	EnumObj 16; R
		EnumObj 17; M	EnumObj 18; R	EnumObj 19; R
		EnumObj 20; R	EnumObj 21; R	EnumObj 22; M
		EnumObj 23; O		
Applicability		C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the unassociated state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. All Enumeration objects must have: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_PART_PHD_AI followed by one of the next: <ul style="list-style-type: none"> ▪ MDC_AI_TYPE_SENSOR_FALL ▪ MDC_AI_TYPE_SENSOR_PERS ▪ MDC_AI_TYPE_SENSOR_SMOKE ▪ MDC_AI_TYPE_SENSOR_CO ▪ MDC_AI_TYPE_SENSOR_WATER ▪ MDC_AI_TYPE_SENSOR_GAS ▪ MDC_AI_TYPE_SENSOR_MOTION ▪ MDC_AI_TYPE_SENSOR_PROPEXIT ▪ MDC_AI_TYPE_SENSOR_ENURESIS ▪ MDC_AI_TYPE_SENSOR_CONTACTCLOSURE ▪ MDC_AI_TYPE_SENSOR_USAGE ▪ MDC_AI_TYPE_SENSOR_SWITCH ▪ MDC_AI_TYPE_SENSOR_DOSAGE ▪ MDC_AI_TYPE_SENSOR_TEMP b. Mandatory attribute Supplemental-Types <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_SPPLEMENTAL_TYPES <input type="checkbox"/> attribute-type = SupplementalTypeList 		

- ❑ attribute-value.length =Sequence of TYPE (TYPE.length= 4 bytes → partition NomPartition (INT-U16) and code (OID-Type))
- ❑ attribute-value=
 - TYPE.partition= 0x00 0x82 (NOM_PART_PHD_AI, dec. value 130)
 - TYPE.code= Upper 10 bits are one of MDC_AI_LOCATION and the lower bits represent the unique instance of the location. This value denotes sensor location.
 - MDC_AI_LOCATION_START 1024
 - MDC_AI_LOCATION_UNKNOWN 1024
 - MDC_AI_LOCATION_UNSPECIFIED 1088
 - MDC_AI_LOCATION_RESIDENT 1152
 - MDC_AI_LOCATION_LOCALUNIT 1216
 - MDC_AI_LOCATION_BEDROOM 3072
 - MDC_AI_LOCATION_BEDROOMMASTER 3136
 - MDC_AI_LOCATION_TOILET 3200
 - MDC_AI_LOCATION_TOILETMAIN 3264
 - MDC_AI_LOCATION_OUTSIDETOILET 3328
 - MDC_AI_LOCATION_SHOWERROOM 3392
 - MDC_AI_LOCATION_KITCHEN 3456
 - MDC_AI_LOCATION_KITCHENMAIN 3520
 - MDC_AI_LOCATION_LIVINGAREA 3584
 - MDC_AI_LOCATION_LIVINGROOM 3648
 - MDC_AI_LOCATION_DININGROOM 3712
 - MDC_AI_LOCATION_STUDY 3776
 - MDC_AI_LOCATION_HALL 3840
 - MDC_AI_LOCATION_LANDING 3904
 - MDC_AI_LOCATION_STAIRS 3968
 - MDC_AI_LOCATION_HALLLANDINGSTAIRS 4032
 - MDC_AI_LOCATION_GARAGE 4096
 - MDC_AI_LOCATION_GARDENGARAGE 4160
 - MDC_AI_LOCATION_GARDENGARAGEAREA 4224
 - MDC_AI_LOCATION_FRONTGARDEN 4288
 - MDC_AI_LOCATION_BACKGARDEN 4352
 - MDC_AI_LOCATION_SHED 4416
 - MDC_AI_APPLIANCE_KETTLE 7168
 - MDC_AI_APPLIANCE_TELEVISION 7232
 - MDC_AI_APPLIANCE_STOVE 7296
 - MDC_AI_APPLIANCE_MICROWAVE 7360
 - MDC_AI_APPLIANCE_TOASTER 7424
 - MDC_AI_APPLIANCE_VACUUM 7488
 - MDC_AI_APPLIANCE_APPLIANCE 7552
 - MDC_AI_APPLIANCE_FAUCET 7616
 - MDC_AI_LOCATION_FRONTDOOR 9216
 - MDC_AI_LOCATION_BACKDOOR 9280
 - MDC_AI_LOCATION_FRIDGEDOOR 9344

- MDC_AI_LOCATION_MEDCABDOOR 9408
- MDC_AI_LOCATION_WARDROBEDOOR 9472
- MDC_AI_LOCATION_FRONTCUPBOARDDOOR 9536
- MDC_AI_LOCATION_OTHERDOOR 9600
- MDC_AI_LOCATION_BED 11264
- MDC_AI_LOCATION_CHAIR 11328
- MDC_AI_LOCATION_SOFA 11392
- MDC_AI_LOCATION_TOILET_SEAT 11456
- MDC_AI_LOCATION_STOOL 11520

c. Mandatory attribute Metric-Spec-Small

- attribute-id = MDC_ATTR_METRIC_SPEC_SMALL
- attribute-type = MetricSpecSmall (BITS-16)
- attribute-value ≠ 0x00 0x00
 - Bit 0 (mss-avail-intermittent(0)) must be set.
 - Bit 1 (mss-avail-stored-data(1)) must be set.
 - Bit 2 (mss-upd-aperiodic(2)) must be set.
 - Bit 3 (mss-msmt-aperiodic(3)) is set.
 - Bit 9 (mss-acc-agent-initiated(9)) is set.

d. Not recommended attribute Metric-Structure-Small

- attribute-id = MDC_ATTR_METRIC_STRUCTURE_SMALL
- attribute-type = MetricStructureSmall
- attribute-value.length = Sequence of (ms-struct.length =1byte(INT-U8) + ms-comp-no =1byte(INT-U8))

e. Not recommended attribute Measurement-Status

- attribute-id = MDC_ATTR_MSMT_STAT
- attribute-type = MeasurementStatus (BITS-16)
- attribute-value.length = 2 bytes

f. Only one attribute of Metric-Id and Metric-Id-List shall be present.

g. Not recommended attribute Metric-Id

- attribute-id = MDC_ATTR_ID_PHYSIO
- attribute-type = OID-Type (INT-U16)
- attribute-value.length = 2 bytes
- attribute-value = Only one attribute of Metric-Id and Metric-Id-List shall be present.

h. Not Recommended attribute Metric-Id-List

- attribute-id = MDC_ATTR_ID_PHYSIO_LIS
- attribute-type = MetricIdList
- attribute-value.length= <variable> (SEQUENCE OF OID-Type (INT-U16))
- The [Metric-Id-List] attribute shall be used if a compound observed value is used, which does not incorporate the Metric-Id directly. The order of the Metric-Id-List shall correspond to the order of the elements in the compound observed value.

i. Not recommended attribute Metric-Id-Partition

- attribute-id = MDC_ATTR_METRIC_ID_PART
- attribute-type = NomPartition (INT-U16)

- attribute-value.length = 2 bytes
- j. Not recommended attribute Unit-Code
 - attribute-id = MDC_ATTR_UNIT_CODE
 - attribute-type = OID-Type (INT-U16)
 - attribute-value.length = 2 bytes
- k. Not recommended attribute Source-Handle-Reference
 - attribute-id = MDC_ATTR_SOURCE_HANDLE_REF
 - attribute-type = HANDLE (INT-U16)
 - attribute-value.length = 2 bytes
- l. Recommended attribute Absolute-Time-Stamp
 - attribute-id = MDC_ATTR_TIME_STAMP_ABS
 - attribute-type = AbsoluteTime
 - attribute-value.length = 8 bytes
- m. Optional attribute Relative-Time
 - attribute-id = MDC_ATTR_TIME_REL
 - attribute-type = RelativeTime (INT-U32)
 - attribute-value.length = 4 bytes
- n. Optional attribute HiRes-Relative-Time
 - attribute-id = MDC_ATTR_TIME_REL_HI_RES
 - attribute-type = HighResRelativeTime
 - attribute-value.length = 8 bytes
- o. Not recommended attribute Measure-Active-Period
 - attribute-id = MDC_ATTR_TIME_PD_MSMT_ACTIVE
 - attribute-type = FLOAT-Type (INT-U32)
 - attribute-value.length = 4 bytes
- p. Not recommended attribute Enum-Observed-Value-Simple-OID
 - attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_OID
 - attribute-type = OID-Type (INT-U16)
 - attribute-value.length = 2 bytes
- q. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str
 - attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR
 - attribute-type = BITS-32
 - attribute-value.length = 4 bytes
- r. Not recommended attribute Enum-Observed-Value-Basic-Bit-Str
 - attribute-id= MDC_ATTR_ENUM_OBS_VAL_BASIC_BIT_STR
 - attribute-type = BITS-16
 - attribute-value.length = 2 bytes
- s. Not recommended attribute Enum-Observed-Value-Simple-Str
 - attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_STR
 - attribute-type = EnumPrintableString
 - attribute-value.length =<variable>
- t. Not recommended attribute Enum-Observed-Value
 - attribute-id= MDC_ATTR_VAL_ENUM_OBS
 - attribute-type = EnumObsValue

	<ul style="list-style-type: none"> <input type="checkbox"/> attribute-value.length =<variable> u. Not recommended attribute Enum-Observed-Value-Partition <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_PART <input type="checkbox"/> attribute-type = NomPartition (INT-U16) <input type="checkbox"/> attribute-value-length=2 bytes
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_A		
TP label	Get activity data Enumeration Objects for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 1; M	
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the unassociated state.		
Test procedure	<ol style="list-style-type: none"> 1. Record for later comparison the number of sensors of every type. 2. The simulated manager receives an association request from the agent under test. 3. The simulated manager responds with a result = accepted-unknown-config. 4. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 5. Check that for every sensor there is one object of the appropriate type. 		
Pass/Fail criteria	All checked values are as specified in the test procedure.		
Notes			

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_B			
TP label	Get activity data fall sensor Enumeration Object attributes			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		FallSensor 1; M	FallSensor 2; O	FallSensor 3; M
		FallSensor 4; M	FallSensor 5; M	FallSensor X; M

Applicability	C_AG_OXP_176 AND C_AG_HUB_021 AND C_AG_OXP_181 AND C_AG_OXP_000
Initial condition	The simulated manager and the agent under test are in the configuring state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data fall sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_FALL b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 2. Simulate a fall in each fall sensor with the agent under test. 3. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value: <ul style="list-style-type: none"> ▪ fall-detected(0) bit must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_C			
TP label	Get activity data PERS sensor Enumeration Object attributes			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		PERSSensor 1; M	PERSSensor 2; O	PERSSensor3; M
PERSSensor4; M	PERSSensor5; M	PERSSensorX; M		

Applicability	C_AG_OXP_176 AND C_AG_HUB_022 AND C_AG_OXP_181 AND C_AG_OXP_000
Initial condition	The simulated manager and the agent under test are in the configuring state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager: 4. The Data PERS sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_PERS b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate an emergency with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value= <ul style="list-style-type: none"> ▪ Bit 0 (pers-activated(0)) must be set.
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_D		
TP label	Get activity data environmental sensor Enumeration Object attributes for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 2; M	EnumObj 3; M
		EnumObj 4; M	
		EnumObj 5; R	EnumObj 6; R
		EnumObj 7; R	
		EnumObj 8; R	EnumObj 9; R
		EnumObj 10; R	
		EnumObj 11; R	EnumObj 13; O
		EnumObj 14; O	
		EnumObj 15; R	EnumObj 16; R
		EnumObj 17; M	
		EnumObj 18; R	EnumObj 19; R
		EnumObj 20; R	
		EnumObj 21; R	EnumObj 22; M
		EnumObj 23; O	
		EnvironSensor 1; M	EnvironSensor 2; O
		EnvironSensor 3; M	
		EnvironSensor 4; M	EnvironSensor 5; M
		EnvironSensor X; M	

Applicability	C_AG_OXP_176 AND C_AG_HUB_023 AND C_AG_OXP_181 AND C_AG_OXP_000
Initial condition	The simulated manager and the agent under test are in the configuring state.
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data environmental sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_SMOKE or MDC_AI_TYPE_SENSOR_CO or MDC_AI_TYPE_SENSOR_WATER or MDC_AI_TYPE_SENSOR_GAS b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate an environmental change with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 0 (condition-detected(0)) must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_E			
TP label	Get activity data motion sensor Enumeration Object attributes for Activity Hub			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		MotionSensor 1; M	MotionSensor 2; O	MotionSensor3; M

		MotionSensor4; M	MotionSensor5; M	MotionSensorX; M
Applicability	C_AG_OXP_176 AND C_AG_HUB_024 AND C_AG_OXP_181 AND C_AG_OXP_000			
Initial condition	The simulated manager and the agent under test are in the configuring state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager: 4. The Data motion sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_MOTION b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate a motion with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value= Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ motion-detected(0) ▪ motion-detected-delayed(1) ▪ tamper-detected(2) 			
Pass/Fail criteria	All checked values are as specified in the test procedure.			
Notes				

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_F			
TP label	Get activity data property exit sensor Enumeration Object attributes for Activity Hub			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O

		PropExitSensor3; M	PropExitSensor4; M	PropExitSensor 1; M
		PropExitSensor 2; O	PropExitSensor5; M	PropExitSensorX; M
Applicability	C_AG_OXP_176 AND C_AG_HUB_025 AND C_AG_OXP_181 AND C_AG_OXP_000			
Initial condition	The simulated manager and the agent under test are in the configuring state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data exit sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_PROPEXIT a. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate a property exit with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value= Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ occupant-exit-property(0) ▪ exit-door-left-open(1) 			
Pass/Fail criteria	All checked values are as specified in the test procedure.			
Notes				

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_G			
TP label	Get activity data property enuresis sensor Enumeration Object attributes for Activity Hub			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R

		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		EnurSensor 1; M	EnurSensor 2; O	EnurSensor3; M
		EnurSensor4; M	EnurSensor5; M	EnurSensorX; M
Applicability	C_AG_OXP_176 AND C_AG_HUB_026 AND C_AG_OXP_181 AND C_AG_OXP_000			
Initial condition	The simulated manager and the agent under test are in the configuring state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager: 4. The Data enuresis sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_ENURESIS b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate an enuresis with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value= Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ enuresis-detected(0) 			
Pass/Fail criteria	All checked values are as specified in the test procedure.			
Notes				

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_H			
TP label	Get activity data property contact closure sensor Enumeration Object attributes for Activity Hub			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R

		EnumObj 21; R	EnumObj 23; O	EnumObj 22; M
		ContactSensor 1; M	ContactSensor 2; O	ContactSensor 3; M
		ContactSensor 4; M	ContactSensor 5; M	ContactSensor X; M
Applicability	C_AG_OXP_176 AND C_AG_HUB_027 AND C_AG_OXP_181 AND C_AG_OXP_000			
Initial condition	The simulated manager and the agent under test are in the configuring state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data contact/closure sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_CONTACTCLOSURE b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate a contact closure sensor activation with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ contact-opened(0) ▪ contact-opened(1) 			
Pass/Fail criteria	All checked values are as specified in the test procedure.			
Notes				

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_I			
TP label	Get activity data property usage sensor Enumeration Object attributes for Activity Hub			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M

		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		UsageSensor 1; O	UsageSensor 2; M	UsageSensor 3; O
		UsageSensor 4; M	UsageSensor 5; M	UsageSensor 6; M
		UsageSensor X; M		
Applicability	C_AG_OXP_176 AND C_AG_HUB_028 AND C_AG_OXP_181 AND C_AG_OXP_000			
Initial condition	The simulated manager and the agent under test are in the configuring state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data usage sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_USAGE b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate an usage sensor activation with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ usage-started(0) ▪ usage-started(1) ▪ usage-started(2) ▪ usage-started(3) ▪ usage-started(4) 			
Pass/Fail criteria	All checked values are as specified in the test procedure.			
Notes				

TP Id	TP/PLT/AG/CLASS/HUB/BV-005_J		
TP label	Get activity data switch sensor Enumeration Object attributes for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable	EnumObj 2; M	EnumObj 3; M
			EnumObj 4; M

	items	EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 23; O	EnumObj 22; M
		SwitchSensor 1; M	SwitchSensor 2; O	SwitchSensor 3; M
		SwitchSensor 4; M	SwitchSensor 5; M	SwitchSensor X; M
Applicability		C_AG_OXP_176 AND C_AG_HUB_029 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the configuring state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager: 4. The Data switch sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_SWITCH b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate a switch-on or switch-off with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ switch-on(0) ▪ switch-off(1) 		
Pass/Fail criteria		All checked values are as specified in the test procedure.		
Notes				

TP Id		TP/PLT/AG/CLASS/HUB/BV-005_K		
TP label		Get activity data dosage sensor Enumeration Object attributes for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		DosageSensor 1; M	DosageSensor 2; O	DosageSensor 3; M
		DosageSensor 4; M	DosageSensor 5; M	DosageSensor X; M
Applicability		C_AG_OXP_176 AND C_AG_HUB_030 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the configuring state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data dosage sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_DOSAGE b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate a valid dose or missed dose with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = = Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ dosage-taken(0) ▪ dosage-taken(1) 		
Pass/Fail criteria		All checked values are as specified in the test procedure.		
Notes				

TP Id		TP/PLT/AG/CLASS/HUB/BV-005_L		
TP label		Get activity data temperature sensor Enumeration Object attributes for Activity Hub		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 2; M	EnumObj 3; M	EnumObj 4; M
		EnumObj 5; R	EnumObj 6; R	EnumObj 7; R
		EnumObj 8; R	EnumObj 9; R	EnumObj 10; R
		EnumObj 11; R	EnumObj 13; O	EnumObj 14; O
		EnumObj 15; R	EnumObj 16; R	EnumObj 17; M
		EnumObj 18; R	EnumObj 19; R	EnumObj 20; R
		EnumObj 21; R	EnumObj 22; M	EnumObj 23; O
		TempSensor 1; M	TempSensor 2; O	TempSensor3; M
		TempSensor4; M	TempSensor5; M	TempSensorX; M
Applicability		C_AG_OXP_176 AND C_AG_HUB_031 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the configuring state.		
Test procedure		<ol style="list-style-type: none"> 1. The simulated manager receives an association request from the agent under test. 2. The simulated manager responds with a result = accepted-unknown-config. 3. The agent responds with a "Remote Operation Invoke Confirmed Event Report" message with an MDC_NOTI_CONFIG event to send its configuration to the manager. 4. The Data temperature sensor object must be: <ol style="list-style-type: none"> a. Mandatory attribute Type <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_ID_TYPE <input type="checkbox"/> attribute-type = TYPE <input type="checkbox"/> attribute-value = MDC_AI_TYPE_SENSOR_TEMP b. Mandatory attribute Absolute-Time-Stamp <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id = MDC_ATTR_TIME_STAMP_ABS <input type="checkbox"/> attribute-type = AbsoluteTime <input type="checkbox"/> attribute-value.length = 8 bytes 5. Simulate a change of temperature with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ high-temperature-detected(0) ▪ high-temperature-detected(1) ▪ high-temperature-detected(2) 		

Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id		TP/PLT/AG/CLASS/HUB/BV-006_A		
TP label		Semantic of activity data property exit sensor.		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	PropExitSensor5;M		
Applicability		C_AG_OXP_176 AND C_AG_HUB_025 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the operating state.		
Test procedure		<ol style="list-style-type: none"> 1. Simulate a property exit with the agent under test. 2. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> b. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value= Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ occupant-exit-properly(0) 7. Simulate an exit that leaves open the door with the agent under test. 8. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value= Only one of the following bits can be set: <ul style="list-style-type: none"> ▪ exit-door-left-open(1) 		
Pass/Fail criteria		All checked values are as specified in the test procedure.		
Notes				

TP Id		TP/PLT/AG/CLASS/HUB/BV-006_B		
TP label		Semantic of activity data property contact closure sensor.		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	ContactSensor5;M		
Applicability		C_AG_OXP_176 AND C_AG_HUB_027 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the operating state.		

Test procedure	<ol style="list-style-type: none"> 1. Simulate an opening with the agent under test. 2. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = contact-opened(0) 3. Simulate a closing with the agent under test. 4. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = contact-closed(1)
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-006_C		
TP label	Semantic of activity data property usage sensor.		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	UsageSensor6;M	
Applicability	C_AG_OXP_176 AND C_AG_HUB_028 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Simulate a correct start of usage with the agent under test. 2. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = usage-started(0) 3. Simulate a correct ending of usage with the agent under test. 4. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = usage-ended(1) 5. Simulate an incorrect start of usage with the agent under test. 6. Wait for the simulated manager to receive the event report: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str 		

	<ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = expected-use-start-violation(2) <p>7. Simulate an incorrect ending of usage with the agent under test.</p> <p>8. Wait for the simulated manager to receive the event report:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = expected-use-stop-violation(3) <p>9. Simulate a correct start of usage with the agent under test.</p> <p>10. Do not end it.</p> <p>11. Wait for the simulated manager to receive the event report:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = absence-violation(4)
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-006_D		
TP label	Semantic of activity data switch sensor.		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	SwitchSensor5;M	
Applicability	C_AG_OXP_176 AND C_AG_HUB_029 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<p>1. Simulate a switch-on with the agent under test.</p> <p>2. Wait for the simulated manager to receive the event report:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = switch-on(0) <p>3. Simulate a switch-off with the agent under test.</p> <p>4. Wait for the simulated manager to receive the event report:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 		

	<input type="checkbox"/> attribute-value.length = 4 bytes attribute-value = switch-off(1)
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-006_E		
TP label	Semantic of activity data dosage sensor.		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	DosageSensor5;M	
Applicability	C_AG_OXP_176 AND C_AG_HUB_030 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	1. Simulate a valid dose with the agent under test. 2. Wait for the simulated manager to receive the event report: <ul style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = dosage-taken(0) 3. Simulate a missed dose with the agent under test. 4. Wait for the simulated manager to receive the event report: <ul style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = dosage-missed(1) 		
Pass/Fail criteria	All checked values are as specified in the test procedure.		
Notes			

TP Id	TP/PLT/AG/CLASS/HUB/BV-006_F		
TP label	Semantic of activity data temperature sensor.		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	TempSensor5;M	
Applicability	C_AG_OXP_176 AND C_AG_HUB_031 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	1. Simulate high temperature with the agent under test. 2. Wait for the simulated manager to receive the event report:		

	<ul style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = high-temperature-detected(0) 3. Simulate a low temperature with the agent under test. 4. Wait for the simulated manager to receive the event report: <ul style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = low-temperature-detected(1) 5. Simulate a fast changing of temperatures with the agent under test. 6. Wait for the simulated manager to receive the event report: <ul style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = rate-of-change-too-fast(2)
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-008			
TP label	Association Activity Hub Agent			
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	MDSMethod 6; M	AssocRqt1; M	AssocRqt2; M
		AssocRqt3; M	AssocRqt4; M	AssocRqt5; M
		AssocRqt6; M	AssocRqt7; M	AssocRqt8; M
		AssocRqt9; M	AssocRqt11; M	AssocRqt12; M
		AssocRqt13; M		
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000			
Initial condition	The simulated manager and the agent under test are in the unassociated state.			
Test procedure	1. The agent sends a message to associate to the simulated manager, the expected fields sent by the agent are: <ul style="list-style-type: none"> a. APDU Type <ul style="list-style-type: none"> <input type="checkbox"/> field- type = AarqApdu <input type="checkbox"/> field-length =2 bytes <input type="checkbox"/> field-value =0xE2 0x00. 			

- b. assoc-version
 - field- type = AssociationVersion
 - field-length =BITS-32
 - field- value=0x80 0x00 0x00 0x00
- c. data-proto-id
 - field- type = DataProtold(INT-U16)
 - field-length =2 bytes
 - field- value=0x50 0x79 (20601)
- d. protocol-version
 - field- type = Protocol Version
 - field-length = 4 bytes
 - field- value=0x80 0x00 0x00 0x00
- e. encoding rules
 - field- type = EncodingRules
 - field-length = 2 bytes
 - field- value=
 - Bit 0 must be set (support MDER)
 - Bits 1 and 2 may be set
 - The rest of the bits must be 0
- f. nomenclature version
 - field- type = NomenclatureVersion
 - field-length = 4 bytes
 - field- value=0x80 0x00 0x00 0x00
 - This value indicates version1 is supported (nom-version1(0) is set).
- g. functional–units
 - field- type = FunctionalUnits
 - field-length = 4 bytes
 - field-value =
 - Bit 0 must not be set
- h. System type
 - field- type = SystemType
 - field-length = 4 bytes
 - field- value = 0x00 0x80 0x00 0x00 (sys-type-agent)
- i. System-Id
 - field- type = OCTET STRING
 - field-length = 8 bytes
 - field- value = 0xXX 0xXX 0xXX 0xXX 0xXX 0xXX 0xXX 0xXX (octet string length = 8 | UI-64 manufacturer and device)
 - This value will be System Id attribute of MDS object.
- j. dev-config-id
 - field- type = ConfigId(INT-U16)
 - field-length = 2 bytes
 - field- value =
 - <between 0x40 0x00 and 0x7F 0xFF > for extended configuration.

	<p>k. data-req-mode-flags (DataReqModeCapab)</p> <ul style="list-style-type: none"> <input type="checkbox"/> field- type = DataReqModeFlags <input type="checkbox"/> field-length = 2 bytes <input type="checkbox"/> If the Agent supports Agent-initiated measurement transfer → Bit 15 is set (data-req-supp-init-agent(15)) <input type="checkbox"/> If the agent supports requesting objects based on the object handle →Bit 6 will be set (data-req-supp-scope-handle(6)). <input type="checkbox"/> If the agent supports single response →Bit 8 will be set (data-req-supp-mode-single-rsp(8)). <input type="checkbox"/> If the agent supports time unlimited data request →Bit 10 will be set (data-req-supp-mode-time-no-limit(10)). <p>l. data-req-init-agent-count (DataReqModeCapab)</p> <ul style="list-style-type: none"> <input type="checkbox"/> field- type = INT-U8 <input type="checkbox"/> field-length = 2 bytes <input type="checkbox"/> field.value = 0x01 <p>m. data-req-init-manager-count (DataReqModeCapab)</p> <ul style="list-style-type: none"> <input type="checkbox"/> field- type = INT-U8 <input type="checkbox"/> field-length = 2 bytes <input type="checkbox"/> field.value = 0x00
Pass/Fail criteria	All checked attributes have proper values.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_A		
TP label	Activity data Fall sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	FallSensor 5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the Operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Trigger a fall sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ IF C_AG_HUB_033 = TRUE, then <ul style="list-style-type: none"> • Bit 16 (auto-presence-received) must be set • Bit 17 (auto-presence-failed) must not be set ▪ IF C_AG_HUB_033 = FALSE, then <ul style="list-style-type: none"> • Bit 16 (auto-presence-received) must not be set • Bit 17 (auto-presence-failed) must not be set 		

	<p>3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager.</p> <p>4. IF C_AG_HUB_033 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_B		
TP label	Activity data PERS sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	PERSSensor5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<p>1. Trigger a PERS sensor supported by the agent under test.</p> <p>2. Wait for the event report, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_035 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_035 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set <p>3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager.</p> <p>4. IF C_AG_HUB_035 = TRUE: Disable or disconnect the sensor (as defined by vendor) and wait again the specified time. In that time an event report must be received by the simulated manager, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 		

	<ul style="list-style-type: none"> <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_C		
TP label	Activity data Environmental sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	EnvironSensor5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Trigger an Environmental sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_036 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_036 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set 3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager. 4. IF C_AG_HUB_036 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set 		
Pass/Fail criteria	All checked values are as specified in the test procedure.		
Notes			

TP Id		TP/PLT/AG/CLASS/HUB/BV-009_D		
TP label		Activity data Motion sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 24; C	MotionSensor5;M	
Applicability		C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the operating state.		
Test procedure		<ol style="list-style-type: none"> 1. Trigger a Motion sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_037 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_037 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set 3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager. 4. IF C_AG_HUB_037 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set 		
Pass/Fail criteria		All checked values are as specified in the test procedure.		
Notes				

TP Id		TP/PLT/AG/CLASS/HUB/BV-009_E		
TP label		Activity data Property Exit sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 24; C	PropExitSensor5;M	

Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Trigger a Property Exit sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_038 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_038 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set 3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager. 4. IF C_AG_HUB_038 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set 		
Pass/Fail criteria	All checked values are as specified in the test procedure.		
Notes			

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_F		
TP label	Activity data Enuresis sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	EnurSensor5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Trigger an Enuresis sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR 		

	<ul style="list-style-type: none"> <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_039 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_039 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set <p>3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager.</p> <p>4. IF C_AG_HUB_039 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_G		
TP label	Activity data Contact Closure sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	ContactSensor5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<p>1. Trigger a Contact Closure sensor supported by the agent under test.</p> <p>2. Wait for the event report, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_040 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_040 = FALSE, then 		

	<ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set <p>3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager.</p> <p>4. IF C_AG_HUB_040 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_H		
TP label	Activity data Usage sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	UsageSensor6;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<p>1. Trigger a Usage sensor supported by the agent under test.</p> <p>2. Wait for the event report, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p> <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_041 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_041 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set <p>3. Wait the time specified by vendor. In that time an event report must be received by the simulated manager.</p> <p>4. IF C_AG_HUB_041 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute:</p> <p>a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str</p>		

	<ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set
Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_I		
TP label	Activity data Switch sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	SwitchSensor5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Trigger a Switch sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_042 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_042 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set 3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager. 4. IF C_AG_HUB_042 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set 		

Pass/Fail criteria	All checked values are as specified in the test procedure.
Notes	

TP Id	TP/PLT/AG/CLASS/HUB/BV-009_J		
TP label	Activity data Dosage sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]	
	Testable items	EnumObj 24; C	DosageSensor5;M
Applicability	C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition	The simulated manager and the agent under test are in the operating state.		
Test procedure	<ol style="list-style-type: none"> 1. Trigger a Dosage sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_043 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_043 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set 3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager. 4. IF C_AG_HUB_043 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set 		
Pass/Fail criteria	All checked values are as specified in the test procedure.		
Notes			

TP Id		TP/PLT/AG/CLASS/HUB/BV-009_K		
TP label		Activity data Temperature sensor Enumeration Object. Heartbeat Operational Status		
Coverage	Spec	[ISO/IEEE 11073-10471]		
	Testable items	EnumObj 24; C	TempSensor5;M	
Applicability		C_AG_OXP_176 AND C_AG_OXP_181 AND C_AG_OXP_000		
Initial condition		The simulated manager and the agent under test are in the operating state.		
Test procedure		<ol style="list-style-type: none"> 1. Trigger a temperature sensor supported by the agent under test. 2. Wait for the event report, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> <input type="checkbox"/> IF C_AG_HUB_044 = TRUE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must be set ▪ Bit 17 (auto-presence-failed) must not be set <input type="checkbox"/> IF C_AG_HUB_044 = FALSE, then <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must not be set 3. Wait the time specified by the vendor. In that time an event report must be received by the simulated manager. 4. IF C_AG_HUB_044 = TRUE: Disable or disconnect the sensor (as defined by the vendor) and again wait the specified time. In that time an event report must be received by the simulated manager, check the following attribute: <ol style="list-style-type: none"> a. Mandatory attribute Enum-Observed-Value-Simple-Bit-Str <ul style="list-style-type: none"> <input type="checkbox"/> attribute-id= MDC_ATTR_ENUM_OBS_VAL_SIM_BIT_STR <input type="checkbox"/> attribute-type = BITS-32 <input type="checkbox"/> attribute-value.length = 4 bytes <input type="checkbox"/> attribute-value = <ul style="list-style-type: none"> ▪ Bit 16 (auto-presence-received) must not be set ▪ Bit 17 (auto-presence-failed) must be set 		
Pass/Fail criteria		All checked values are as specified in the test procedure.		
Notes				

TP Id		TP/PLT/AG/CLASS/HUB/BV-010		
TP label		Operating State. Manager to Agent Maximum APDU Size		
Coverage	Spec	[ISO/IEEE 11073-20601A]		
	Testable items	CommonCharac 3; M		
	Spec	[ISO/IEEE 11073-10471]		

	Testable items	ComCharac2; M		
Applicability	C_AG_OXP_000 AND C_AG_OXP_176			
Initial condition	The simulated manager and the agent are in the operating state.			
Test procedure	<ol style="list-style-type: none"> 1. The simulated manager issues a "Remote Operation Invoke Get" command with: <ol style="list-style-type: none"> a. Obj-handle set to 0 (to request for MDS object) b. attribute-id-list.count = 103 c. attribute-id-list: (MDC_ATTR_ID_MODEL, MDC_ATTR_SYS_ID, MDC_ATTR_DEV_CONFIG_ID) repeated 34 times followed by an additional MDC_ATTR_ID_MODEL 2. Check the response of the agent. 3. The simulated manager issues a "Remote Operation Invoke Get" command with the handle set to 0 (to request for an MDS object) and an empty attribute-id-list to indicate all attributes. 4. Check the response of the agent 			
Pass/Fail criteria	<ul style="list-style-type: none"> • In step 2, the agent under test may respond with a rors-cmip-get listing all the requested attributes, or with a roer message. If PICS C_AG_OXP_100 =TRUE and the agent does not respond with a rors-cmip-get message, it responds with a roer message or rorj(resource-limitation) message, a WARNING will appear. <ul style="list-style-type: none"> ○ If the response is a get response, the total size of the response cannot exceed the sum of the APDU sizes of the supported specializations (limited to an absolute limit of 64512 octets): <ul style="list-style-type: none"> ▪ Pulse oximeter -> 9216 octets ▪ Weighing scales -> 896 octets ▪ Glucose meter -> 5120 octets or 64512 octets if the agent supports PM-Store ▪ Blood pressure -> 896 octets ▪ Thermometer -> 896 octets ▪ Independent activity hub -> 5120 octets ▪ Cardiovascular -> 64512 octets or 6624 octets if the agent under test only supports Step Counter Profile ▪ Strength -> 64512 octets: ▪ Adherence monitor -> 1024 octets ▪ Peak Flow -> 2030 octets ▪ Body composition analyser -> 7730 octets ▪ Basic ECG/Simple ECG -> 7168 octets or 64512 octets if the agent supports PM-Store ▪ Basic ECG/Heart Rate -> 1280 octets or 64512 octets if the agent supports PM-Store ▪ International normalized ratio -> 896 octets or 64512 if the agent supports PM-Store ○ In the case where it responds with a roer, the reason must not be protocol-violation (23) • In step 4, the agent must respond with a rors-cmip-get message. 			
Notes				

Bibliography

- [b-CDG 1.0] Continua Health Alliance, Continua Design Guidelines v1.0 (2008), *Continua Design Guidelines*.
- [b-CDG 2010] Continua Health Alliance, Continua Design Guidelines v1.5 (2010), *Continua Design Guidelines*.
- [b-CDG 2011] Continua Health Alliance, Continua Design Guidelines (2011), "Adrenaline", *Continua Design Guidelines*.
- [b-CDG 2012] Continua Health Alliance CDG, Continua Design Guidelines (2012), "Catalyst", *Continua Design Guidelines*.
- [b-ETSI SR 001 262] ETSI SR 001 262 v1.8.1 (2003-12): *ETSI drafting rules*.

SERIES OF ITU-T RECOMMENDATIONS

Series A	Organization of the work of ITU-T
Series D	General tariff principles
Series E	Overall network operation, telephone service, service operation and human factors
Series F	Non-telephone telecommunication services
Series G	Transmission systems and media, digital systems and networks
Series H	Audiovisual and multimedia systems
Series I	Integrated services digital network
Series J	Cable networks and transmission of television, sound programme and other multimedia signals
Series K	Protection against interference
Series L	Construction, installation and protection of cables and other elements of outside plant
Series M	Telecommunication management, including TMN and network maintenance
Series N	Maintenance: international sound programme and television transmission circuits
Series O	Specifications of measuring equipment
Series P	Terminals and subjective and objective assessment methods
Series Q	Switching and signalling
Series R	Telegraph transmission
Series S	Telegraph services terminal equipment
Series T	Terminals for telematic services
Series U	Telegraph switching
Series V	Data communication over the telephone network
Series X	Data networks, open system communications and security
Series Y	Global information infrastructure, Internet protocol aspects and next-generation networks
Series Z	Languages and general software aspects for telecommunication systems