

## RECOMMENDATION ITU-R BT.1366-1

**Transmission of time code and control code in the ancillary data space  
of a digital television stream according to ITU-R BT.656\*,  
ITU-R BT.799\*\* and ITU-R BT.1120\*\*\***

(Question ITU-R 42/6)

(1998-2007)

**Scope**

This Recommendation defines a transmission format for conveyance of linear (LTC) or vertical interval (VITC) time code data formatted according to Recommendation ITU-R BR.780-2 in 8- or 10-bit digital television data interfaces according to Recommendations ITU-R BT.656, ITU-R BT.799 and ITU-R BT.1120.

The ITU Radiocommunication Assembly,

*considering*

- a) that the use of time-code signals is well-established in the area of post-production;
- b) that many countries are installing digital television production facilities based on the use of digital video components conforming to Recommendations ITU-R BT.601, ITU-R BT.656, or ITU-R BT.1120;
- c) that there exists the capacity within a signal conforming to Recommendations ITU-R BT.656, ITU-R BT.799 and ITU-R BT.1120 for additional data signals to be multiplexed with the video data signal;
- d) that there are operational and economic benefits to be achieved by the multiplexing of ancillary data signals with the video data signal;
- e) that the operational benefits are increased if a minimum of different formats are used for ancillary data signals;
- f) that the exchange of programme material between and within organizations is facilitated if a common format of time-code signal is used;
- g) that extension of the capacity of the time-code signal to carry additional information is desirable,

*recommends*

**1** that the time-code ancillary data signal format described in Annex 1 to this Recommendation should be used for the interfaces defined in ITU-R BT.656, ITU-R BT.799 and ITU-R BT.1120.

---

\* Recommendation ITU-R BT.656 – Interface for digital component video signals in 525-line and 625-line television systems operating at the 4:2:2 level of Recommendation ITU-R BT.601.

\*\* Recommendation ITU-R BT.799 – Interface for digital component video signals in 525-line and 625-line television systems operating at the 4:4:4 level of Recommendation ITU-R BT.601.

\*\*\* Recommendation ITU-R BT.1120 – Digital interfaces for HDTV studio signals.

## Annex 1

### 1 Introduction

Time code information is transmitted in the ancillary data space as defined in Recommendation ITU-R BT.1364. Multiple codes can be transmitted within a single digital video data stream. Other time information, such as real time clock, DTTR tape timer information, and other user-defined information, may also be carried in the ancillary time code packet instead of time code. The actual information transmitted through the interface is identified by the coding of a distributed binary bit.

### 2 Normative references

The Recommendations indicated below contain provisions which, through reference in this text, constitute provisions of this Recommendation. All standards and Recommendations are subject to revision, and parties to agreements based on this practice are encouraged to investigate the possibility of applying the most recent edition of the standards and Recommendations indicated below.

Recommendation ITU-R BR.780-2 – Time and control code standards, for production applications in order to facilitate the international exchange of television programmes on magnetic tapes.

Recommendation ITU-R BT.1364 – Format of ancillary data signals carried in digital component studio interfaces.

### 3 Ancillary time code format

**3.1** One ancillary data packet of constant length excluding ancillary data flag shall fully represent an ancillary time code (ATC) word.

**3.2** The ancillary time code packet shall be type 2, having a data identification (DID) and a secondary data identification (SDID). The DID and SDID shall be set to:

$$\text{DID} = 60\text{h}$$

$$\text{SDID} = 60\text{h}$$

**3.3** The data count value for ancillary time code shall be set to:

$$\text{DC} = 10\text{h}$$

### 4 Format of user data words in ancillary time code packet

**4.1** All user data words in the ancillary time code packets are formatted as shown in Table 1.

NOTE 1 – References to user data word (UDW) bits in this Recommendation are for a 10-bit UDW word. Correspondence between an 8-bit word and a 10-bit word is shown in Table 1.

TABLE 1  
User data words format

| UDW <sub>10</sub> bit<br>(10-bit words) | UDW <sub>8</sub> bit<br>(8-bit words) | Assignment  |
|---|---------------------------------------|---|
| b0 (LSB)                                | N/A                                   | Set to "0" in 10-bit words. N/A in 8-bit words            |
| b1                                      | N/A                                   | Set to "0" in 10-bit words. N/A in 8-bit words            |
| b2                                      | b0                                    | Set to "0" in 10-bit and 8-bit words                      |
| b3                                      | b1                                    | Distributed binary bit (DBB)                              |
| b4                                      | b2                                    | ANC binary group LSB                                      |
| b5                                      | b3                                    | ANC binary group  |
| b6                                      | b4                                    | ANC binary group  |
| b7                                      | b5                                    | ANC binary group MSB                                      |
| b8                                      | b6                                    | Even parity for data contained in UDW bit 7 through bit 0 |
| b9 (MSB)                                | b7                                    | Not bit 8   |

**4.1.1** Bit b7 through bit b3 of the UDW<sub>10-1</sub> through UDW<sub>10-16</sub> shall contain the time code information and additional information as per Recommendation ITU-R BR.780-2.

**4.2** Bit b3 of the UDW<sub>10-1</sub> through UDW<sub>10-16</sub> form two groups of distributed binary bits DBB 1 and DBB 2 (see Table 3).

**4.2.1** The first group of distributed binary bits (DBB 1) is formed by bit 3 of UDW<sub>10-1</sub> through UDW<sub>10-8</sub>, where UDW<sub>10-1</sub> (b3) represents the LSB and UDW<sub>10-8</sub> (b3) represents the MSB.

**4.2.2** The second group of distributed binary bits (DBB 2) is formed by bit 3 of UDW<sub>10-9</sub> through UDW<sub>10-16</sub>, where UDW<sub>10-9</sub> (b3) represents the LSB and UDW<sub>10-16</sub> (b3) represents the MSB.

**4.3** Bits b7 through b4 form an ancillary binary group into which the time code is mapped. Bits b4 of the UDW<sub>10</sub> represents the LSB of this group.

**4.4** Information coded in the distributed binary bit group is defined in Table 3.

**4.4.1** Bits b4 through b0 of the distributed binary bit group DBB 2 convey VITC line number location indicating the position of VITC data on the output digital video signal interface within the vertical blanking interval. The line select number depends on the television system and shall be constrained to a range as shown in Table 2.

TABLE 2  
Line select number

| DBB 2<br>bits b4 through b0 |    |    |    |    | VITC line select  |                                |                   |                                |
|-----------------------------|----|----|----|----|-------------------|--------------------------------|-------------------|--------------------------------|
|                             |    |    |    |    | 525/60            |                                | 625/50            |                                |
|                             |    |    |    |    | bit b5 = x        | bit b5 = 1                     | bit b5 = x        | bit b5 = 1                     |
| b4                          | b3 | b2 | b1 | b0 | VITC<br>on line N | Repeated VITC<br>on line (N+2) | VITC<br>on line N | Repeated VITC<br>on line (N+2) |
|                             |    |    |    |    | field 1/field 2   | field 1/field 2                | field 1/field 2   | field 1/field 2                |
| 0                           | 0  | 1  | 1  | 0  | -                 | -                              | 6/319             | 8/321                          |
| 0                           | 0  | 1  | 1  | 1  | -                 | -                              | 7/320             | 9/322                          |
| 0                           | 1  | 0  | 0  | 0  | -                 | -                              | 8/321             | 10/323                         |
| 0                           | 1  | 0  | 0  | 1  | -                 | -                              | 9/322             | 11/324                         |
| 0                           | 1  | 0  | 1  | 0  | 10/273            | 12/275                         | 10/323            | 12/325                         |
| 0                           | 1  | 0  | 1  | 1  | 11/274            | 13/276                         | 11/324            | 13/326                         |
| 0                           | 1  | 1  | 0  | 0  | 12/275            | 14/277                         | 12/325            | 14/327                         |
| 0                           | 1  | 1  | 0  | 1  | 13/276            | 15/278                         | 13/326            | 15/328                         |
| 0                           | 1  | 1  | 1  | 0  | 14/277            | 16/279                         | 14/327            | 16/329                         |
| 0                           | 1  | 1  | 1  | 1  | 15/278            | 17/280                         | 15/328            | 17/330                         |
| 1                           | 0  | 0  | 0  | 0  | 16/279            | 18/281                         | 16/329            | 18/331                         |
| 1                           | 0  | 0  | 0  | 1  | 17/280            | 19/282                         | 17/330            | 19/332                         |
| 1                           | 0  | 0  | 1  | 0  | 18/281            | 20/283                         | 18/331            | 20/333                         |
| 1                           | 0  | 0  | 1  | 1  | 19/282            | -                              | 19/332            | 21/334                         |
| 1                           | 0  | 1  | 0  | 0  | 20/283            | -                              | 20/333            | 22/335                         |
| 1                           | 0  | 1  | 0  | 1  | -                 | -                              | 21/334            | -                              |
| 1                           | 0  | 1  | 1  | 0  | -                 | -                              | 22/335            | -                              |

NOTE – x = irrelevant.

**4.4.2** Bit b5 of DBB 2 when set to “1” shall signify that the VITC word carried in the ancillary time code word, when converted to an analogue video output signal, shall be inserted on the selected line number and shall be repeated again on the selected line number +2 (see Table 2, bit b5 = 1).

**4.4.3** Bits b7 and b6 of the DBB 2 word represent different time code condition bits (see Table 3). Data errors indicated by the error detection system of the received time code signal at the input receiving interface to the ancillary time code formatter and the type of processing of receiving user bits shall be signalled by these bits in the transmitted ATC word. The coding of these two bits is shown in Table 4.

**4.5** Mapping of the time code data into the UDW 1 through UDW 16 of the ancillary time code data packet is shown in Table 5.

TABLE 3  
Distributed binary bit group coding

| DBB group | Bit 3 of UDW  | Distributed binary bit (DBB) |               | Definition  |
|-----------|---|------------------------------|---------------|---|
|           |   | MSB                          | LSB           |   |
| DBB 1     | UDW <sub>10-1</sub><br>through<br>UDW <sub>10-8</sub> | 0                            | 0 0 0 0 0 0 0 | Longitudinal time code                                      |
|           |   | 0                            | 0 0 0 0 0 0 1 | Vertical interval time code #1                              |
|           |   | 0                            | 0 0 0 0 0 1 0 | Vertical interval time code #2                              |
|           |   | 0                            | 0 0 0 0 0 1 1 | User defined  |
|           |   | 0                            | 0 0 0 0 1 1 1 |   |
|           |   | 0                            | 0 0 0 0 1 0 0 | Locally generated time address and user data (user defined) |
|           |   | 0                            | 0 1 1 1 1 1 1 |   |
| 1         | 0 0 0 0 0 0 0   | Reserved                     |               |   |
| 1         | 1 1 1 1 1 1 1   |                              |               |   |
| DBB 2     | UDW <sub>10-9</sub>                                   |                              | b0            | VITC line select (LSB) (Note)                               |
|           | UDW <sub>10-10</sub>                                  |                              | b1            | VITC line select (Note)                                     |
|           | UDW <sub>10-11</sub>                                  |                              | b2            | VITC line select (Note)                                     |
|           | UDW <sub>10-12</sub>                                  |                              | b3            | VITC line select (Note)                                     |
|           | UDW <sub>10-13</sub>                                  |                              | b4            | VITC line select (MSB) (Note)                               |
|           | UDW <sub>10-14</sub>                                  |                              | b5            | VITC line duplication (Note)                                |
|           | UDW <sub>10-15</sub>                                  |                              | b6            | Time code validity  |
|           | UDW <sub>10-16</sub>                                  |                              | b7            | (User bits) process bit                                     |

NOTE – These bits are not used in interfaces which are in accordance with Recommendation ITU-R BT.1120.

TABLE 4  
Coding of validity and process bits

| VITC validity bit (b6) and process bit (b7) | Definition   |
|---|--|
| b6 = 0                                      | No time code error received or locally generated time code address                                 |
| b6 = 1                                      | Transmitted time code interpolated from previous time code (received a time code error)            |
| b7 = 0                                      | Binary group of user bits in time code data stream are processed to compensate for latency         |
| b7 = 1                                      | Binary groups of user bits in time code data stream are only retransmitted (no delay compensation) |

TABLE 5  
Mapping of time code data into UDW

| UDW |    | Time code bit | Time code definitions<br>(as per Rec. ITU-R BR.780-2) |
|-----|----|---------------|---|
| 1   | b4 | 0             | Units of frames 1                                     |
|     | b5 | 1             | Units of frames 2                                     |
|     | b6 | 2             | Units of frames 4                                     |
|     | b7 | 3             | Units of frames 8                                     |
| 2   | b4 | 4             | LSB binary group 1                                    |
|     | b5 | 5             | xxx binary group 1                                    |
|     | b6 | 6             | xxx binary group 1                                    |
|     | b7 | 7             | MSB binary group 1                                    |
| 3   | b4 | 8             | Tens of frames 10                                     |
|     | b5 | 9             | Tens of frames 20                                     |
|     | b6 | 10            | Flag  |
|     | b7 | 11            | Flag  |
| 4   | b4 | 12            | LSB binary group 2                                    |
|     | b5 | 13            | xxx binary group 2                                    |
|     | b6 | 14            | xxx binary group 2                                    |
|     | b7 | 15            | MSB binary group 2                                    |
| 5   | b4 | 16            | Units of seconds 1                                    |
|     | b5 | 17            | Units of seconds 2                                    |
|     | b6 | 18            | Units of seconds 4                                    |
|     | b7 | 19            | Units of seconds 8                                    |
| 6   | b4 | 20            | LSB binary group 3                                    |
|     | b5 | 21            | xxx binary group 3                                    |
|     | b6 | 22            | xxx binary group 3                                    |
|     | b7 | 23            | MSB binary group 3                                    |
| 7   | b4 | 24            | Tens of seconds 10                                    |
|     | b5 | 25            | Tens of seconds 20                                    |
|     | b6 | 26            | Tens of seconds 40                                    |
|     | b7 | 27            | Flag  |
| 8   | b4 | 28            | LSB binary group 4                                    |
|     | b5 | 29            | xxx binary group 4                                    |
|     | b6 | 30            | xxx binary group 4                                    |
|     | b7 | 31            | MSB binary group 4                                    |

TABLE 5 (continued)

| UDW |    | Time code bit | Time code definitions<br>(as per Rec. ITU-R BR.780-2) |
|-----|----|---------------|---|
| 9   | b4 | 32            | Units of minutes 1                                    |
|     | b5 | 33            | Units of minutes 2                                    |
|     | b6 | 34            | Units of minutes 4                                    |
|     | b7 | 35            | Units of minutes 8                                    |
| 10  | b4 | 36            | LSB binary group 5                                    |
|     | b5 | 37            | xxx binary group 5                                    |
|     | b6 | 38            | xxx binary group 5                                    |
|     | b7 | 39            | MSB binary group 5                                    |
| 11  | b4 | 40            | Tens of minutes 10                                    |
|     | b5 | 41            | Tens of minutes 20                                    |
|     | b6 | 42            | Tens of minutes 40                                    |
|     | b7 | 43            | Flag  |
| 12  | b4 | 44            | LSB binary group 6                                    |
|     | b5 | 45            | xxx binary group 6                                    |
|     | b6 | 46            | xxx binary group 6                                    |
|     | b7 | 47            | MSB binary group 6                                    |
| 13  | b4 | 48            | Units of hours 1                                      |
|     | b5 | 49            | Units of hours 2                                      |
|     | b6 | 50            | Units of hours 4                                      |
|     | b7 | 51            | Units of hours 8                                      |
| 14  | b4 | 52            | LSB binary group 7                                    |
|     | b5 | 53            | xxx binary group 7                                    |
|     | b6 | 54            | xxx binary group 7                                    |
|     | b7 | 55            | MSB binary group 7                                    |
| 15  | b4 | 56            | Tens of hours 10                                      |
|     | b5 | 57            | Tens of hours 20                                      |
|     | b6 | 58            | Flag  |
|     | b7 | 59            | Flag  |
| 16  | b4 | 60            | LSB binary group 8                                    |
|     | b5 | 61            | xxx binary group 8                                    |
|     | b6 | 62            | xxx binary group 8                                    |
|     | b7 | 63            | MSB binary group 8                                    |

NOTE – Appropriate flag information for each television system as per Recommendation ITU-R BR.780-2 is inserted into the corresponding positions of Table 5 marked as “flag.”

## 5 Transmission of ancillary time code packets

**5.1** Multiple transmissions of ancillary time code packets per video frame code information are permissible under the provisions of this Recommendation.

NOTE 1 – This Recommendation permits transmission of different ATC packets within a single video frame; as for example an ATC packet containing LTC information and a second ATC packet containing VITC information. The time code information in these two ATC packets shall correspond to the relevant video frame (see § 5.2).

**5.2** Transmission of ancillary time code packets should be at least once per frame for LTC data word and once per field for interlaced signals or once per frame for progressive signals for VITC data word. (For progressive systems with frame rates above 30 frames per second please see ITU-R BR.720-2 for special handling of LTC and VITC data.)

**5.2.1** Only the 64 information bits of time code are transferred to the ATC. The LTC sync word (bits 64-79) and the VITC (“1”/”0”) sync bit pairs and CRC word are omitted from the ancillary time code packets.

## 6 Ancillary time code packets location

**6.1** Insertion of ancillary time code (ATC) packets into any available location in the digital data stream is permitted under the provisions of this recommendation, but it is recommended that packet insertion occurs within the vertical blanking interval directly after the vertical switching point.

For systems according to ITU-R BT.1120 the following ATC insertion points should be considered as preferred location.

| Type of time code  | location for multiplexing in 1125/50/60 system                          |
|--------------------|---|
| Packet for LTC     | horizontal ancillary data space of line 10                              |
| Packet for VITC #1 | horizontal ancillary data space of line 9                               |
| Packet for VITC #2 | horizontal ancillary data space of line 571                             |
| Packet for others  | available any horizontal ancillary data space except line 9, 10 and 571 |

**6.2** Frame or field address information (LTC or VITC) contained in an ATC packet shall correspond to the respective video frame or field in which the ATC packet resides. Look-ahead compensation shall be applied to the time code (LTC or VITC) frame count when converting between ATC and either LTC or VITC.

**6.3** Transmission of the VITC word for field 1 or field 2 in the ancillary time code word for interlaced signals is signalled by a corresponding field flag (defined in Recommendation ITU-R BR.780-2) located in the ancillary binary group of the ATC word (see Table 5).