



INTERNATIONAL TELECOMMUNICATION UNION

**ITU-T**

TELECOMMUNICATION  
STANDARDIZATION SECTOR  
OF ITU

**G.997.1**

**Amendment 2**  
(01/2005)

SERIES G: TRANSMISSION SYSTEMS AND MEDIA,  
DIGITAL SYSTEMS AND NETWORKS

Digital sections and digital line system – Access networks

---

Physical layer management for digital subscriber  
line (DSL) transceivers

**Amendment 2**

ITU-T Recommendation G.997.1 (2003) – Amendment 2

---

ITU-T G-SERIES RECOMMENDATIONS  
TRANSMISSION SYSTEMS AND MEDIA, DIGITAL SYSTEMS AND NETWORKS

INTERNATIONAL TELEPHONE CONNECTIONS AND CIRCUITS	G.100–G.199
GENERAL CHARACTERISTICS COMMON TO ALL ANALOGUE CARRIER-TRANSMISSION SYSTEMS	G.200–G.299
INDIVIDUAL CHARACTERISTICS OF INTERNATIONAL CARRIER TELEPHONE SYSTEMS ON METALLIC LINES	G.300–G.399
GENERAL CHARACTERISTICS OF INTERNATIONAL CARRIER TELEPHONE SYSTEMS ON RADIO-RELAY OR SATELLITE LINKS AND INTERCONNECTION WITH METALLIC LINES	G.400–G.449
COORDINATION OF RADIOTELEPHONY AND LINE TELEPHONY	G.450–G.499
TRANSMISSION MEDIA CHARACTERISTICS	G.600–G.699
DIGITAL TERMINAL EQUIPMENTS	G.700–G.799
DIGITAL NETWORKS	G.800–G.899
DIGITAL SECTIONS AND DIGITAL LINE SYSTEM	G.900–G.999
General	G.900–G.909
Parameters for optical fibre cable systems	G.910–G.919
Digital sections at hierarchical bit rates based on a bit rate of 2048 kbit/s	G.920–G.929
Digital line transmission systems on cable at non-hierarchical bit rates	G.930–G.939
Digital line systems provided by FDM transmission bearers	G.940–G.949
Digital line systems	G.950–G.959
Digital section and digital transmission systems for customer access to ISDN	G.960–G.969
Optical fibre submarine cable systems	G.970–G.979
Optical line systems for local and access networks	G.980–G.989
<b>Access networks</b>	<b>G.990–G.999</b>
QUALITY OF SERVICE AND PERFORMANCE – GENERIC AND USER-RELATED ASPECTS	G.1000–G.1999
TRANSMISSION MEDIA CHARACTERISTICS	G.6000–G.6999
DIGITAL TERMINAL EQUIPMENTS	G.7000–G.7999
DIGITAL NETWORKS	G.8000–G.8999

*For further details, please refer to the list of ITU-T Recommendations.*

# **ITU-T Recommendation G.997.1**

## **Physical layer management for digital subscriber line (DSL) transceivers**

### **Amendment 2**

#### **Summary**

This amendment to ITU-T Rec. G.997.1 (05/2003) contains:

- Extension of INP values;
- Modification of MSGMIN bounds;
- Addition of an upstream PSD mask parameter;
- Use of one-second normalized CRC anomaly counter increment for SES declaration.

#### **Source**

Amendment 2 to ITU-T Recommendation G.997.1 (2003) was approved on 13 January 2005 by ITU-T Study Group 15 (2005-2008) under the ITU-T Recommendation A.8 procedure.

## FOREWORD

The International Telecommunication Union (ITU) is the United Nations specialized agency in the field of telecommunications. The ITU Telecommunication Standardization Sector (ITU-T) is a permanent organ of ITU. ITU-T is responsible for studying technical, operating and tariff questions and issuing Recommendations on them with a view to standardizing telecommunications on a worldwide basis.

The World Telecommunication Standardization Assembly (WTSA), which meets every four years, establishes the topics for study by the ITU-T study groups which, in turn, produce Recommendations on these topics.

The approval of ITU-T Recommendations is covered by the procedure laid down in WTSA Resolution 1.

In some areas of information technology which fall within ITU-T's purview, the necessary standards are prepared on a collaborative basis with ISO and IEC.

## NOTE

In this Recommendation, the expression "Administration" is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

Compliance with this Recommendation is voluntary. However, the Recommendation may contain certain mandatory provisions (to ensure e.g. interoperability or applicability) and compliance with the Recommendation is achieved when all of these mandatory provisions are met. The words "shall" or some other obligatory language such as "must" and the negative equivalents are used to express requirements. The use of such words does not suggest that compliance with the Recommendation is required of any party.

## INTELLECTUAL PROPERTY RIGHTS

ITU draws attention to the possibility that the practice or implementation of this Recommendation may involve the use of a claimed Intellectual Property Right. ITU takes no position concerning the evidence, validity or applicability of claimed Intellectual Property Rights, whether asserted by ITU members or others outside of the Recommendation development process.

As of the date of approval of this Recommendation, ITU had received notice of intellectual property, protected by patents, which may be required to implement this Recommendation. However, implementors are cautioned that this may not represent the latest information and are therefore strongly urged to consult the TSB patent database.

© ITU 2005

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without the prior written permission of ITU.

## CONTENTS

	<b>Page</b>
1) Addition of new INP values .....	1
2) Modification of MSGMIN bounds .....	1
3) New parameter for upstream PSD Mask .....	1
4) Use of one-second normalized CRC anomaly counter increment for SES declaration.....	2



# ITU-T Recommendation G.997.1

## Physical layer management for digital subscriber line (DSL) transceivers

### Amendment 2

#### 1) Addition of new INP values

*Modify 7.3.2.3 as follows:*

##### 7.3.2.3 Minimum Impulse Noise Protection

This parameter specifies the minimum impulse noise protection for the bearer channel. The impulse noise protection is expressed in symbols and can take the values 0,  $\frac{1}{2}$ , 1, ~~or~~ 2, 4, 8 and 16 symbols.

#### 2) Modification of MSGMIN bounds

*Modify clauses 7.3.1.5.1 and 7.3.1.5.2 as follows:*

##### 7.3.1.5.1 Minimum Overhead Rate Upstream (MSGMINus)

This parameter defines the minimum rate of the message based overhead that shall be maintained by the ATU in upstream direction. MSGMINus is expressed in bits per second and ranges from 4000 to ~~64000~~ 63 000 bit/s.

##### 7.3.1.5.2 Minimum Overhead Rate Downstream (MSGMINds)

This parameter defines the minimum rate of the message based overhead that shall be maintained by the ATU in downstream direction. MSGMINds is expressed in bits per second and ranges from 4000 to ~~64000~~ 63 000 bit/s.

#### 3) New parameter for upstream PSD Mask

i) *Add the following new clause 7.3.1.2.11:*

##### 7.3.1.2.11 Upstream PSD Mask (PSDMASKus)

This configuration parameter defines the upstream PSD mask applicable at the U-R2 reference point. This MIB PSD mask may impose PSD restrictions in addition to the Limit PSD mask defined in the relevant Recommendations (e.g., ITU-T Rec. G.992.3).

The upstream PSD mask in the CO-MIB shall be specified through a set of breakpoints. Each breakpoint shall consist of a subcarrier index  $t$  and a MIB PSD mask level (expressed in dBm/Hz) at that subcarrier. The set of breakpoints can then be represented as  $[(t_1, PSD_1), (t_2, PSD_2), \dots, (t_N, PSD_N)]$ . The subcarrier index shall be coded as an unsigned integer. The MIB PSD mask level shall be coded as an unsigned integer representing the MIB PSD mask levels 0 dBm/Hz (coded as 0) to -95 dBm/Hz (coded as 255), in steps of 0.5 dBm/Hz. The maximum number of breakpoints is 4.

The requirements for a valid set of breakpoints are defined in the relevant Recommendations (e.g., ITU-T Rec. G.992.3).

ii) Add a line in Table 7-9 after the RFIBANDS downstream as follows:

Category/Element	Defined in:	Q Interface	U-C Interface	U-R Interface	T/S Interface
PSDMASK upstream	7.3.1.2.11	R/W (M)	R (O)		

iii) Add a line in Table 7-10 after the RFIBANDS downstream as follows:

Category/Element	G.992.1	G.992.2	G.992.3	G.992.4	G.992.5
PSDMASK upstream			Y (Annexes J/M)		Y (Annexes J/M)

#### 4) Use of one-second normalized CRC anomaly counter increment for SES declaration

i) Modify clauses 7.2.1.1.3 and 7.2.1.2.3 as follows:

##### 7.2.1.1.3 Severely errored second – line (SES-L)

This parameter is a count of severely errored second (SES). A SES is declared if 1-second intervals with 18 or more CRC-8 anomalies summed over all received bearer channels, or one or more LOS defects, or one or more SEF defects, or one or more LPR defects, occur during a 1-second interval.

If the relevant Recommendation (e.g., ITU-T Rec. G.992.3) supports one-second normalized CRC anomaly counter increment, the one-second counter used to declare SES shall increment with this value instead of one for each CRC-8 anomaly.

If a common CRC is applied over multiple bearer channels, then each related CRC-8 anomaly shall be counted only once for the whole set of bearer channels over which the CRC is applied.

##### 7.2.1.2.3 Severely Errored Second – Line far-end (SES-LFE)

This parameter is a count of severely errored second (SES). A SES is declared if 1-second intervals with 18 or more FEBE anomalies summed over all transmitted bearer channels, or one or more far-end LOS defects, or one or more RDI defects, or one or more LPR-FE defects, occur during a 1 second-interval.

If the relevant Recommendation (e.g., ITU-T Rec. G.992.3) supports one-second normalized CRC anomaly counter increment, the one-second counter used to declare SES shall increment with this value instead of one for each FEBE anomaly.

If a CRC is applied over multiple bearer channels, then each related FEBE anomaly shall be counted only once for the whole set of related bearer channels.

ii) Add a new Note 4 in Table 7-1 as follows:

**Table 7-1/G.997.1 – Line performance monitoring parameter definitions**

Name	Text subclause	End	Use at ATU-C	Use at ATU-R	Definition
FECS-L		Near	M	M	$FEC \geq 1$ for one or more bearer channels
FECS-LFE		Far	M	O	$FFEC \geq 1$ for one or more bearer channels
ES-L		Near	M	M	$CRC-8 \geq 1$ for one or more bearer channels <b>OR</b> $LOS \geq 1$ <b>OR</b> $SEF \geq 1$ <b>OR</b> $LPR \geq 1$



**Table 7-1/G.997.1 – Line performance monitoring parameter definitions**

Name	Text subclause	End	Use at ATU-C	Use at ATU-R	Definition
ES-LFE		Far	M	O	FEBE $\geq$ 1 for one or more bearer channels <b>OR</b> LOS-FE $\geq$ 1 <b>OR</b> RDI $\geq$ 1 <b>OR</b> LPR-FE $\geq$ 1
SES-L		Near	M	M	(CRC-8 summed over all bearer channels) $\geq$ 18 <b>OR</b> LOS $\geq$ 1 <b>OR</b> SEF $\geq$ 1 <b>OR</b> LPR $\geq$ 1
SES-LFE		Far	M	O	(FEBE summed over all bearer channels) $\geq$ 18 <b>OR</b> LOS-FE $\geq$ 1 <b>OR</b> RDI $\geq$ 1 <b>OR</b> LPR-FE $\geq$ 1
LOSS-L		Near	O	O	LOS $\geq$ 1
LOSS-LFE		Far	O	O	LOS-FE $\geq$ 1
UAS-L		Near	M	M	A second of unavailability
UAS-LFE		Far	M	O	A second of unavailability

NOTE 1 – Note that **OR** represents a logical OR of two conditions.

NOTE 2 – Unavailability begins at the onset of 10 contiguous severely errored seconds, and ends at the onset of 10 contiguous seconds with no severely errored seconds.

NOTE 3 – If a common CRC or FEC is applied over multiple bearer channels, then each related CRC-8 or FEC anomaly shall be counted only once for the whole set of bearer channels over which the CRC or FEC is applied.

NOTE 4 – If the relevant Recommendation supports one-second normalized CRC counter increments, these increments shall be used instead of an increment of one for each CRC-8 and FEBE anomaly to declare SES.





## SERIES OF ITU-T RECOMMENDATIONS

Series A	Organization of the work of ITU-T
Series D	General tariff principles
Series E	Overall network operation, telephone service, service operation and human factors
Series F	Non-telephone telecommunication services
<b>Series G</b>	<b>Transmission systems and media, digital systems and networks</b>
Series H	Audiovisual and multimedia systems
Series I	Integrated services digital network
Series J	Cable networks and transmission of television, sound programme and other multimedia signals
Series K	Protection against interference
Series L	Construction, installation and protection of cables and other elements of outside plant
Series M	Telecommunication management, including TMN and network maintenance
Series N	Maintenance: international sound programme and television transmission circuits
Series O	Specifications of measuring equipment
Series P	Telephone transmission quality, telephone installations, local line networks
Series Q	Switching and signalling
Series R	Telegraph transmission
Series S	Telegraph services terminal equipment
Series T	Terminals for telematic services
Series U	Telegraph switching
Series V	Data communication over the telephone network
Series X	Data networks, open system communications and security
Series Y	Global information infrastructure, Internet protocol aspects and next-generation networks
Series Z	Languages and general software aspects for telecommunication systems