

I n t e r n a t i o n a l T e l e c o m m u n i c a t i o n U n i o n

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

H.830.15

(11/2019)

SERIES H: AUDIOVISUAL AND MULTIMEDIA SYSTEMS

E-health multimedia systems, services and applications –
Interoperability compliance testing of personal health
systems (HRN, PAN, LAN, TAN and WAN)

**Conformance of ITU-T H.810 personal health
system: Services interface Part 15: FHIR
Observation Upload: Health & Fitness Service
sender**

Recommendation ITU-T H.830.15

ITU-T



ITU-T H-SERIES RECOMMENDATIONS
AUDIOVISUAL AND MULTIMEDIA SYSTEMS

CHARACTERISTICS OF VISUAL TELEPHONE SYSTEMS	H.100–H.199
INFRASTRUCTURE OF AUDIOVISUAL SERVICES	
General	H.200–H.219
Transmission multiplexing and synchronization	H.220–H.229
Systems aspects	H.230–H.239
Communication procedures	H.240–H.259
Coding of moving video	H.260–H.279
Related systems aspects	H.280–H.299
Systems and terminal equipment for audiovisual services	H.300–H.349
Directory services architecture for audiovisual and multimedia services	H.350–H.359
Quality of service architecture for audiovisual and multimedia services	H.360–H.369
Telepresence, immersive environments, virtual and extended reality	H.420–H.439
Supplementary services for multimedia	H.450–H.499
MOBILITY AND COLLABORATION PROCEDURES	
Overview of Mobility and Collaboration, definitions, protocols and procedures	H.500–H.509
Mobility for H-Series multimedia systems and services	H.510–H.519
Mobile multimedia collaboration applications and services	H.520–H.529
Security for mobile multimedia systems and services	H.530–H.539
Security for mobile multimedia collaboration applications and services	H.540–H.549
VEHICULAR GATEWAYS AND INTELLIGENT TRANSPORTATION SYSTEMS (ITS)	
Architecture for vehicular gateways	H.550–H.559
Vehicular gateway interfaces	H.560–H.569
BROADBAND, TRIPLE-PLAY AND ADVANCED MULTIMEDIA SERVICES	
Broadband multimedia services over VDSL	H.610–H.619
Advanced multimedia services and applications	H.620–H.629
Ubiquitous sensor network applications and Internet of Things	H.640–H.649
IPTV MULTIMEDIA SERVICES AND APPLICATIONS FOR IPTV	
General aspects	H.700–H.719
IPTV terminal devices	H.720–H.729
IPTV middleware	H.730–H.739
IPTV application event handling	H.740–H.749
IPTV metadata	H.750–H.759
IPTV multimedia application frameworks	H.760–H.769
IPTV service discovery up to consumption	H.770–H.779
Digital Signage	H.780–H.789
E-HEALTH MULTIMEDIA SYSTEMS, SERVICES AND APPLICATIONS	
Personal health systems	H.810–H.819
Interoperability compliance testing of personal health systems (HRN, PAN, LAN, TAN and WAN)	H.820–H.859
Multimedia e-health data exchange services	H.860–H.869
Safe listening	H.870–H.879

For further details, please refer to the list of ITU-T Recommendations.

Recommendation ITU-T H.830.15

Conformance of ITU-T H.810 personal health system: Services interface Part 15: FHIR Observation Upload: Health & Fitness Service sender

Summary

Recommendation ITU-T H.830.15 provides a test suite structure (TSS) and the test purposes (TPs) for fast healthcare interoperability resource (FHIR) Observation Upload through the Health & Fitness Service (HFS) sender in the Services interface, based on the requirements defined in the Recommendations of the ITU-T H.810 sub-series, of which Recommendation ITU-T H.810 (2017) is the base Recommendation. The objective of this test specification is to provide a high probability of interoperability at this interface.

Recommendation ITU-T H.830.15 includes an electronic attachment with the protocol implementation conformance statements (PICSs) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

History

Edition	Recommendation	Approval	Study Group	Unique ID*
1.0	ITU-T H.830.15	2018-08-29	16	11.1002/1000/13676
2.0	ITU-T H.830.15	2019-11-29	16	11.1002/1000/14115

Keywords

Conformance testing, Continua Design Guidelines, e-health, Health & Fitness Service, ITU-T H.810, personal connected health devices, Services interface, Capability Exchange, FHIR Observation Upload.

* To access the Recommendation, type the URL <http://handle.itu.int/> in the address field of your web browser, followed by the Recommendation's unique ID. For example, <http://handle.itu.int/11.1002/1000/11830-en>.

FOREWORD

The International Telecommunication Union (ITU) is the United Nations specialized agency in the field of telecommunications, information and communication technologies (ICTs). The ITU Telecommunication Standardization Sector (ITU-T) is a permanent organ of ITU. ITU-T is responsible for studying technical, operating and tariff questions and issuing Recommendations on them with a view to standardizing telecommunications on a worldwide basis.

The World Telecommunication Standardization Assembly (WTSA), which meets every four years, establishes the topics for study by the ITU-T study groups which, in turn, produce Recommendations on these topics.

The approval of ITU-T Recommendations is covered by the procedure laid down in WTSA Resolution 1.

In some areas of information technology which fall within ITU-T's purview, the necessary standards are prepared on a collaborative basis with ISO and IEC.

NOTE

In this Recommendation, the expression "Administration" is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

Compliance with this Recommendation is voluntary. However, the Recommendation may contain certain mandatory provisions (to ensure, e.g., interoperability or applicability) and compliance with the Recommendation is achieved when all of these mandatory provisions are met. The words "shall" or some other obligatory language such as "must" and the negative equivalents are used to express requirements. The use of such words does not suggest that compliance with the Recommendation is required of any party.

INTELLECTUAL PROPERTY RIGHTS

ITU draws attention to the possibility that the practice or implementation of this Recommendation may involve the use of a claimed Intellectual Property Right. ITU takes no position concerning the evidence, validity or applicability of claimed Intellectual Property Rights, whether asserted by ITU members or others outside of the Recommendation development process.

As of the date of approval of this Recommendation, ITU had not received notice of intellectual property, protected by patents, which may be required to implement this Recommendation. However, implementers are cautioned that this may not represent the latest information and are therefore strongly urged to consult the TSB patent database at <http://www.itu.int/ITU-T/ipr/>.

© ITU 2020

All rights reserved. No part of this publication may be reproduced, by any means whatsoever, without the prior written permission of ITU.

Table of Contents

	Page
1	Scope 1
2	References..... 1
3	Definitions 2
3.1	Terms defined elsewhere 2
3.2	Terms defined in this Recommendation 2
4	Abbreviations and acronyms 2
5	Conventions 3
6	Test suite structure 4
7	Electronic attachment 7
Annex A	Test procedures..... 8
A.1	Test purpose definition conventions..... 8
A.2	Subgroup 1.9.1: General (GEN)..... 9
A.2	Subgroup 1.9.2: FHIR Encoding Guidelines (ENC)..... 14
Bibliography 43

Electronic attachment: This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICSs) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

Introduction

The table below shows the revision history of this test specification.

Version	Date	Revision history
1.0	2018-02-27	Initial release for the inclusion of FHIR Observation Upload for Health & Fitness Service senders.
1.1	2019-06-13	Second maintenance release for Test Tool DG2017. It uses "H.830.15_201808" as a baseline and adds some updates according to the 2018/2019 maintenance activity.

Recommendation ITU-T H.830.15

Conformance of ITU-T H.810 personal health system: Services interface Part 15: FHIR Observation Upload: Health & Fitness Service sender

1 Scope

The scope of this Recommendation¹ is to provide a test suite structure (TSS) and the test purposes (TPs) for the Services interface based on the requirements defined in the Continua Design Guidelines (CDG) [ITU-T H.810 (2017)]. The objective of this test specification is to provide a high probability of interoperability at this interface.

The TSS and TPs for the services interface have been divided into the parts specified below. This Recommendation covers Part 15.

- Part 1: Web services interoperability. Health & Fitness Service sender
- Part 2: Web services interoperability. Health & Fitness Service receiver
- Part 3: SOAP/ATNA. Health & Fitness Service sender
- Part 4: SOAP/ATNA. Health & Fitness Service receiver
- Part 5: PCD-01 HL7 Messages. Health & Fitness Service sender
- Part 6: PCD-01 HL7 Messages. Health & Fitness Service receiver
- Part 7: Consent Management. Health & Fitness Service sender
- Part 8: Consent Management. Health & Fitness Service receiver
- Part 9: hData Observation Upload. Health & Fitness Service sender
- Part 10: hData Observation Upload. Health & Fitness Service receiver
- Part 11: Questionnaires. Health & Fitness Service sender
- Part 12: Questionnaires. Health & Fitness Service receiver
- Part 13: Capability Exchange. Health & Fitness Service sender
- Part 14: Capability Exchange. Health & Fitness Service receiver
- **Part 15: FHIR Observation Upload. Health & Fitness Service sender**
- Part 16: FHIR Observation Upload. Health & Fitness Service receiver.

2 References

The following ITU-T Recommendations and other references contain provisions which, through reference in this text, constitute provisions of this Recommendation. At the time of publication, the editions indicated were valid. All Recommendations and other references are subject to revision; users of this Recommendation are therefore encouraged to investigate the possibility of applying the most recent edition of the Recommendations and other references listed below. A list of the currently valid ITU-T Recommendations is regularly published. The reference to a document within this Recommendation does not give it, as a stand-alone document, the status of a Recommendation.

[ITU-T H.810 (2017)] Recommendation ITU-T H.810 (2017), *Interoperability design guidelines for personal health systems: Introduction*.

¹ This Recommendation includes an electronic attachment with the protocol implementation conformance statements (PICS) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A.

3 Definitions

3.1 Terms defined elsewhere

None.

3.2 Terms defined in this Recommendation

None.

4 Abbreviations and acronyms

This Recommendation uses the following abbreviations and acronyms:

AHD	Application Hosting Device
ATNA	Audit Trail and Node Authentication
BLE	Bluetooth Low Energy
BT HDP	Bluetooth Health Device Profile
CDG	Continua Design Guidelines
CGM	Continuous Glucose Monitor
DUT	Device Under Test
FHIR	Fast Healthcare Interoperability Resources
HFS	Health & Fitness Service
HFSS	Health & Fitness Service Sender
HFSR	Health & Fitness Service Receiver
HL7	Health Level 7
HTTP	Hypertext Transfer Protocol
INR	International Normalized Ratio
IP	Insulin Pump
JSON	JavaScript Object Notation
MDS	Medical Device System
NFC	Near Field Communication
PCD	Patient Care Device
PHD	Personal Health Device
PHDC	Personal Healthcare Device Class
PHG	Personal Health Gateway
PICS	Protocol Implementation Conformance Statement
PIXIT	Protocol Implementation extra Information for Testing
SABTE	Sleep Apnoea Breathing Therapy Equipment
SCR	Static Conformance Review

SOAP	Simple Object Access Protocol
TLS	Transport Level Security
TP	Test Purpose
TSS	Test Suite Structure
USB	Universal Serial Bus
URI	Uniform Resource Identifier
WS	Web Service
WSI	Web Services Interoperability
XDR	Cross-Enterprise Document Reliable Interchange
XML	extensible Markup Language
ZB	Zigbee

5 Conventions

The key words "SHALL", "SHALL NOT", "SHOULD", "SHOULD NOT", "MAY", "MAY NOT" in this Recommendation are to be interpreted as in [b-ETSI SR 001 262].

- SHALL is equivalent to 'must' or 'it is required to'.
- SHALL NOT is equivalent to 'must not' or 'it is not allowed'.
- SHOULD is equivalent to 'it is recommended to'.
- SHOULD NOT is equivalent to 'it is not recommended to'.
- MAY is equivalent to 'is permitted'.
- MAY NOT is equivalent to 'it is not required that'.

NOTE – The above-mentioned key words are capitalized for illustrative purposes only and they do not appear capitalized within this Recommendation.

Reference is made in the ITU-T H.800-series of Recommendations to different versions of the Continua Design Guidelines (CDG) by a specific designation. The list of terms that may be used in this Recommendation is provided in Table 1.

Table 1 – List of designations associated with the various versions of the CDG

CDG release	Transposed as	Version	Description	Designation
2017	–	7.0	Release 2017 of the CDG including maintenance updates of the CDG 2016 and additional guidelines that cover new functionalities.	–
2016 plus errata	[ITU-T H.810 (2016)]	6.1	Release 2016 plus errata noting all ratified bugs [b-CDG 2016].	–
2016	–	6.0	Release 2016 of the CDG including maintenance updates of the CDG 2015 and additional guidelines that cover new functionalities.	Iris
2015 plus errata	[b-ITU-T H.810 (2015)]	5.1	Release 2015 plus errata noting all ratified bugs [b-CDG 2015]. The 2013 edition of [ITU-T H.810] is split into eight parts in the ITU-T H.810-series.	–
2015	–	5.0	Release 2015 of the CDG including maintenance updates of the CDG 2013 and additional guidelines that cover new functionalities.	Genome
2013 plus errata	[b-ITU-T H.810 (2013)]	4.1	Release 2013 plus errata noting all ratified bugs [b-CDG 2013].	–
2013	–	4.0	Release 2013 of the CDG including maintenance updates of the CDG 2012 and additional guidelines that cover new functionalities.	Endorphin
2012 plus errata	–	3.1	Release 2012 plus errata noting all ratified bugs [b-CDG 2012].	–
2012	–	3.0	Release 2012 of the CDG including maintenance updates of the CDG 2011 and additional guidelines that cover new functionalities.	Catalyst
2011 plus errata	–	2.1	CDG 2011 integrated with identified errata.	–
2011	–	2.0	Release 2011 of the CDG including maintenance updates of the CDG 2010 and additional guidelines that cover new functionalities [b-CDG 2011].	Adrenaline
2010 plus errata	–	1.6	CDG 2010 integrated with identified errata	–
2010	–	1.5	Release 2010 of the CDG with maintenance updates of the CDG Version 1 and additional guidelines that cover new functionalities [b-CDG 2010].	1.5
1.0	–	1.0	First released version of the CDG [b-CDG 1.0].	–

6 Test suite structure

The test procedures (TPs) for the Services interface have been divided into the main subgroups specified below. Annex A describes the TPs for subgroups 1.7.1 and 1.7.2 (shown in bold):

- Group 1: HFS sender (HFSS)
 - Group 1.1: Web services interoperability (WSI)
 - Subgroup 1.1.1: Basic profile (BP)
 - Subgroup 1.1.2: Basic security profile (BSP)
 - Subgroup 1.1.3: Reliable messaging (RM)
 - Group 1.2: Simple object access protocol (SOAP)
 - Subgroup 1.2.1: SOAP headers (HEAD)
 - Group 1.3: Audit trail and node authentication (ATNA)
 - Subgroup 1.3.1: General (GEN)
 - Subgroup 1.3.2: PCD-01 (PCD-01)
 - Subgroup 1.3.3: Consent Management (CM)
 - Group 1.4: PCD-01 HL7 messages (PCD-01-DATA)
 - Subgroup 1.4.1: General (GEN)
 - Subgroup 1.4.2: Design guidelines (DG)
 - Subgroup 1.4.3: Pulse oximeter (PO)
 - Subgroup 1.4.4: Blood pressure monitor (BPM)
 - Subgroup 1.4.5: Thermometer (TH)
 - Subgroup 1.4.6: Weighing scales (WEG)
 - Subgroup 1.4.7: Glucose meter (GL)
 - Subgroup 1.4.8: Cardiovascular fitness and activity monitor (CV)
 - Subgroup 1.4.9: Strength fitness equipment (ST)
 - Subgroup 1.4.10: Independent living activity hub (HUB)
 - Subgroup 1.4.11: Adherence monitor (AM)
 - Subgroup 1.4.12: Peak expiratory flow monitor (PF)
 - Subgroup 1.4.13: Body composition analyser (BCA)
 - Subgroup 1.4.14: Basic electrocardiograph (ECG)
 - Subgroup 1.4.15: International normalized ratio (INR)
 - Subgroup 1.4.16: Sleep apnoea breathing therapy equipment (SABTE)
 - Subgroup 1.4.17: Insulin pump (IP)
 - Subgroup 1.4.18: Continuous glucose monitor (CGM)
 - Group 1.5: Consent Management (CM)
 - Subgroup 1.5.1: HFS XDR transaction (TRANS)
 - Subgroup 1.5.2: HFS metadata validation (META)
 - Subgroup 1.5.3: HFS consent directive validation (CDV)
 - Group 1.6: hData Observation Upload (HDATA)
 - Subgroup 1.6.1: General (GEN)
 - Group 1.7: Questionnaires (QUE)
 - Subgroup 1.7.1: General (GEN)
 - Subgroup 1.7.2: CDA validation (CDA)
 - Group 1.8: Capability Exchange (CE)
 - Subgroup 1.8.1: General (GEN)

- Subgroup 1.8.2: hData record format (HRF)
- **Group 1.9: FHIR Observation Upload (FHIR)**
 - **Subgroup 1.9.1: General (GEN)**
 - **Subgroup 1.9.2: FHIR Encoding Guidelines (ENC)**
- Group 2: HFS receiver (HFSR)
 - Group 2.1: Web service interoperability (WSI)
 - Subgroup 2.1.1: Basic profile (BP)
 - Subgroup 2.1.2: Basic security profile (BSP)
 - Subgroup 2.1.3: Reliable messaging (RM)
 - Group 2.2: SOAP (SOAP)
 - Subgroup 2.2.1: SOAP headers (HEAD)
 - Group 2.3: Audit (ATNA)
 - Subgroup 2.3.1: General (GEN)
 - Subgroup 2.3.2: PCD-01 (PCD-01)
 - Subgroup 2.3.3: Consent Management (CM)
 - Group 2.4: PCD-01 HL7 messages (PCD-01-DATA)
 - Subgroup 2.4.1: General (GEN)
 - Subgroup 2.4.2: Design guidelines (DG)
 - Subgroup 2.4.3: Pulse oximeter (PO)
 - Subgroup 2.4.4: Blood pressure monitor (BPM)
 - Subgroup 2.4.5: Thermometer (TH)
 - Subgroup 2.4.6: Weighing scales (WEG)
 - Subgroup 2.4.7: Glucose meter (GL)
 - Subgroup 2.4.8: Cardiovascular fitness and activity monitor (CV)
 - Subgroup 2.4.9: Strength fitness equipment (ST)
 - Subgroup 2.4.10: Independent living activity hub (HUB)
 - Subgroup 2.4.11: Adherence monitor (AM)
 - Subgroup 2.4.12: Peak expiratory flow monitor (PF)
 - Subgroup 2.4.13: Body composition analyser (BCA)
 - Subgroup 2.4.14: Basic electrocardiograph (ECG)
 - Subgroup 2.4.15: International normalized ratio (INR)
 - Subgroup 2.4.16: Sleep apnoea breathing therapy equipment (SABTE)
 - Subgroup 2.4.17: Insulin pump (IP)
 - Subgroup 2.4.18: Continuous glucose monitor (CGM)
 - Group 2.5: Consent Management (CM)
 - Subgroup 2.5.1: HFS XDR transaction (TRANS)
 - Subgroup 2.5.2: HFS service validation (SER)
 - Group 2.6: hData Observation Upload (HDATA)
 - Subgroup 2.6.1: General (GEN)
 - Subgroup 2.6.2: hData record format (HRF)

- Group 2.7: Questionnaires (QUE)
 - Subgroup 2.7.1: General (GEN)
 - Subgroup 2.7.2: CDA validation (CDA)
 - Subgroup 2.7.3: hData record format (HRF)
- Group 2.8: Capability Exchange (CE)
 - Subgroup 2.8.1: General (GEN)
 - Subgroup 2.8.2: hData record format (HRF)
- Group 2.9: FHIR Observation Upload (FHIR)
 - Subgroup 2.9.1: General (GEN)

7 Electronic attachment

The protocol implementation conformance statements (PICSs) and the protocol implementation extra information for testing (PIXIT) required for the implementation of Annex A can be downloaded from <http://handle.itu.int/11.1002/2000/12067>. See [b-HFSR PICS & PIXIT] and [b-HFSS PICS & PIXIT].

In the electronic attachment, letters "C" and "I" in the column labelled "Mandatory" are used to distinguish between "PICSs" and "PIXIT", respectively, during testing. If the cell is empty, the corresponding PICS is "independent". If the field contains a "C", the corresponding PICS is dependent on other PICSs, and the logical expression is detailed in the "SCR_Expression" field. The static conformance review (SCR) is used in the test tool to assert whether the PICS selection is consistent.

Annex A

Test procedures

(This annex forms an integral part of this Recommendation.)

A.1 Test purpose definition conventions

The TPs are defined according to the following rules:

- **TP Id:** This is a unique identifier (TP/<TT>/<DUT>/<GR>/<SGR>/<XX> – <NNN>). It is specified according to the naming convention defined below:
Each TP identifier is introduced by the prefix "TP".
 - <TT>: This is the test tool that will be used in the test case.
 - HFS: Health & Fitness Services Interface
 - <DUT>: This is the device under test.
 - SEN: HFS sender
 - REC: HFS receiver
 - <GR>: This identifies a group of test cases.
 - <SGR>: This identifies a subgroup of test cases.
 - <XX>: This identifies the type of testing.
 - BV: Valid behaviour test
 - BI: Invalid behaviour test
 - <NNN>: This is a sequential number that identifies the TP.
- **TP label:** This is title of the TP.
- **Coverage:** This contains the specification reference and clause to be checked by the TP.
 - Spec: This indicates the earliest version of the specification from which the testable items to be checked by the TP were included.
 - Testable item: This contains testable items to be checked by the TP.
- **Test purpose:** This is a description of the requirements to be tested.
- **Applicability:** This contains the PICS items that define if a test case is applicable or not for a specific device. When a TP contains an "ALL" in this field it means that it applies to the DUT within that scope of the test (specialization, transport used, etc.).
- **Other PICSs:** This contains additional PICS items (apart from the PICS specified in the Applicability row) which are used within the test case implementation and can modify the final verdict. When this row is empty, it means that only the PICS specified in the Applicability row are used within the test case implementation.
- **Initial condition:** This indicates the state to which the DUT needs to be moved at the beginning of TC execution.
- **Test procedure:** This describes the steps to be followed in order to execute the test case.
- **Pass/Fail criteria:** This provides criteria to decide whether the DUT passes or fails the test case.

A.2 Subgroup 1.9.1: General (GEN)

TP Id	TP/HFS/SEN/FHIR/GEN/BV-000			
TP label	Oauth support			
Coverage	Spec	[ITU-T H.812]		
	Testable items	RESTSec 3;M	RESTSec 4;M	RESTSec 5;M
		CommonReq 5;M		
	Spec	[b-HSTP-H812-FHIR]		
	Testable items	PHGCommon 1; M	PHGCommon 2; M	PHGCommon 9; M
PHGCommon 21; M				
Test purpose	<p>Check that:</p> <p>The PHG) under test is able to retrieve the OAuth Descriptor of the simulated H&FS using the link element of the provided Atom Feed.</p> <p>[AND]</p> <p>The PHG under test uploads a complete FHIR resource bundle using TLS 1.1 and an OAuth v2.0 bearer token to the simulated H&FS using a create or conditional create operation.</p>			
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)			
Other PICSS				
Initial condition	<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. The H&FS supports all available OAuth 2.0 authorization grant types (so they are listed in the grantTypes element of its OAuthDescriptor). Simulated H&FS has no previously stored resources.</p>			
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG under test to retrieve the OAuthDescriptor of the simulated H&FS. 2. The PHG obtains the root file of the H&FS, and retrieves the OAuthDescriptor via the link element in the Atom Feed provided by the root file. 3. Ask the PHG under test to upload an Observation resource as a complete bundle to the simulated H&FS. 4. The PHG uses a create or conditional create operation (HTTP POST) to upload the bundle to the simulated H&FS using TLS 1.1 and a valid OAuth 2.0 bearer token obtained using one of the available authorization grant types. 5. The H&FS accepts the request and returns <HTTP 201> (Created) and a Location header, which contains the new Logical Id and Version Id of the created resources versions. 			
Pass/fail criteria	<ul style="list-style-type: none"> • PHG correctly retrieves the OAuthDescriptor in step 2. • PHG uploads the resource bundle as described in step 4, so the simulated H&FS can accept the operation. 			
Notes				

TP Id	TP/HFS/SEN/FHIR/GEN/BV-001
TP label	JSON Web Token support

Coverage	Spec	[ITU-T H.812]		
	Testable items	RESTSec 3;M	RESTSec 4;M	RESTSec 5;M
		CommonReq 5;M		
	Spec	[b-HSTP-H812-FHIR]		
	Testable items	PHGCommon 9; M	PHGCommon 3; M	PHGCommon 4; M
		PHGCommon 6; M	PHGCommon 7; M	PHGCommon 8; M
PHGCommon 21; M				
Test purpose	<p>Check that:</p> <p>The PHG under test is able to retrieve the OAuth Descriptor of the simulated H&FS using the link element of the provided Atom Feed.</p> <p>[AND]</p> <p>The PHG using a bearer JWT shall issue an access token request with the appropriate parameters and values and shall issue the JWT with the specified claims.</p> <p>[AND]</p> <p>The PHG under test uploads a complete FHIR resource bundle using TLS 1.1 and the JSON Web Token to the simulated H&FS using a create or conditional create operation.</p>			
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008) AND C_SEN_FHIR_001			
Other PICSS				
Initial condition	<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. The H&FS supports JWT authorization grant type (so the string "rfc7523" is included in the grantTypes element of its OAuthDescriptor). Simulated H&FS has no previously stored resources.</p>			
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG under test to retrieve the OAuthDescriptor of the simulated H&FS. 2. The PHG obtains the root file of the H&FS, and retrieves the OAuthDescriptor via the link element in the Atom Feed provided by the root file and checks that the string "rfc7523" is included in the grantTypes element. 3. Ask the PHG to upload a complete FHIR resource bundle including an observation using the extension (JWT) authorization grant type to provide a valid JWT. 4. When the PHG performs the upload check that: <ul style="list-style-type: none"> • The PHG uses a create or conditional create operation using HTTP POST. • The PHG sends a grant_type value of: "urn:ietf:params:oauth:granttype:jwt-bearer". • The PHG contains a single valid JWT, and: <ul style="list-style-type: none"> • It contains an "iat" (issued at) claim that identifies the time at which the claim was issued. • It contains a "jti" (JWT ID) claim that provides a unique identifier for the token. 5. The H&FS accepts the request and returns <HTTP 201> (Created) and a Location header, which contains the new Logical Id and Version Id of the created resources versions. 			
Pass/fail criteria	<ul style="list-style-type: none"> • PHG correctly retrieves the OAuthDescriptor in step 2 and checks for JWT support. • PHG uploads the resource bundle as described in step 4, so the simulated H&FS can accept the operation. 			
Notes				

TP Id	TP/HFS/SEN/FHIR/GEN/BV-002			
TP label	FHIR API for FHIR Operation Client			
Coverage	Spec	[ITU-T H.812]		
	Testable items	RESTSec 3;M	RESTSec 4;M	RESTSec 5;M
		CommonReq 5;M		
	Spec	[b-HSTP-H812-FHIR]		
	Testable items	PHGCommon 11; M	PHGCommon 12; M	PHGCommon 16; C
		PHGCommon 17; C	PHGCommon 18; C	PHGCommon 19; M
PHGCommon 21; M		PHGCommon 24; M	FOCReq 2; M	
Test purpose	<p>Check that:</p> <p>A PHG client shall not specify the Logical ID for the Patient Resource when performing a single-resource create or a conditional create of the Patient Resource The PHG client shall provide the Patient Designator information in the Patient Resource. Additionally, in the created resource, the <i>Patient.identifier.system</i> shall be a URI set to the health care identification system and the <i>Patient.identifier.value</i> shall be set to the patient identifier component of the Patient Descriptor.</p> <p>[AND]</p> <p>If a conditional create operation is used, the search parameter of the "If-None-Exist" header shall be the healthcare identification system and the patient identifier placed in the <i>Patient.identifier</i> element.</p> <p>[AND]</p> <p>A PHG client shall specify the Logical ID for the Patient Resource when performing a single-resource update</p> <p>[AND]</p> <p>If the Patient Resource Logical ID is to be created by the PHG, the PHG shall specify the Logical ID as the concatenation of field values: <i>Patient.identifier.value-Patient.identifier.system</i>.</p> <p>[AND]</p> <p>When a DeviceComponent Resource is uploaded the PHG shall use the FHIR update or conditional create operations.</p> <p>[AND]</p> <p>When an Observation Resource is uploaded the PHG shall use the create or conditional create operations</p> <p>[AND]</p> <p>A PHG shall format measurement payloads in JSON or XML, and can send single resources or complete bundles.</p>			
Applicability	C_SEN_000 AND C_SEN_GEN_007			
Other PICSSs				
Initial condition	<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>			

<p>Test procedure</p>	<ol style="list-style-type: none"> 1. Ask the PHG to upload a new single FHIR Patient Resource to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 2. Check that the request is a create or conditional create operation using HTTP POST and that, in the request: <ul style="list-style-type: none"> • The PHG client does not specify a Logical ID. • The PHG client provides the Patient Designator information in the Patient Resource so that the H&FS can provide a Logical ID. • In the created Patient Resource, the Patient.identifier.system shall be a URI set to the health care identification system. • In the created Patient Resource, the Patient.identifier.value is set to the patient identifier component of the Patient Descriptor. • If a conditional create operation is used, the search parameter of the "If-None-Exist" header shall be the healthcare identification system and the patient identifier placed in the Patient.identifier element 3. The simulated H&FS accepts the operation and returns <HTTP 201> (created) and a Location header, which contains the Logical Id and Version Id of the created resource 4. Ask the PHG to perform an update on the previously uploaded FHIR Patient Resource in the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or a valid JWT. 5. Check that the request is an update operation using HTTP PUT and that: <ul style="list-style-type: none"> • The PHG client specifies the previously provided Logical ID. 6. The simulated H&FS accepts the operation, updates the Patient Resource and returns an <HTTP 200> (OK) status code. 7. Ask the PHG to upload a new single FHIR Patient Resource to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT, including the generation of a new Logical ID. 8. Check that the request is an update operation using HTTP PUT and that: <ul style="list-style-type: none"> • The PHG-created Logical ID concatenation of field values: <i>Patient.identifier.value-Patient.identifier.system</i> where: <ul style="list-style-type: none"> ▪ The italicized strings represent the values associated with the named fields. ▪ If the original string is longer than 64 characters, it is truncated to 64 characters (by removing characters from the end of the string). ▪ If this original string contains any characters other than A-Z, a-z, 0-9, "-", or ".", they are replaced by a ".". 9. The simulated H&FS accepts the operation and returns <HTTP 201> (created). 10. Ask the PHG to upload a new single FHIR DeviceComponent Resource (linked to the Patient Resource created in step 9) to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 11. Check that the request is an update operation using HTTP PUT or a conditional create operation using HTTP POST. 12. The H&FS creates the resource and returns <HTTP 201> (Created) and a Location header, which contains the new Logical Id and Version Id of the created resource version 13. Ask the PHG to upload a new FHIR Observation Resource (linked to the DeviceComponent Resource created in step 9) to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 14. Check that the request is a create or a conditional create operation using HTTP POST. 15. The H&FS creates the resource and returns <HTTP 201> (Created) and a Location header, which contains the new Logical Id and Version Id of the created resource version 16. Ask the PHG to upload a complete FHIR bundle in JSON format including a new Observation resource to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 17. Check that the request is a create or a conditional create operation using HTTP POST.
------------------------------	---

	18. The H&FS creates the resource and returns <HTTP 201> (Created) and a Location header, which contains the new Logical Id and Version Id of the created resource version
Pass/fail criteria	<ul style="list-style-type: none"> Simulated H&FS accepts the requests as described in steps 2, 5, 8, 11, 14 and 17.
Notes	

TP Id	TP/HFS/SEN/FHIR/GEN/BV-003			
TP label	FHIR API for FHIR Operation Reporting Client			
Coverage	Spec	[ITU-T H.812]		
	Testable items	RESTSec 3;M	RESTSec 4;M	RESTSec 5;M
		CommonReq 5;M		
	Spec	[b-HSTP-H812-FHIR]		
	Testable items	PHGCommon 13; M	PHGCommon 14; M	PHGCommon 15; M
		PHGCommon 16; C	PHGCommon 19; M	PHGCommon 21; M
FORCReq 1; M		FORCReq 2; M		
Test purpose	<p>Check that:</p> <p>When uploading to a FHIR Observation Reporting Server the measurement shall be uploaded as an http POST operation with the payload containing a complete FHIR transaction bundle.</p> <p>[AND]</p> <p>Within a transaction bundle the FHIR operation on the Patient Resource shall be either update or conditional create The update shall only be used when the Logical ID of the Patient Resource is known.</p> <p>[AND]</p> <p>A PHG shall specify a temporary Logical ID for the Patient Resource being created or conditionally created in a Transaction Bundle if the Patient Resource is referenced by another resource in the transaction Bundle (i.e. a DeviceComponent resource). The PHG client shall provide the Patient Designator information in the Patient Resource</p> <p>[AND]</p> <p>When a DeviceComponent Resource is uploaded in a bundle, the PHG shall use the FHIR update or conditional create operations.</p> <p>[AND]</p> <p>When an Observation Resource is uploaded in a bundle, the PHG shall use the create or conditional create operations</p> <p>[AND]</p> <p>A PHG implementing only a FHIR Observation Reporting Client shall be able to upload measurements to an H&FS advertising a FHIR Observation Server Continua Certified Capability Class or FHIR Observation Reporting Server Continua Certified Capability Class.</p>			
Applicability	C_SEN_000 AND C_SEN_GEN_008			
Other PICs				
Initial condition	Simulated H&FS supports FHIR Observation Reporting Server and Capability Exchange Continua Certified Capability Classes, so it can accept FHIR resource bundles using TLS			

	1.1 security and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG to upload a new FHIR Patient Resource within a complete FHIR bundle to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 2. Check that the request is a create or conditional create operation using HTTP POST and that, in the request: <ul style="list-style-type: none"> • A temporary Logical ID for the Patient Resource being created is specified in the transaction bundle. • The Patient Designator information is provided in the Patient Resource. 3. The simulated H&FS accepts the operation and returns <HTTP 201> (created) and a Location header, which contains the Logical Id and Version Id of the created resources. 4. Ask the PHG to upload a new FHIR DeviceComponent Resource within a complete FHIR bundle to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 5. Check that the request is an update operation using HTTP PUT or a conditional create operation using HTTP POST. 6. The simulated H&FS accepts the operation and returns <HTTP 201> (created) and a Location header, which contains the Logical Id and Version Id of the created resources. 7. Ask the PHG to upload a new FHIR Observation Resource within a complete FHIR bundle to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 8. Check that the request is a create or conditional create operation using HTTP POST. 9. The simulated H&FS accepts the operation and returns <HTTP 201> (created) and a Location header, which contains the Logical Id and Version Id of the created resources. 10. The simulated H&FS is re-configured to support only FHIR Observation Server Continua Certified Capability Class. 11. Ask the PHG under test to retrieve the root file and OAuthDescriptor of this new configuration. 12. Ask the PHG to upload a new FHIR Observation Resource within a complete FHIR bundle to the simulated H&FS using TLS 1.1 and an OAuth 2.0 bearer token or JWT. 13. Check that the request is a create or conditional create operation using HTTP POST. 14. The simulated H&FS accepts the operation and returns <HTTP 201> (created) and a Location header, which contains the Logical Id and Version Id of the created resources.
Pass/fail criteria	<ul style="list-style-type: none"> • Simulated H&FS accepts the requests as described in steps 2, 5, 8, and 13.
Notes	

A.2 Subgroup 1.9.2: FHIR Encoding Guidelines (ENC)

TP Id	TP/HFS/SEN/FHIR/ENC/BV-000			
TP label	PHG Properties Encoding			
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	PHGFHIR 1; M	PHGFHIR 2; M	PHGFHIR 3; C
		PHGFHIR 4; M	PHGFHIR 5; M	PHGFHIR 6; M
		PHGFHIR 7; O	PHGFHIR 8; C	PHGFHIR 9; C
PHGFHIR 10; M		PHGFHIR 11; M	PHGFHIR 12; M	

		PHGFHIR 13; M	PHGFHIR 14; M	PHGFHIR 15; O
		PHGFHIR 16; O	PHGCommon 28; M	
Test purpose	Check that: The FHIR resource representing the PHG Properties is properly encoded.			
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)			
Other PICSSs				
Initial condition	Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.			
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a PHG FHIR resource. 2. In the PHG FHIR resource check that: <ol style="list-style-type: none"> a) resourceType is set to "DeviceComponent". b) IF the PHG performs a FHIR "update interaction", then DeviceComponent.id (logical id) is present. It is specifically NOT allowed to have an id if the transaction is a create or conditional create. IF the PHG performs a FHIR "update interaction" the value of DeviceComponent.id shall be: "[system Id as 16-digit HEX string].[transport address]", where the transport address is <ul style="list-style-type: none"> • a 12-digit HEX string for Bluetooth without the 0x prefix • a 16-digit HEX string for ZigBee without the 0x prefix • a 4-digit VID HEX string followed by a 4-digit PID HEX string for USB separated by a dot without the 0x prefix. • If the transport address is not known, it shall be set to all 0s. c) DeviceComponent.meta.profile (profile) is present and it is set to "placeholder/phgDeviceComponent". d) DeviceComponent.identifier is present and: <ul style="list-style-type: none"> • DeviceComponent.identifier.use shall be set to "official". • DeviceComponent.identifier.system shall be set to "urn:oid:1.2.840.10004.1.1.1.0.0.1.0.0.1.2680". • DeviceComponent.identifier.value shall be set to a16-digit HEX string without the 0x prefix and with each byte separated by dashes (PHG System Id). e) DeviceComponent.type is present and: <ul style="list-style-type: none"> • DeviceComponent.type.coding.code shall be set to "531981" • DeviceComponent.type.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.type.coding.display shall include "MDC_MOC_VMS_MDS_AHD" plus optional text. • If an alternative coding is used this shall occur first. f) DeviceComponent.productionSpecification may be present, and if it present then: <ul style="list-style-type: none"> • DeviceComponent.productionSpecification.specType.coding.code shall be set to "531969" OR "531970" OR "531971" OR "531972" OR "531973" OR "531974" OR "531975" OR "531976" OR "531977" OR "531978". • DeviceComponent.productionSpecification.specType.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.productionSpecification.coding.display is strongly recommended and, if present, its value shall be the reference id of the value of 			

	<p>DeviceComponent.productionSpecification.coding.code (in parentheses) plus optional text: "MDC_ID_MODEL_NUMBER" (531969) OR "MDC_ID_MODEL_MANUFACTURER" (531970) OR "MDC_ID_PROD_SPEC_UNSPECIFIED" (531971) OR "MDC_ID_PROD_SPEC_SERIAL" (531972) OR "MDC_ID_PROD_SPEC_PART" (531973) OR "MDC_ID_PROD_SPEC_HW" (531974) OR "MDC_ID_PROD_SPEC_SW" (531975) OR "MDC_ID_PROD_SPEC_FW" (531976) OR "MDC_ID_PROD_SPEC_PROTOCOL" (531977) OR "MDC_ID_PROD_SPEC_GMDN" (531978).</p> <ul style="list-style-type: none"> • If an alternative coding is also used, this coding element (11073) shall occur first <p>g) IF the Production Specification is present and is one of: Unspecified (unspecified), Serial number (serial-number), Part number (part-number), Hardware revision (hardware-revision), Software revision (software-revision), Firmware revision (firmware-revision) or Protocol (protocol), THEN an additional productionSpecification.specType.coding entry MUST be added to the productionSpecification in f) and:</p> <ul style="list-style-type: none"> • DeviceComponent.productionSpecification.specType.coding.code shall be set to "unspecified" OR "serial-number" OR "part-number" OR "hardware-revision" OR "software-revision" OR "firmware-revision" OR "protocol". • DeviceComponent.productionSpecification.specType.coding.system shall be set to "http://hl7.org/fhir/specification-type". • DeviceComponent.productionSpecification.productionSpec shall be present and shall be the production spec value. <p>h) The Continua Version is present as a DeviceComponent.productionSpecification with:</p> <ul style="list-style-type: none"> • DeviceComponent.productionSpecification.specType.coding.code shall be set to "532352". • DeviceComponent.productionSpecification.specType.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.productionSpecification.coding.display is strongly recommended, if present, its value shall be "MDC_REG_CERT_DATA_CONTINUA_VERSION" plus any optional text. • DeviceComponent.productionSpecification.productionSpec shall be present and shall be the Continua (major version).(minor version). <p>i) The List of Continua Certified Transports and Specializations shall be present as a DeviceComponent.property, and:</p> <ul style="list-style-type: none"> • DeviceComponent.property.type.coding.code shall be set to "532353". • DeviceComponent.property.type.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.type.coding.display is strongly recommended, if present, its value shall be "MDC_REG_CERT_DATA_CONTINUA_CERT_DEV_LIST" plus any optional text. • For each certified specialization there shall be a DeviceComponent.property.valueCodeableConcept with: <ul style="list-style-type: none"> ▪ DeviceComponent.property.valueCodeableConcept.coding.code shall be set to Tcode * 8192 +16-bit mdc profile code – 4096, where: <ul style="list-style-type: none"> ✓ Tcode may be 0 (Continua version 1.0) OR 1 (USB) OR 2 BT HDP) OR 3 (ZB) OR 4 (BLE) OR 5 (NFC). ✓ 16-bit mdc profile code is the MDC_DEV_*_SPEC_PROFILE_* term code representing the specialization. ▪ DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "placeholder/fhir/reg-cert-codes". ▪ DeviceComponent.property.type.coding.display is optional.
--	---

- j) The List of Continua Certified H&FS Interfaces shall be present as a DeviceComponent.property, and:
- DeviceComponent.property.type.coding.code shall be set to "532355".
 - DeviceComponent.property.type.coding.system shall be set to "urn.iso.std.iso:11073:10101".
 - DeviceComponent.property.type.coding.display is strongly recommended and, if present, its value shall be "MDC_REG_CERT_DATA_CONTINUA_AHD_CERT_LIST" plus optional text
 - For each certified interface there shall be a DeviceComponent.property.valueCodeableConcept with:
 - DeviceComponent.property.valueCodeableConcept.coding.code shall be set to 0 (PCD-01 web services) OR 1 (Consent enabled PCD-01 web service) OR 2 (Capability exchange) OR 3 (PCD-01 upload using hData) OR 4 (Consent enabled PCD-01 using hData) OR 5 (Questionnaire CDA) OR 6 (Authenticated Persistent Sessions) OR 7 (FHIR resource upload).
 - DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "placeholder/fhir/reg-cert-wan-codes".
 - DeviceComponent.property.type.coding.display is strongly recommended and its value shall be one of (it shall match the code): "observation-upload-soap" (0) OR "consent-enabled-soap" (1) OR "capabilities" (2) OR "observation-upload-hdata" (3) OR "consent-enabled-hdata" (4) OR "questionnaire" (5) OR "aps" (6) OR "observation-upload-fhir" (7).
- k) The Regulation Status shall be present as a DeviceComponent.property, and:
- DeviceComponent.property.type.coding.code shall be set to "532354.0"
 - DeviceComponent.property.type.coding.system shall be set to ".placeholder/fhir/IEEE.ASN1".
 - DeviceComponent.property.type.coding.display is strongly recommended and, if present, its value shall be "regulation-bit-field" plus any optional text
 - DeviceComponent.property.valueCodeableConcept.coding.code shall be set to "y" (if set) "n" (if cleared).
 - DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "http://hl7.org/fhir/v2/0136".
 - DeviceComponent.property.type.coding.display shall be set to "unregulated" or "regulated" plus any optional text.
- l) Time synchronization shall be present as a DeviceComponent.property, and:
- DeviceComponent.property.name.coding.code shall be set to "68220".
 - DeviceComponent.property.name.coding.system shall be set to "urn.iso.std.iso:11073:10101".
 - DeviceComponent.property.name.coding.display is strongly recommended and, if present, its value shall be "MDC_TIME_SYNC_PROTOCOL" plus optional text.
 - If an alternative coding is also used, this coding element shall occur first.
 - DeviceComponent.property.valueCodeableConcept.coding.code shall be set 32-bit code of time synchronization method if synchronized otherwise 532224 (MDC_TIME_SYNC_NONE).
 - DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "urn.iso.std.iso:11073:10101".
 - DeviceComponent.property.type.coding.display is strongly recommended. If present, it shall be set to reference id of synchronization code (see Table A-29 of [b-HSTP-H812-FHIR]) plus any additional optional text
 - If an alternative coding is also used, this coding element shall occur first.
- m) Time synchronization accuracy may be present as a DeviceComponent.property, and, if present:

	<ul style="list-style-type: none"> • DeviceComponent.property.name.coding.code shall be set to "68221". • DeviceComponent.property.name.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.name.coding.display is strongly recommended, and, if present, its value shall be "MDC_TIME_SYNC_ACCURACY" plus any optional text. • If an alternative coding is also used, this coding element shall occur first. • DeviceComponent.property.valueQuantity.value shall be the accuracy in microseconds. • DeviceComponent.property.valueQuantity.unit shall be set to "us" (UCUM). • DeviceComponent.property.valueQuantity.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.valueQuantity.code shall be set to "264339". <p>n) Time resolution encoding may be present as a DeviceComponent.property, and, if present:</p> <ul style="list-style-type: none"> • DeviceComponent.property.name.coding.code shall be set to "68226". • DeviceComponent.property.name.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.name.coding.display is strongly recommended and, if present, its value shall be "MDC_TIME_RES_BO" plus any optional text. • If an alternative coding is also used, this coding element shall occur first. • DeviceComponent.property.valueQuantity.value shall be the resolution in microseconds. • DeviceComponent.property.valueQuantity.unit shall be set to "us" (UCUM). • DeviceComponent.property.valueQuantity.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.valueQuantity.code shall be set to "264339".
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for the PHG properties is as specified in [b-HSTP-H812-FHIR].
Notes	

TP Id		TP/HFS/SEN/FHIR/ENC/BV-001		
TP label		Sensor Properties Encoding		
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	SensorFHIR 1; M	SensorFHIR 2; C	SensorFHIR 3; M
		SensorFHIR 4; C	SensorFHIR 5; M	SensorFHIR 6; M
		SensorFHIR 7; M	SensorFHIR 8; M	SensorFHIR 9; O
		SensorFHIR 10; C	SensorFHIR 11; C	SensorFHIR 12; M
		SensorFHIR 13; M	SensorFHIR 14; M	SensorFHIR 15; O
		SensorFHIR 16; O	SensorFHIR 17; O	SensorFHIR 18; O
		SensorFHIR 19; C	SensorFHIR 20; O	SensorFHIR 21; O
		SensorFHIR 22; O	PHGCommon 29; M	

Test purpose	Check that: The FHIR resource representing the Sensor Properties is properly encoded.
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)
Other PICSS	
Initial condition	Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Sensor FHIR resource. 2. In the Sensor FHIR resource check that: <ol style="list-style-type: none"> a) resourceType is set to "DeviceComponent". b) IF the PHG performs a FHIR "update interaction", then DeviceComponent.id (logical id) is present. It is specifically NOT allowed to have an id if the transaction is a create or conditional create. IF the Logical Id is set by a FHIR "update interaction" the value of DeviceComponent.id shall be: "[system Id as 16-digit HEX string].[transport address]", where the transport address is <ul style="list-style-type: none"> • a 12-digit HEX string for Bluetooth without the 0x prefix • a 16-digit HEX string for ZigBee without the 0x prefix • a 4-digit VID HEX string followed by a 4-digit PID HEX string for a USB separated by a dot without the 0x prefix. • If the transport address is not known, it shall be set to all 0's. • If the system Id is not known, which may happen with some badly behaved BTLE devices, the 16-digit HEX string shall be set to all 0s. c) For the top-level DeviceComponent resource, DeviceComponent.identifier shall be present and: <ul style="list-style-type: none"> • DeviceComponent.identifier.use shall be set to "official". • DeviceComponent.identifier.system shall be set to "urn:oid:1.2.840.10004.1.1.1.0.0.1.0.0.1.2680". • DeviceComponent.identifier.value shall be set to a16-digit HEX string without the 0x prefix and with each byte separated by dashes. • if an additional identifier is used this one shall be first (multiple identifiers are allowed) d) For the top-level DeviceComponent resource, DeviceComponent.meta.profile shall be present and its value shall be "placeholder/placeholder/phdParentDeviceComponent" e) For the top-level DeviceComponent resource, DeviceComponent.type shall be present and: <ul style="list-style-type: none"> • DeviceComponent.type.coding.code shall be set to: <ul style="list-style-type: none"> ▪ $8 \times 2^{16} + \text{System-Type-Spec-List}[0].\text{type}$ for a device with a single specialization OR ▪ 528834 for a multi-specialization device • DeviceComponent.type.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.type.coding.display is strongly recommended and it shall contain: <ul style="list-style-type: none"> ▪ "MDC_DEV_*_SPEC_PROFILE_*" plus optional text for a device with a single specialization OR ▪ "MDC_DEV_SPEC_PROFILE_HYDRA" plus optional text for a multi-

	<p style="text-align: center;">specialization device</p> <ul style="list-style-type: none"> • If an alternative coding is also used, this coding element shall occur first <p>f) For the top-level DeviceComponent resource, DeviceComponent.meta.parent shall be present and shall point to a PHG-DeviceComponent.</p> <p>g) For the top-level DeviceComponent resource, Production Specification may be present as a DeviceComponent.productionSpecification element, and:</p> <ul style="list-style-type: none"> • DeviceComponent.productionSpecification.specType.coding.code shall be set to "531969" OR "531970" OR "531971" OR "531972" OR "531973" OR "531974" OR "531975" OR "531976" OR "531977" OR "531978". • DeviceComponent.productionSpecification.specType.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.productionSpecification.coding.display is strongly recommended and, if present, its value shall be the reference id of the value of DeviceComponent.productionSpecification.coding.code (in parentheses) plus optional text: "MDC_ID_MODEL_NUMBER" (531969) OR "MDC_ID_MODEL_MANUFACTURER" (531970) OR "MDC_ID_PROD_SPEC_UNSPECIFIED" (531971) OR "MDC_ID_PROD_SPEC_SERIAL" (531972) OR "MDC_ID_PROD_SPEC_PART" (531973) OR "MDC_ID_PROD_SPEC_HW" (531974) OR "MDC_ID_PROD_SPEC_SW" (531975) OR "MDC_ID_PROD_SPEC_FW" (531976) OR "MDC_ID_PROD_SPEC_PROTOCOL" (531977) OR "MDC_ID_PROD_SPEC_GMDN" (531978). • If an alternative coding is also used, this coding element (11073) shall occur first • DeviceComponent.productionSpecification.productionSpec shall be present and shall be the production spec value <p>h) IF the Production Specification is present and is one of: Unspecified (unspecified), Serial number (serial-number), Part number (part-number), Hardware revision (hardware-revision), Software revision (software-revision), Firmware revision (firmware-revision) or Protocol (protocol), THEN an additional productionSpecification.specType.coding entry MUST be added to the productionSpecification in g) and:</p> <ul style="list-style-type: none"> • DeviceComponent.productionSpecification.specType.coding.code shall be set to "unspecified" OR "serial-number" OR "part-number" OR "hardware-revision" OR "software-revision" OR "firmware-revision" OR "protocol". • DeviceComponent.productionSpecification.specType.coding.system shall be set to "http://hl7.org/fhir/specification-type". • DeviceComponent.productionSpecification.productionSpec shall be present and shall be the production spec value. <p>i) For the top-level DeviceComponent resource, the Continua Version is present as a DeviceComponent.productionSpecification with:</p> <ul style="list-style-type: none"> • DeviceComponent.productionSpecification.specType.coding.code shall be set to "532352". • DeviceComponent.productionSpecification.specType.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.productionSpecification.coding.display is strongly recommended, if present, its value shall be "MDC_REG_CERT_DATA_CONTINUA_VERSION" plus any optional text. • DeviceComponent.productionSpecification.productionSpec shall be present and shall be the Continua (major version).(minor version). <p>j) For the top-level DeviceComponent resource, the list of Continua Certified Transports and Specializations shall be present as a DeviceComponent.property, and:</p> <ul style="list-style-type: none"> • DeviceComponent.property.type.coding.code shall be set to "532353". • DeviceComponent.property.type.coding.system shall be set to "urn.iso.std.iso:11073:10101".
--	---

	<ul style="list-style-type: none"> • DeviceComponent.property.type.coding.display is strongly recommended, if present, its value shall be "MDC_REG_CERT_DATA_CONTINUA_CERT_DEV_LIST" plus any optional text. • For each certified specialization there shall be a DeviceComponent.property.valueCodeableConcept with: <ul style="list-style-type: none"> ▪ DeviceComponent.property.valueCodeableConcept.coding.code shall be set to Tcode * 8192 +16-bit mdc profile code – 4096, where: <ul style="list-style-type: none"> ✓ Tcode may be 0 (Continua version 1.0) OR 1 (USB) OR 2 (BT HDP) OR 3 (ZB) OR 4 (BLE) OR 5 (NFC). ✓ 16-bit MDC profile code is the MDC_DEV_*_SPEC_PROFILE_* term code representing the specialization. ▪ DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "placeholder/fhir/reg-cert-codes". ▪ DeviceComponent.property.type.coding.display is optional. <p>k) For the top-level DeviceComponent resource, the Regulation Status shall be present as a DeviceComponent.property, and:</p> <ul style="list-style-type: none"> • DeviceComponent.property.type.coding.code shall be set to "532354.0" • DeviceComponent.property.type.coding.system shall be set to ".placeholder/fhir/IEEE.ASN1". • DeviceComponent.property.type.coding.display is strongly recommended and, if present, its value shall be "regulation-bit-field" plus any optional text. • DeviceComponent.property.valueCodeableConcept.coding.code shall be set to "y" (if set) "n" (if cleared). • DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "http://hl7.org/fhir/v2/0136". • DeviceComponent.property.type.coding.display shall be set to "unregulated" or "regulated" plus any optional text. <p>l) For the top-level DeviceComponent resource, time synchronization shall be present as a DeviceComponent.property, and:</p> <ul style="list-style-type: none"> • DeviceComponent.property.name.coding.code shall be set to "68220". • DeviceComponent.property.name.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.name.coding.display is strongly recommended and, if present, its value shall be "MDC_TIME_SYNC_PROTOCOL" plus optional text. • If an alternative coding is also used, this coding element shall occur first. • DeviceComponent.property.valueCodeableConcept.coding.code shall be set 32-bit code of time synchronization method if synchronized otherwise 532224 (MDC_TIME_SYNC_NONE). • DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.type.coding.display is strongly recommended. If present, it shall be set to reference id of synchronization code (see Table A-29 of [b-HSTP-H812-FHIR]) plus any additional optional text • If an alternative coding is also used, this coding element shall occur first. <p>m) For the top-level DeviceComponent resource, time synchronization accuracy may be present as a DeviceComponent.property and, if present:</p> <ul style="list-style-type: none"> • DeviceComponent.property.name.coding.code shall be set to "68221". • DeviceComponent.property.name.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.name.coding.display is strongly recommended, and, if present, its value shall be "MDC_TIME_SYNC_ACCURACY" plus any optional
--	--

	<p>text.</p> <ul style="list-style-type: none"> • If an alternative coding is also used, this coding element shall occur first. • DeviceComponent.property.valueQuantity.value shall be the accuracy in microseconds. • DeviceComponent.property.valueQuantity.unit shall be set to "us" (UCUM). • DeviceComponent.property.valueQuantity.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.valueQuantity.code shall be set to "264339". <p>n) For the top-level DeviceComponent resource, the sensor time capabilities may be reported as a DeviceComponent.property and, if present:</p> <ul style="list-style-type: none"> • DeviceComponent.property.type.coding.code shall be set to "68219.i". • DeviceComponent.property.type.coding.system shall be set to "placeholder/fhir/IEEE.ASN1" (placeholder). • DeviceComponent.property.type.coding.display is strongly recommended and, if present, its value shall be the ASN.1 name from Table A-32 of [b-HSTP-H812-FHIR], plus any optional text. • DeviceComponent.property.valueCodeableConcept.coding.code shall be set "y" (if set) "n" (if cleared). • DeviceComponent.property.valueCodeableConcept.coding.system shall be set to "http://hl7.org/fhir/v2/0136". • DeviceComponent.property.type.coding.display is an optional text <p>o) For the top-level DeviceComponent resource, time resolution encoding may be present as a DeviceComponent.property, and, if present:</p> <ul style="list-style-type: none"> • DeviceComponent.property.name.coding.code shall be set to "68226". • DeviceComponent.property.name.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.name.coding.display is strongly recommended and, if present, its value shall be "MDC_TIME_RES_BO" plus any optional text. • If an alternative coding is also used, this coding element shall occur first. • DeviceComponent.property.valueQuantity.value shall be the resolution in microseconds. • DeviceComponent.property.valueQuantity.unit shall be set to "us" (UCUM). • DeviceComponent.property.valueQuantity.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.property.valueQuantity.code shall be set to "264339". <p>p) If there are multiple specializations or when there are specialization sub-profiles, there will be a child DeviceComponent resource for each specialization or sub-profile in which:</p> <ul style="list-style-type: none"> • DeviceComponent.meta.profile shall be present and its value shall be "placeholder/placeholder/phdChildDeviceComponent". • DeviceComponent.parent shall be present and shall point to its parent DeviceComponent resource. • DeviceComponent.type.coding.code shall be present and contain the specialization or sub-profile information. • DeviceComponent.type.coding.system shall be set to "urn.iso.std.iso:11073:10101". • DeviceComponent.type.coding.display is strongly recommended and, if present, it shall contain the MDC code for the specialization or sub-profile plus optional text. <p>q) MDS Battery-Level may reported in an Observation resource. If present, it will be encoded as shown below:</p>
--	--

	<ul style="list-style-type: none"> • Observation.<i>identifier</i> is optional (value is always current). • Observation.<i>status</i> shall be set to "final". • Observation.code.coding.<i>code</i> shall be set to "67996". • Observation.code.coding.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.<i>display</i> is strongly recommended and, if present, it shall be set to "MDC_ATTR_VAL_BATT_CHARGE" plus optional text. • If an alternative coding is also used, this coding element shall occur first • Observation.<i>subject</i> shall contain a reference to the Patient Resource • Observation.<i>effectiveDateTime</i> shall contain the time of the PHG including offset to UTC at which the battery attribute was read or the value was received. • Observation.valueQuantity.<i>value</i> shall be Battery-Level.<i>value</i>. • Observation.valueQuantity.<i>unit</i> is strongly recommended to be present and shall be "%". • Observation.valueQuantity.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". • Observation.valueQuantity.<i>code</i> shall be set to "262688". • Observation.<i>device</i> shall point to the parent DeviceComponent resource. <p>r) MDS Remaining-Battery-Time may be reported in an Observation resource, if present, it will be encoded as shown below:</p> <ul style="list-style-type: none"> • Observation.<i>identifier</i> is optional (value is always current). • Observation.<i>status</i> shall be set to "final". • Observation.code.coding.<i>code</i> shall be set to "67956". • Observation.code.coding.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.<i>display</i> is strongly recommended, and, if present, it shall be set to "MDC_ATTR_TIME_BATT_REMAIN" plus optional text. • If an alternative coding is also used, this coding element shall occur first. • Observation.<i>subject</i> shall contain a reference to the Patient Resource. • Observation.<i>effectiveDateTime</i> shall contain the time of the PHG including offset to UTC at which the battery time remaining attribute was read or the value was received. • Observation.valueQuantity.<i>value</i> shall be the Remaining-Battery-Time.<i>value</i> • Observation.valueQuantity.<i>unit</i> is strongly recommended and shall be either min (minutes), hr (hours), or days. • Observation.valueQuantity.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101" • Observation.valueQuantity.<i>code</i> shall be set to $4 \times 2^{16} + \text{Remaining-Battery-Time}$.<i>unit</i> (where Remaining-Battery-Time.<i>unit</i> is MDC_DIM_MIN (minutes), MDC_DIM_HR (hours), or MDC_DIM_DAY (days)). • Observation.<i>device</i> shall point to the parent DeviceComponent resource. <p>s) MDS Power-Status may be reported in an Observation resource. If present, it will be encoded as shown below:</p> <ul style="list-style-type: none"> • Observation.<i>identifier</i> is optional (value is always current). • Observation.<i>status</i> shall be set to "final". • Observation.code.coding.<i>code</i> shall be set to "67925". • Observation.code.coding.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.<i>display</i> is strongly recommended and, if present, it shall be set to "MDC_ATTR_POWER_STAT" plus optional text. • If an alternative coding is also used, this coding element shall occur first. • Observation.<i>subject</i> shall contain a reference to the Patient Resource.
--	---

	<ul style="list-style-type: none"> • Observation.<i>effectiveDateTime</i> shall contain the time of the PHG including offset to UTC at which the battery time remaining attribute was read or the value was received. • Observation.<i>value[x]</i> shall not be reported. • Observation.<i>device</i> shall point to the parent DeviceComponent resource. • For each bit that is defined and reported there is an Observation.component element (only set values shall be reported): <ul style="list-style-type: none"> ▪ Observation.component.code.coding.code shall be set to <i>ASN1code = nomenclatureCode.bitPosition</i> (Table A-46 of [b-HSTP-H812-FHIR]), where: <ul style="list-style-type: none"> ✓ <i>bitsValue</i> = Enum-Observed-Value-Basic-Bit-Str or (16-bits) = Enum-Observed-Value-Simple-Bit-Str or (32-bits) = Enum-Observed-Value-EnumVal.enum-bit-str (always 32 bit) ✓ <i>nomenclatureCode</i> = procedure from Measurement Type section ✓ <i>bitPosition</i> = Mder Bit to be reported from 0 to 15/31 ▪ Observation.component.code.coding.system shall be set to "placeholder/fhir/IEEE.ASN1" ▪ Observation.component.code.coding.display is optional and if present shall be "onMains" OR "onBattery" OR "chargingFull" OR "chargingTrickle" OR "chargingOff". ▪ Observation.component.valueCodeableConcept.code.coding.code shall be set "y" if set, "n" if cleared. ▪ Observation.component.valueCodeableConcept.code.coding.system shall be set to "http://hl7.org/fhir/v2/0136". ▪ Observation.component.valueCodeableConcept.code.coding.display is optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for the Sensor properties is as specified in [b-HSTP-H812-FHIR].
Notes	

TP Id	TP/HFS/SEN/FHIR/ENC/BV-002			
TP label	Coincident Time Stamp Encoding			
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	CoincTS 1; O	CoincTS 2; C	CoincTS 3; M
		CoincTS 4; M	CoincTS 5; C	CoincTS 6; C
CoincTS 7; C		CoincTS 8; C	PHGCommon 30; M	
Test purpose	Check that: The FHIR resource representing the Coincident Time Stamp is properly encoded.			
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)			
Other PICSS				
Initial condition	Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0			

	bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Coincident Time Stamp FHIR resource. 2. In the Coincident Time Stamp FHIR resource check that: <ol style="list-style-type: none"> a) resourceType is set to "Observation". b) If a logical id is needed, the Observation.id shall be populated with a temporary id. c) Observation.status shall be set to "final". d) Observation.meta.profile shall be set to "placeholder/phdCoincidentTimeStampObservation". e) If the sensor uses Absolute Time, the coincident time stamp shall be encoded as follows: <ul style="list-style-type: none"> • Observation.code.coding.code shall be set to "67975". • Observation.code.coding.system shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended, and, if present, it shall be set to "MDC_ATTR_TIME_ABS" plus optional text. • If an alternative coding is also used, this coding element shall occur first. • Observation.effectiveDateTime shall contain the current time of the PHG including offset to UTC at the time of reading the sensor current time. • Observation.valueDateTime shall contain the date-and-Time converted to a FHIR dateTime data type: <ul style="list-style-type: none"> ▪ This element is absent if there is a time fault. ▪ This element is set to the effectiveDateTime if the PHG set the sensor time and the set is successful f) If the sensor uses Base Offset Time, the coincident time stamp shall be encoded as follows: <ul style="list-style-type: none"> • Observation.code.coding.code shall be set to "68226". • Observation.code.coding.system shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended, and, if present, it shall be set to "MDC_ATTR_TIME_BO" plus optional text. • If an alternative coding is also used, this coding element shall occur first. • Observation.effectiveDateTime shall contain the current time of the PHG including offset to UTC at the time of reading the sensor current time. • Observation.valueDateTime shall contain the Base-Offset-Time converted to a FHIR dateTime data type: <ul style="list-style-type: none"> ▪ This element is absent if there is a time fault. ▪ This element is set to the effectiveDateTime if the PHG set the sensor time and the set is successful. g) If the sensor uses Relative Time, the coincident time stamp shall be encoded as follows: <ul style="list-style-type: none"> • Observation.code.coding.code shall be set to "67983". • Observation.code.coding.system shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended, and, if present, it shall be set to "MDC_ATTR_TIME_REL" plus optional text • If an alternative coding is also used, this coding element shall occur first. • Observation.effectiveDateTime shall contain the current time of the PHG including offset to UTC at the time of reading the sensor current time. • If there is no time fault: <ul style="list-style-type: none"> ▪ Observation.valueQuantity.value shall be set to Relative-Time * 125 (to

	<p>convert to microseconds)</p> <ul style="list-style-type: none"> ▪ Observation.valueQuantity.<i>unit</i> shall be set to "us" ▪ Observation.valueQuantity.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". ▪ Observation.valueQuantity.<i>code</i> shall be set to "264339" <p>h) If the sensor uses High Resolution Relative Time, the coincident time stamp shall be encoded as follows:</p> <ul style="list-style-type: none"> • Observation.code.coding.<i>code</i> shall be set to "68072". • Observation.code.coding.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.<i>display</i> is strongly recommended and, if present, it shall be set to ""MDC_ATTR_TIME_REL_HI_RES" plus optional text. • If an alternative coding is also used, this coding element shall occur first • Observation.<i>effectiveDateTime</i> shall contain the current time of the PHG including offset to UTC at the time of reading the sensor current time. • If there is no time fault: <ul style="list-style-type: none"> ▪ Observation.valueQuantity.<i>value</i> shall be set to HiRes-Relative-Time which is in microseconds ▪ Observation.valueQuantity.<i>unit</i> shall be set to "us". ▪ Observation.valueQuantity.<i>system</i> shall be set to "urn.iso.std.iso:11073:10101". ▪ Observation.valueQuantity.<i>code</i> shall be set to "264339".
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for the Coincident Time Stamp is as specified in [b-HSTP-H812-FHIR].
Notes	

TP Id	TP/HFS/SEN/FHIR/ENC/BV-003			
TP label	Measurements Encoding: general and specific metric attributes			
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	MeasGen 1; M	MeasGen 2; M	MeasGen 3; O
		MeasGen 4; O	MeasGen 5; O	MeasGen 6; C
		MeasGen 7; M	MeasGen 8; M	MeasGen 9; M
		MeasGen 10; C	MeasGen 11; C	MeasGen 12; C
		MeasGen 13; C	MeasGen 14; C	MeasGen 15; C
		MeasPOX 1; C	MeasPOX 2; C	MeasPOX 3; C
		MeasAM 1; C	MeasCGM 1; C	MeasCGM 2; C
		MeasCGM 3; C	PHGCommon 31;M	
Test purpose	Check that: General and specific metric attributes in an FHIR Measurement are properly encoded.			
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)			

Other PICSS	
Initial condition	<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource. 2. In the Measurement FHIR resource check that: <ol style="list-style-type: none"> a) resourceType is set to "Observation". b) Measurement Type shall be present and shall be coded as: <ul style="list-style-type: none"> • Observation.code.coding.code shall be set to $partition \times 2^{16} + termCode$, where <ul style="list-style-type: none"> ▪ $termCode = Type.code$ ▪ $partition = Type.partition$ ▪ IF Metric-Id or Nu-Observed-Value or Enum-Observed-Value attribute exists: <ul style="list-style-type: none"> ✓ IF Nu-Observed-Value or Enum-Observed-Value exists: <ul style="list-style-type: none"> $termCode = Nu-Observed-Value.metric-id$ OR $termCode = Enum_Observed-Value.metric-id$ ELSE IF Metric-Id is present: <ul style="list-style-type: none"> $termCode = Metric-Id$ ✓ IF Metric-Id-Partition exists: <ul style="list-style-type: none"> $partition = Metric-Id-Partition$ • Observation.code.coding.system shall be set to "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended and, if present, it shall be set to Reference Id for the code plus optional text. • If an alternative coding is also used, this coding element shall occur first. • If the measurement type is a vital sign, FHIR requires a translation to LOINC, which shall come second, and will be encoded as follows: • Observation.code.coding.code shall be set to the LOINC code for the above vital sign. • Observation.code.coding.system shall be set to "http://loinc.org". • Observation.code.coding.display is optional text. c) The PHG may report non-relative time stamps (Absolute, Base Offset and PHG Received), and it will encode them as follows if there is no Measure-Active-Period attribute: <ul style="list-style-type: none"> • Observation.effectiveDateTime shall be present and set to $effectiveDateTime = finalTimeStamp$, where: <ul style="list-style-type: none"> ▪ IF Absolute-Time-Stamp: $finalTimeStamp = Absolute-Time-Stamp$ encoded as YYYY-MM-DDTHH:MM:SS[.ss] +/-ZZ:zz, where +/-ZZ:zz is the offset from local time to UTC obtained from the PHG, and [.ss] shall be excluded if the time stamp has no fractional seconds or the time resolution is \geq to one second. ▪ IF Base-Offset-Time-Stamp: $finalTimeStamp = Base-Offset-Time-Stamp$ encoded as YYYY-MM-DDTHH:MM:SS[.ss] +/-ZZ:zz, where [.ss] shall be excluded if the time stamp has no fractional seconds or the time resolution is \geq to one second. ▪ IF there is no time stamp: $finalTimeStamp = PHG$ time of reception encoded as YYYY-MM-DDTHH:MM:SS.sss +/-ZZ:zz d) The PHG may report non-relative time stamps (Absolute, Base Offset and PHG Received), and it will encode them as follows if there is a Measure-Active-Period attribute:

	<ul style="list-style-type: none"> • Observation.effectivePeriod.Start shall be present and set to <i>start = finalTimeStamp</i>, where: <ul style="list-style-type: none"> ▪ IF Absolute-Time-Stamp: <i>finalTimeStamp</i> = Absolute-Time-Stamp encoded as YYYY-MM-DDTHH:MM:SS[.ss] +/-ZZ:zz, where +/-ZZ:zz is the offset from local time to UTC obtained from the PHG, and [.ss] shall be excluded if the time stamp has no fractional seconds or the time resolution is >= to one second. ▪ IF Base-Offset-Time-Stamp: <i>finalTimeStamp</i> = Base-Offset-Time-Stamp encoded as YYYY-MM-DDTHH:MM:SS[.ss] +/-ZZ:zz, where [.ss] shall be excluded if the time stamp has no fractional seconds or the time resolution is >= to one second. • Observation.effectivePeriod.End shall be present and set to <i>finalTimeStamp + Measure-Active-Period</i> with precision indicated by the Mder FLOAT, and encoded as a FHIR dateTime data type. <p>e) The PHG may report relative time stamps, and it will encode them as follows:</p> <ul style="list-style-type: none"> • If there is no Measure-Active-Period attribute: <ul style="list-style-type: none"> ▪ Observation.effectivePeriod.effectiveDateTime shall be set to <i>wallclockMeasurementTime</i> from Table A-54 of [b-HSTP-H812-FHIR]. • If there is a Measure-Active-Period attribute: <ul style="list-style-type: none"> ▪ Observation.effectivePeriod.Start shall be present and set to <i>start = wallclockMeasurementTime</i> from Table A-54 of [b-HSTP-H812-FHIR]. ▪ Observation.effectivePeriod.End shall be present and set to <i>end = wallclockDurationTime</i> from Table A-54 of [b-HSTP-H812-FHIR]. <p>f) If there is a time stamp reported by the sensor, there shall be an Observation.related.target element pointing to the appropriate Coincident Time Stamp Observation resource.</p> <p>g) Observation.identifier.value shall be present and set as in section A.6.7 [b-HSTP-H812-FHIR].</p> <p>h) Observation.status shall be present and set to "final" or "preliminary" (if a measurement status of "early indication").</p> <p>i) Observation.device shall point to the top-level DeviceComponent resource.</p> <p>j) If an error or special value is reported in the observation, one of the following elements will be encoded with values according to Table A-57 of [b-HSTP-H812-FHIR]:</p> <ul style="list-style-type: none"> • Observation.value[x] • Observation.dataAbsentReason <p>k) If PHG reports a Source-Handle-Reference or Source-Handle-Reference-List attribute, it shall encode it as:</p> <ul style="list-style-type: none"> • Observation.related.target set to the URL to Observation being referenced. <p>l) If Supplemental Types attribute is present, then for each supplemental types there is an Observation.component element, encoded as:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.code shall be present and set to "68193". • Observation.component.code.coding.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_SUPPLEMENTAL_TYPES" plus any optional text. • If an alternative coding system is used, this element shall occur first. • Observation.component.valueCodeableConcept.coding.code shall be set to Supplemental-Types[n].partition x 2¹⁶ + SupplementalTypes[n].termCode. • Observation.component.valueCodeableConcept.coding.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.valueCodeableConcept.coding.display is strongly
--	---

	<p>recommended. If present, it shall be set to the reference id corresponding to the code plus optional text</p> <ul style="list-style-type: none"> • If an alternative coding system is used, this element shall occur first. <p>m) If Accuracy attribute is present, it shall be encoded as an Observation.component element:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.code shall be present and set to "67914". • Observation.component.code.coding.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_NU_ACCUR_MSMT" plus any optional text. • If an alternative coding system is used, this element shall occur first • Observation.component.valueQuantity.value shall be set to the Accuracy decoded from the FLOAT with the precision given by the respective Mder encoding. • Observation.component.valueQuantity.units is strongly recommended. If present, it shall be set to the UCUM string for the unit code. • Observation.component.valueQuantity.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.valueQuantity.code shall be set to Observation.valueQuantity.code or in the compound case the unit code associated with the compound value. <p>n) If Relative Time Stamp attribute is present, it shall be encoded as an Observation.component element:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.code shall be present and set to "67985". • Observation.component.code.coding.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_TIME_STAMP_REL" plus any optional text. • If an alternative coding system is used, this element shall occur first. • Observation.component.valueQuantity.value shall be set to Relative-Time-Stamp * 125. • Observation.component.valueQuantity.units shall be set to "us" (microseconds). • Observation.component.valueQuantity.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.valueQuantity.code shall be set to "264339". <p>o) If HiRes Relative Time Stamp attribute is present, it shall be encoded as an Observation.component element:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.code shall be present and set to "68073". • Observation.component.code.coding.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_TIME_STAMP_REL_HI_RES" plus any optional text. • If an alternative coding system is used, this element shall occur first. • Observation.component.valueQuantity.value shall be set HiRes-Time-Stamp. • Observation.component.valueQuantity.units shall be set to "us". • Observation.component.valueQuantity.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.valueQuantity.code shall be set to "264339".
--	---

3. Ask the PHG to upload a new FHIR resource bundle that contains a Pulse Oximeter Measurement FHIR resource in which the sensor reports Alert-Op-State, Current-Limits and Alert-Op-Text attributes.
4. In the Measurement FHIR resource check that:
 - a) If Alert-Op-State attribute is present, it shall be encoded as follows:
 - For each bit to be mapped there is an Observation.component element, encoded as:
 - Observation.component.code.coding.code shall be present and set to "68746.0" OR "68746.1" OR "68746.2".
 - Observation.component.code.coding.system shall be set to "placeholder/fhir/IEEE.ASN1".
 - Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "lim-alert-off" OR "lim-low-off" OR "lim-high-off" plus optional text.
 - Observation.component.valueCodeableConcept.coding.code shall be set to "y" if set, "n" if cleared.
 - Observation.component.valueCodeableConcept.coding.system shall be set to "http://hl7.org/fhir/v2/0136".
 - Observation.component.valueCodeableConcept.coding.display is some optional text.
 - b) If Current-Limits attribute is present, it shall be encoded as an Observation.component element as follows:
 - Observation.component.code.coding.code shall be present and set to "67892".
 - Observation.component.code.coding.system shall be set to "placeholder/fhir/IEEE.ASN1".
 - Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_LIMIT_CURR" plus optional text.
 - Observation.component.valueRange.low.value shall be set to Current-Limits.lower coded to a FHIR decimal with the precision of the Mder FLOAT
 - Observation.component.valueRange.low.unit is strongly recommended, if present shall be set to UCUM code of the Unit-Code attribute.
 - Observation.component.valueRange.low.system shall be set to "urn:iso:std:iso:11073:10101".
 - Observation.component.valueRange.low.code shall be set to $4 \times 2^{16} + \text{Unit-Code}$
 - Observation.component.valueRange.high.value shall be set to Current-Limits.upper coded to a FHIR decimal with the precision of the Mder FLOAT.
 - Observation.component.valueRange.high.unit is strongly recommended, if present shall be set to UCUM code of the Unit-Code attribute.
 - Observation.component.valueRange.high.system shall be set to $4 \times 2^{16} + \text{Unit-Code}$.
 - Observation.component.valueRange.high.code shall be set to $4 \times 2^{16} + \text{Unit-Code}$.
 - c) If Alert-Op-Text attribute is present, it shall be encoded as an Observation.component as follows:
 - Observation.component.code.coding.code shall be present and set to "68104".
 - Observation.component.code.coding.system shall be set to "urn:iso:std:iso:11073:10101".
 - Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_AL_OP_TEXT_STRING" plus optional text.
 - If an alternative coding system is used, this element shall occur first.

	<ul style="list-style-type: none"> • Observation.<i>valueString</i> shall contain the information from the Alert-Op-Text.<i>lower_text</i> and Alert-Op-Text.<i>upper_text</i> presented in an application dependent manner. <p>5. Ask the PHG to upload a new FHIR resource bundle that contains a Medication Monitor Measurement FHIR resource in which the sensor reports the Context-Key attribute.</p> <p>6. In the Measurement FHIR resource check that:</p> <p>a) If Context-Key attribute is present, it shall be encoded as an Observation.component element as follows:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.<i>code</i> shall be present and set to "68216". • Observation.component.code.coding.<i>system</i> shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.code.coding.<i>display</i> is strongly recommended. If present, it shall be set to "MDC_ATTR_CONTEXT_KEY" plus optional text. • Observation.component.valueCodeableConcept.coding.<i>code</i> shall be set to the Context-Key as a 16-digit Hexadecimal string. • Observation.component.valueCodeableConcept.coding.<i>system</i> shall be set to "urn:oid:1.2.840.10004.1.1.1.0.0.1.0.0.1.2680". • Observation.component.valueCodeableConcept.coding.<i>display</i> is some optional text. <p>7. Ask the PHG to upload a new FHIR resource bundle that contains a Continuous Glucose Monitor Measurement FHIR resource in which the sensor reports the Measurement-Confidence-95, Threshold-Notification-Text-String and Measurement Status alert attributes.</p> <p>8. In the Measurement FHIR resource check that:</p> <p>a) If Measurement-Confidence-95 attribute is present, it shall be encoded as an Observation.component element as follows:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.<i>code</i> shall be present and set to "526988". • Observation.component.code.coding.<i>system</i> shall be set to "placeholder/fhir/IEEE.ASN1". • Observation.component.code.coding.<i>display</i> is strongly recommended. If present, it shall be set to "MDC_ATTR_MSMT_CONFIDENCE_95" plus optional text. • Observation.component.valueRange.low.<i>value</i> shall be set to Measurement-Confidence-95.<i>lower</i> coded to a FHIR decimal with the precision of the Mder FLOAT. • Observation.component.valueRange.low.<i>unit</i> is strongly recommended, if present shall be set to UCUM code of the Unit-Code attribute. • Observation.component.valueRange.low.<i>system</i> shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.valueRange.low.<i>code</i> shall be set to $4 \times 2^{16} + \text{Unit-Code}$. • Observation.component.valueRange.high.<i>value</i> shall be set to Measurement-Confidence-95.<i>upper</i> coded to a FHIR decimal with the precision of the Mder FLOAT. • Observation.component.valueRange.high.<i>unit</i> is strongly recommended, if present shall be set to UCUM code of the Unit-Code attribute • Observation.component.valueRange.high.<i>system</i> shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.valueRange.high.<i>code</i> shall be set to $4 \times 2^{16} + \text{Unit-Code}$. <p>b) IF Alert-Op-Text attribute is present, it may be included in the Observation.<i>text</i> element or it may be encoded as an Observation.component as follows:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.<i>code</i> shall be present and set to "68232".
--	---

	<ul style="list-style-type: none"> • Observation.component.code.coding.system shall be set to "urn:iso:std:iso:11073:10101". • Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "MDC_ATTR_THRES_NOTIF_TEXT_STRING" plus optional text. • Observation.valueString shall contain the Threshold-Notification-Text-String. <p>c) If Measurement Status Alert attribute is present, it shall be encoded as follows:</p> <ul style="list-style-type: none"> • For each bit to be mapped there is an Observation.component element, encoded as: <ul style="list-style-type: none"> ▪ Observation.component.code.coding.code shall be present and set to "133447.14" or "133447.15". ▪ Observation.component.code.coding.system shall be set to "placeholder/fhir/IEEE.ASN1". ▪ Observation.component.code.coding.display is strongly recommended. If present, it shall be set to "msmt-state-in-alarm" OR "msmt-state-al-inhibited" plus optional text. ▪ Observation.component.valueCodeableConcept.coding.code shall be set to "y" if set, "n" if cleared. ▪ Observation.component.valueCodeableConcept.coding.system shall be set to "http://hl7.org/fhir/v2/0136". ▪ Observation.component.valueCodeableConcept.coding.display may be present as some optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for general and specific metric attributes of ISO/IEEE 11073 measurements is as specified in [b-HSTP-H812-FHIR].
Notes	

TP Id	TP/HFS/SEN/FHIR/ENC/BV-004		
TP label	Measurements Encoding: non-compound numeric values		
Coverage	Spec	[b-HSTP-H812-FHIR]	
	Testable items	MeasNCNum 1; M	MeasNCNum 2; M
		MeasGen 2; M	PHGCommon 31;M
Test purpose	Check that: The FHIR resource representing a measurement with a non-compound numeric value is properly encoded.		
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)		
Other PICSS			
Initial condition	Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.		
Test procedure	<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource with a non-compound numeric value 2. In the Measurement FHIR resource check that: 		

3. Once the measurement is received, the simulated H&FS checks that an Observation resource ("resourceType":"Observation") with Observation.meta.profile = "placeholder/phdNumericObservation" is present.
4. In this resource, check that:
- a) Observation.code is present and:
- Observation.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where:
 - $termCode = Type.code$
 - $partition = Type.partition$
 - IF Nu-Observed-Value exists then $termcode = Nu-Observed-Value.metric-id$ ELSE IF *Metric-Id* is present then $termcode = Metric-Id$.
 - IF *Metric-Id-Partition* is present then $partition = Metric-Id-Partition$.
 - Observation.code.coding.system is present and its value is "urn.iso.std.iso:11073:10101".
 - Observation.code.coding.display is strongly recommended, and its value is the Reference Id for the code plus optional text.
 - If an alternative coding is also used, this coding element shall occur first.
- IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:
- b) A second Observation.code.coding is present and:
- Observation.code.coding.code is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]).
 - Observation.code.coding.system is present and its value is "http://loinc.org".
 - Observation.code.coding.display is optional and it contains optional text.
 - This coding element shall occur second.
- IF there is no error or no special value is reported:
- c) Observation.valueQuantity is present
- Observation.valueQuantity.value is present and it contains a <string> representing the value of Basic-Nu-Observed-Value, Simple-Nu-Observed-Value or Nu-Observed-Value decoded from SFLOAT or FLOAT with the precision given by the respective Mder encoding (see Table A-42 of [b-HSTP-H812-FHIR]).
 - Observation.valueQuantity.unit is strongly recommended and it contains the UCUM string for the unit code.
 - Observation.valueQuantity.code is present and its value is $4 \times 2^{16} + unitTermCode$, where
 - $unitTermCode = Unit-Code$
 - IF Nu-Observed-Value is reported THEN $unitTermCode = Nu-Observed-Value.unit$.
 - Observation.valueQuantity.system is present and its value is "urn.iso.std.iso:11073:10101".
 - Observation.valueQuantity.display is strongly recommended and its value shall contain a reference id for the code plus optional code.
- IF there is an error or a special value is reported:
- d) Observation.dataAbsentReason is present
- Observation.dataAbsentReason.coding.code is present and its value is one of the FHIR codes defined in "https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html".
 - Observation.dataAbsentReason.coding.system is present and its value is "http://hl7.org/fhir/data-absent-reason".
 - Observation.dataAbsentReason.coding.display is optional and its value some optional text.

Pass/Fail criteria	<ul style="list-style-type: none"> FHIR resource encoding for the Observation resource is as described in step 4. If the dataAbsentReason is present, the valueQuantity shall be absent If the valueQuantity is present, the dataAbsentReason shall be absent
Notes	This encoding applies to Basic-Nu-Observed-Value (contains an Mder SFLOAT), Simple-Nu-Observed-Value (contains an Mder FLOAT) or Nu-Observed-Value (value element is an Mder FLOAT)

TP Id	TP/HFS/SEN/FHIR/ENC/BV-005		
TP label	Measurements Encoding: compound numeric values		
Coverage	Spec	[b-HSTP-H812-FHIR]	
	Testable items	MeasCNum 1; M	MeasCNum 2; M
		PHGCommon 31;M	MeasGen 2; M
Test purpose	<p>Check that:</p> <p>The FHIR resource representing a measurement with a compound numeric value is properly encoded.</p>		
Applicability	C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)		
Other PICSS			
Initial condition	<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>		
Test procedure	<ol style="list-style-type: none"> Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource containing a compound numeric value. Once the measurement is received, the simulated H&FS checks that an Observation resource ("resourceType":"Observation") with Observation.meta.profile = "placeholder/phdCompoundNumericObservation" is present. In this resource check that <ol style="list-style-type: none"> Observation.code is present and: <ul style="list-style-type: none"> Observation.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where: <ul style="list-style-type: none"> $termCode = Type.code$. $partition = Type.partition$. Observation.code.coding.system is present and its value is "urn.iso.std.iso:11073:10101". Observation.code.coding.display is strongly recommended, and its value is the Reference Id for the code plus optional text. If an alternative coding is also used, this coding element shall occur first. <p>IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:</p> A second Observation.code.coding is present and: <ul style="list-style-type: none"> Observation.code.coding.code is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]). Observation.code.coding.system is present and its value is "http://loinc.org". 		

- Observation.code.coding.display is optional and it contains optional text.
- This coding element shall occur second.

c) Observation.value[x] shall not be encoded.

d) Observation.dataAbsentReason shall not be encoded.

In this resource, check that for each of the N sub-values of the Metric-Id list:

e) An Observation.component is present.

f) Observation.component.code is present and:

- Observation.component.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where:
 - $termCode = Metric-Id-List[n].value$
 - $partition = Type.partition$
 - IF Compound-Nu-Observed-Value exists then $termcode = Compound-Nu-Observed-Value[n].metric-id$.
 - IF *Metric-Id-Partition* is present then $partition = Metric-Id-Partition$.
- Observation.component.code.coding.system is present and its value is "urn.iso.std.iso:11073:10101".
- Observation.component.code.coding.display is strongly recommended, and its value is the Reference Id for the code plus optional text.
- If an alternative coding is also used, this coding element shall occur first.

IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:

g) A second Observation.component.code.coding is present and:

- Observation.component.code.coding.code is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]).
- Observation.component.code.coding.system is present and its value is "http://loinc.org".
- Observation.component.code.coding.display is optional and it contains optional text.
- This coding element shall occur second.

IF there is no error or no special value is reported:

h) Observation.component.valueQuantity is present

- Observation.component.valueQuantity.value is present and it contains a <string> representing the value of Compound-*Nu-Observed-Value[n].value decoded from the SFLOAT or FLOAT with the precision given by the respective Mder encoding (see Table A-42 of [b-HSTP-H812-FHIR]).
- Observation.component.valueQuantity.unit is strongly recommended and it contains the UCUM string for the unit code.
- Observation.component.valueQuantity.code is present and its value is $4 \times 2^{16} + unitTermCode$, where
 - $unitTermCode = Unit-Code$
 - IF Compound-Nu-Observed-Value is reported THEN $unitTermCode = Compound-Nu-Observed-Value[n].unit$.
- Observation.component.valueQuantity.system is present and its value is "urn.iso.std.iso:11073:10101".

IF there is an error or a special value is reported:

i) Observation.component.dataAbsentReason is present.

- Observation.component.dataAbsentReason.coding.code is present and its value is one of the FHIR codes defined in <https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html>.
- Observation.component.dataAbsentReason.coding.system is present and its

	<p>value is "http://hl7.org/fhir/data-absent-reason".</p> <ul style="list-style-type: none"> • Observation.component.dataAbsentReason.coding.display is optional and its content is some optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • The Observation.code is obtained from Type attribute. • There is an Observation.component element for each of the N sub-entries of the compound numeric value. • These component elements shall occur before any additional component elements. • FHIR resource encoding for each Observation.component is as described in step 3. • For every component, if the dataAbsentReason is present, the valueQuantity shall be absent, and if the valueQuantity is present, the dataAbsentReason shall be absent
Notes	This encoding applies to Compound-Basic-Nu-Observed-Value (contains N Mder SFLOATs), Compound-Simple-Nu-Observed-Value (contains N Mder FLOATs), or Compound-Nu-Observed-Value (contains N Mder FLOATs)

TP Id		TP/HFS/SEN/FHIR/ENC/BV-006		
TP label		Measurements Encoding: enumeration OID values		
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	MeasEnumOID 1; M	MeasEnumOID 2; M	PHGCommon 31;M
		MeasGen 2; M		
Test purpose		<p>Check that:</p> <p>The FHIR resource representing a measurement with an enumeration OID value is properly encoded.</p>		
Applicability		C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)		
Other PICs				
Initial condition		<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>		
Test procedure		<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource containing an enumeration OID value. 2. Once the measurement is received, the simulated H&FS checks that an Observation resource ("resourceType":"Observation") with Observation.meta.profile = "placeholder/phdCodedEnumerationObservation" is present. 3. In this resource, check that: <ol style="list-style-type: none"> a) Observation.code is present and: <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where: <ul style="list-style-type: none"> ▪ $termCode = Type.code$. ▪ $partition = Type.partition$. 		

	<ul style="list-style-type: none"> ▪ IF Enum-Observed-Value exists then <i>termCode</i> = Enum_Observed-Value.<i>metric-id</i>. ▪ IF <i>Metric-Id</i> is present then <i>termcode</i> = <i>Metric-Id</i>. ▪ IF <i>Metric-Id-Partition</i> is present then <i>partition</i> = <i>Metric-Id-Partition</i>. <ul style="list-style-type: none"> • Observation.code.coding.system is present and its value is "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended, and its value is the Reference Id for the code plus optional text. • If an alternative coding is also used, this coding element shall occur first. <p>IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:</p> <p>b) A second Observation.code.coding is present and:</p> <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]). • Observation.code.coding.system is present and its value is "http://loinc.org". • Observation.code.coding.display is optional and it contains optional text. • This coding element shall occur second. <p>IF there is no error:</p> <p>c) Observation.valueCodeableConcept is present</p> <ul style="list-style-type: none"> • Observation.valueCodeableConcept.coding.code is present and its value is $partition \times 2^{16} + enumTermCode$, where <ul style="list-style-type: none"> ▪ $partition = Type.partition$ ▪ $enumTermCode = Enum-Observed-Value-Simple-OID \text{ OR } Enum-Observed-Value-EnumVal.enum-obj-id$. ▪ IF Enum-Observed-Value-Partition exists THEN $partition = Enum-Observed-Value-Partition$. • Observation.valueCodeableConcept.coding.system is present and its value is "urn.iso.std.iso:11073:10101". • Observation.valueCodeableConcept.coding.display is strongly recommended and its value shall contain a reference id for the code plus optional code. <p>IF there is an error:</p> <p>d) Observation.dataAbsentReason is present</p> <ul style="list-style-type: none"> • Observation.dataAbsentReason.coding.code is present and its value is one of the FHIR codes defined in https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html • Observation.dataAbsentReason.coding.system is present and its value is "http://hl7.org/fhir/data-absent-reason". • Observation.dataAbsentReason.coding.display is optional and its value some optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for the Observation resource is as described in step 3. • If the dataAbsentReason is present, the valueCodeableConcept shall be absent • If the valueCodeableConcept is present, the dataAbsentReason shall be absent
Notes	This encoding applies to Enum-Observed-Value-Simple-OID or an Enum-Observed-Value whose EnumVal element indicates that it is an OID

TP Id	TP/HFS/SEN/FHIR/ENC/BV-007
--------------	----------------------------

TP label		Measurements Encoding: enumeration BIT values		
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	MeasEnumBIT 1; M	MeasEnumBIT 2; M	MeasEnumBIT 3; M
		MeasEnumBIT 4; M	PHGCommon 31;M	MeasGen 2; M
Test purpose		<p>Check that:</p> <p>The FHIR resource representing a measurement with an enumeration BIT value is properly encoded.</p>		
Applicability		C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)		
Other PICSSs				
Initial condition		<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>		
Test procedure		<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource containing an enumeration BIT value. 2. Once the measurement is received, the simulated H&FS checks that an Observation resource ("resourceType":"Observation") with Observation.meta.profile = "placeholder/phdBitsEnumerationObservation" is present. 3. In this resource, check that: <ol style="list-style-type: none"> a) Observation.code is present and: <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where: <ul style="list-style-type: none"> ▪ $termCode = Type.code$ ▪ $partition = Type.partition$ ▪ IF Enum-Observed-Value exists then $termCode = Enum_Observed-Value.metric-id$. ▪ IF <i>Metric-Id</i> is present then $termcode = Metric-Id$. ▪ IF <i>Metric-Id-Partition</i> is present then $partition = Metric-Id-Partition$. • Observation.code.coding.system is present and its value is "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended, and its value is the Reference Id for the code plus optional text. • If an alternative coding is also used, this coding element shall occur first. <p>IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:</p> <ol style="list-style-type: none"> b) A second Observation.code.coding is present and: <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]). • Observation.code.coding.system is present and its value is "http://loinc.org". • Observation.code.coding.display is optional and it contains optional text. • This coding element shall occur second. c) Observation.value[x] shall not be encoded. d) Observation.dataAbsentReason shall not be encoded <p>In this resource, check that for each of the bit settings to be mapped:</p> <ol style="list-style-type: none"> e) An Observation.component is present. 		

	<p>f) Observation.component.code. is present and:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.code is present and set <i>ASN1code</i> computedfromTable A-46 of [b-HSTP-H812-FHIR]. • Observation.component.code.coding.system is present and its value is "placeholder/fhir/IEEE.ASN1". • Observation.component.code.coding.display is optional and it contains ASN.1 name if known plus optional text. <p>g) Observation.component.valueCodeableConcept is present</p> <ul style="list-style-type: none"> • Observation.component.valueCodeableConcept.coding.code is present and its value is "y" if set or "n" if cleared. • Observation.component.valueCodeableConcept.coding.system is present and its value is http://hl7.org/fhir/v2/0136 • Observation.component.valueCodeableConcept.coding.display is optional and contains optional text. <p>IF there is an error, the PHG may map the measurement. If mapped:</p> <p>h) Observation.dataAbsentReason is present</p> <ul style="list-style-type: none"> • Observation.dataAbsentReason.coding.code is present and its value is one of the FHIR codes defined in https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html • Observation.dataAbsentReason.coding.system is present and its value is "http://hl7.org/fhir/data-absent-reason". • Observation.dataAbsentReason.coding.display is optional and its value some optional text. <p>The PHG may map an unsupported bit setting. If mapped, for each unsupported bit setting to be mapped:</p> <p>i) An Observation.component is present.</p> <p>j) Observation.component.code is present and:</p> <ul style="list-style-type: none"> • Observation.component.code.coding.code is present and set <i>ASN1code</i> computedfromTable A-46 of [b-HSTP-H812-FHIR]. • Observation.component.code.coding.system is present and its value is "placeholder/fhir/IEEE.ASN1". • Observation.component.code.coding.display is optional and it contains ASN.1 name if known plus optional text. <p>k) Observation.component.valueCodeableConcept is not present</p> <p>l) Observation.component.dataAbsentReason is present</p> <ul style="list-style-type: none"> • Observation.component.dataAbsentReason.coding.code is present and its value is one of the FHIR codes defined in https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html • Observation.component.dataAbsentReason.coding.system is present and its value is "http://hl7.org/fhir/data-absent-reason". • Observation.component.dataAbsentReason.coding.display is optional and its value some optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • All components listed shall occur before any additional component elements. • FHIR resource encoding for each component of the Observation resource is as described in step 3.
Notes	<p>This encoding applies to Enum-Observed-Value-Basic-Bit-Str or an Enum-Observed-Value-Simple-Bit-Str or an Enum-Observed-Value whose EnumVal element indicates it is a BITS-string</p>

TP Id		TP/HFS/SEN/FHIR/ENC/BV-008		
TP label		Measurements Encoding: enumeration String values		
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	MeasEnumStr 1; M	MeasEnumStr 2; M	PHGCommon 31;M
Test purpose		<p>Check that:</p> <p>The FHIR resource representing a measurement with an enumeration String value is properly encoded.</p>		
Applicability		C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)		
Other PICSS				
Initial condition		<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>		
Test procedure		<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource containing an enumeration String value. 2. Once the measurement is received, the simulated H&FS checks that an Observation resource ("resourceType":"Observation") with Observation.meta.profile = "placeholder/phdStringEnumerationObservation" is present. 3. In this resource, check that: <ol style="list-style-type: none"> a) Observation.code is present and: <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where: <ul style="list-style-type: none"> ▪ $termCode = Type.code$. ▪ $partition = Type.partition$. ▪ IF Enum-Observed-Value exists then $termCode = Enum_Observed-Value.metric-id$. ▪ IF <i>Metric-Id</i> is present then $termcode = Metric-Id$. ▪ IF <i>Metric-Id-Partition</i> is present then $partition = Metric-Id-Partition$. • Observation.code.coding.system is present and its value is "urn.iso.std.iso:11073:10101". • Observation.code.coding.display is strongly recommended, and its value is the Reference Id for the code plus optional text. • If an alternative coding is also used, this coding element shall occur first. <p>IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:</p> <ol style="list-style-type: none"> b) A second Observation.code.coding is present and: <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]). • Observation.code.coding.system is present and its value is "http://loinc.org". • Observation.code.coding.display is optional and it contains optional text. • This coding element shall occur second. <p>IF there is no error:</p> <ol style="list-style-type: none"> c) Observation.valueString is present 		

	<ul style="list-style-type: none"> • Observation.valueString.value is present and its value is <i>Enum-Observed-Value-Simple-Str</i> or = Enum-Observed-Value-EnumVal.enum-text-string <p>IF there is an error:</p> <p>d) Observation.dataAbsentReason is present</p> <ul style="list-style-type: none"> • Observation.dataAbsentReason.coding.code is present and its value is one of the FHIR codes defined in https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html • Observation.dataAbsentReason.coding.system is present and its value is "http://hl7.org/fhir/data-absent-reason". • Observation.dataAbsentReason.coding.display is optional and its value some optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for the Observation resource is as described in step 3. • If the dataAbsentReason is present, the valueString shall be absent • If the valueString is present, the dataAbsentReason shall be absent
Notes	This encoding applies to Enum-Observed-Value-Simple-Str or an Enum-Observed-Value whose EnumVal element indicates that it is a string.

TP Id		TP/HFS/SEN/FHIR/ENC/BV-009		
TP label		Measurements Encoding: RTSA values		
Coverage	Spec	[b-HSTP-H812-FHIR]		
	Testable items	MeasRTSA 1; M	MeasRTSA 2; M	PHGCommon 31;M
		MeasGen 2; M		
Test purpose		<p>Check that:</p> <p>The FHIR resource representing a measurement with RTSA value is properly encoded.</p>		
Applicability		C_SEN_000 AND (C_SEN_GEN_007 OR C_SEN_GEN_008)		
Other PICSS				
Initial condition		<p>Simulated H&FS supports FHIR Observation Server and Capability Exchange Continua Certified Capability Classes, so it has an FHIR API that can accept a FHIR Observation Upload that requires TLS 1.1 and an authentication token. PHG under test has already retrieved the OAuthDescriptor via the link element in the Atom Feed and has an OAuth 2.0 bearer token or valid JSON Web token to access operation in the FHIR API exposed by the H&FS.</p>		
Test procedure		<ol style="list-style-type: none"> 1. Ask the PHG to upload a FHIR resource bundle that contains a Measurement FHIR resource containing a RTSA value. 2. Once the measurement is received, the simulated H&FS checks that an Observation resource ("resourceType":"Observation") with Observation.meta.profile = "placeholder/phdRtsaObservation" is present. 3. In this resource, check that: <ol style="list-style-type: none"> a) Observation.code is present and: <ul style="list-style-type: none"> • Observation.code.coding.code is present and set to $partition \times 2^{16} + termcode$, where: <ul style="list-style-type: none"> ▪ $termCode = Type.code$. ▪ $partition = Type.partition$. 		

	<ul style="list-style-type: none"> ▪ IF <i>Metric-Id</i> is present then <i>termcode</i> = <i>Metric-Id</i>. ▪ IF <i>Metric-Id-Partition</i> is present then <i>partition</i> = <i>Metric-Id-Partition</i>. <ul style="list-style-type: none"> • <i>Observation.code.coding.system</i> is present and its value is "urn.iso.std.iso:11073:10101". • <i>Observation.code.coding.display</i> is strongly recommended, and its value is the Reference Id for the code plus optional text. • If an alternative coding is also used, this coding element shall occur first. <p>IF the measurement type is a vital sign, FHIR requires a translation to LOINC, so:</p> <p>b) A second <i>Observation.code.coding</i> is present and:</p> <ul style="list-style-type: none"> • <i>Observation.code.coding.code</i> is present and set to the LOINC code for the vital sign (see Table A-40 of [b-HSTP-H812-FHIR]). • <i>Observation.code.coding.system</i> is present and its value is "http://loinc.org". • <i>Observation.code.coding.display</i> is optional and it contains optional text. • This coding element shall occur second. <p>IF there is no error:</p> <p>c) <i>Observation.valueSampledData</i> is present and:</p> <ul style="list-style-type: none"> • <i>Observation.valueSampledData.period</i> shall be present. Its value may be set to Sample-Period / 8 (time between samples in milliseconds). • <i>Observation.valueSampledData.factor</i> shall be present. Its value may be set to scaleFactor from Table A-51 of [b-HSTP-H812-FHIR] as a decimal given the precision of the FLOAT. • <i>Observation.valueSampledData.dimensions</i> shall be set to Sa-Specification.array-size (number of samples). • <i>Observation.valueSampledData.data[i]</i> shall be set to saObsVal[i] from Table A-51 of [b-HSTP-H812-FHIR] converted to strings separated by a space, unsigned if significantBits from Table A-51 of [b-HSTP-H812-FHIR] is 255 or signed otherwise. • <i>Observation.valueSampledData.origin.value</i> shall be present. Its value may be set to offset from Table A-51 of [b-HSTP-H812-FHIR] as a decimal given the precision of the FLOAT. • <i>Observation.valueSampledData.origin.unit</i> is strongly recommended, if present, it shall be set to the UCUM code string corresponding to the Unit-Code. • <i>Observation.valueSampledData.origin.system</i> shall be set to "urn:iso:std:iso:11073:10101". • <i>Observation.valueSampledData.origin.code</i> shall be set to $4 \times 2^{16} + \text{Unit-Code}$ <p>IF there is an error:</p> <p>d) <i>Observation.dataAbsentReason</i> is present</p> <ul style="list-style-type: none"> • <i>Observation.dataAbsentReason.coding.code</i> is present and its value is one of the FHIR codes defined in https://www.hl7.org/fhir/valueset-observation-valueabsentreason.html • <i>Observation.dataAbsentReason.coding.system</i> is present and its value is "http://hl7.org/fhir/data-absent-reason". • <i>Observation.dataAbsentReason.coding.display</i> is optional and its value some optional text.
Pass/Fail criteria	<ul style="list-style-type: none"> • FHIR resource encoding for the Observation resource is as described in step 3. • If the dataAbsentReason is present, the valueSampledData shall be absent • If the valueSampledData is present, the dataAbsentReason shall be absent
Notes	

Bibliography

- [b-ITU-T H.810 (2013)] Recommendation ITU-T H.810 (2013), *Interoperability design guidelines for personal health systems*.
- [b-ITU-T H.810 (2015)] Recommendation ITU-T H.810 (2015), *Interoperability design guidelines for personal health systems*.
- [b-ITU-T H.810 (2016)] Recommendation ITU-T H.810 (2016), *Interoperability design guidelines for personal health systems*.
- [b-ITU-T H.811] Recommendation ITU-T H.811 (2017), *Interoperability design guidelines for personal connected health systems: Personal Health Devices interface*.
- [b-ITU-T H.812.1] Recommendation ITU-T H.812.1 (2017), *Interoperability design guidelines for personal connected health systems: Services interface: Observation Upload certified*.
- [b-ITU-T H.812.2] Recommendation ITU-T H.812.2 (2017), *Interoperability design guidelines for personal connected health systems: Services interface: Questionnaire capability*.
- [b-ITU-T H.812.3] Recommendation ITU-T H.812.3 (2017), *Interoperability design guidelines for personal connected health systems: Services interface: Capability Exchange capability*.
- [b-ITU-T H.812.4] Recommendation ITU-T H.812.4 (2017), *Interoperability design guidelines for personal connected health systems: Services interface: Authenticated Persistent Session capability*.
- [b-ITU-T H.813] Recommendation ITU-T H.813 (2017), *Interoperability design guidelines for personal connected health systems: Healthcare Information System interface*.
- [b-CDG 1.0] Continua Health Alliance, Continua Design Guidelines v1.0 (2008), *Continua Design Guidelines*.
- [b-CDG 2010] Continua Health Alliance, Continua Design Guidelines v1.5 (2010), *Continua Design Guidelines*.
- [b-CDG 2011] Continua Health Alliance, Continua Design Guidelines (2011), "Adrenaline", *Continua Design Guidelines*.
- [b-CDG 2012] Continua Health Alliance, Continua Design Guidelines (2012), "Catalyst", *Continua Design Guidelines*.
- [b-CDG 2013] Continua Health Alliance, Continua Design Guidelines (2013), "Endorphin", *Continua Design Guidelines*.
- [b-CDG 2015] Continua Health Alliance, Continua Design Guidelines (2015), "Genome", *Continua Design Guidelines*.
- [b-CDG 2016] Personal Connected Health Alliance, Continua Design Guidelines (2016), "Iris", *Continua Design Guidelines*.

- [b-ETSI SR 001 262] ETSI SR 001 262 v1.8.1 (2003), *ETSI drafting rules*.
<https://docbox.etsi.org/MTS/MTS/10-PromotionalMaterial/MBS-20111118/Referenced%20Documents/Drafting%20Rules.pdf>
- [b-HL7 V3 HRF] Health Level Seven (2014), *HL7 Version 3 Specification: hData Record Format, Release 1*.
http://www.hl7.org/documentcenter/private/standards/v3/V3_ITS_HDATA_RF_R1_2014JUN.pdf
- [b-IETF RFC 3339] IETF RFC 3339 (2002), *Date and Time on the Internet: Timestamps*.
<https://datatracker.ietf.org/doc/rfc3339>
- [b-HFSR PICS & PIXIT] HFS Receiver PICS and PIXIT Test Tool v7.0.2.0 – Excel sheet v1.8.
<https://handle.itu.int/11.1002/2000/12067>
- [b-HFSS PICS & PIXIT] HFS Sender PICS and PIXIT Test Tool v7.0.2.0 – Excel sheet v1.8.
<https://handle.itu.int/11.1002/2000/12067>
- [b-HSTP-H812-FHIR] Technical Paper ITU-T HSTP-H812-FHIR (2019), *Interoperability design guidelines for personal health systems: Services interface: FHIR Observation Upload for trial implementation*.

SERIES OF ITU-T RECOMMENDATIONS

Series A	Organization of the work of ITU-T
Series D	Tariff and accounting principles and international telecommunication/ICT economic and policy issues
Series E	Overall network operation, telephone service, service operation and human factors
Series F	Non-telephone telecommunication services
Series G	Transmission systems and media, digital systems and networks
Series H	Audiovisual and multimedia systems
Series I	Integrated services digital network
Series J	Cable networks and transmission of television, sound programme and other multimedia signals
Series K	Protection against interference
Series L	Environment and ICTs, climate change, e-waste, energy efficiency; construction, installation and protection of cables and other elements of outside plant
Series M	Telecommunication management, including TMN and network maintenance
Series N	Maintenance: international sound programme and television transmission circuits
Series O	Specifications of measuring equipment
Series P	Telephone transmission quality, telephone installations, local line networks
Series Q	Switching and signalling, and associated measurements and tests
Series R	Telegraph transmission
Series S	Telegraph services terminal equipment
Series T	Terminals for telematic services
Series U	Telegraph switching
Series V	Data communication over the telephone network
Series X	Data networks, open system communications and security
Series Y	Global information infrastructure, Internet protocol aspects, next-generation networks, Internet of Things and smart cities
Series Z	Languages and general software aspects for telecommunication systems