Exercises on preparing frequency assignment notices to be notified to the BR (WRS-16)

Fixed and Mobile Service (FXM)

Introduction

The goal of these exercises is to familiarize with the most common notice types applicable for Fixed and Mobile services. For recording in the Master Register, the technical and administrative characteristics required by these notice types are based on Appendix 4 to the Radio Regulations.

The list of all available notice types is given in the Preface to the BR IFIC (see Chapter III, Section 2), which is a reference document associated with the BR IFIC containing the explanation of abbreviations, symbols and remarks used in the BR IFIC as well as for notification (for example, Class of station, Nature of service, Polarization, etc.). The Preface is available in the BR IFIC DVD and on the ITU website at http://www.itu.int/en/ITU-R/terrestrial/brific/BRIFIC/Preface/PREFACE_EN.pdf

Please note, the Bureau provides guidelines and examples of notice types on the ITU website at http://www.itu.int/en/ITU-R/terrestrial/tpr/Pages/Notification.aspx

A fixed or mobile frequency assignment is uniquely identified by the following data items:

- > Assigned frequency
- ➤ Geographical coordinates (or area)
- > Designation of emission (Necessary bandwidth and class of emission)
- Class of station
- > Hours of operation

or by giving:

➤ the unique identification code of the assignment (t_adm_ref_id). This code is given and managed by the administration;

This means that these items must be unique.

In addition to the validation facility available in TerRaNotices, there is a comprehensive **online validation tool** accessible to **all TIES users** from the ITU web site at http://www.itu.int/ITU-R/terrestrial/OnlineValidation/Login.aspx. It is important to use this tool before submitting official submission to the Bureau as it would help to expedite the treatement of your notices. For any assistance, please contact brtpr dp@itu.int.

FXM 01: Fixed service (point-to-point)

Prepare an electronic notice of frequency 22.10250 GHz used for the operation of fixed link based on the information below, for its recording in the Master Register.

To prepare this notice we will use the "Wizard" functionality of TerRaNotices and we will select the administration of **Belgium (BEL)** as the notifying administration and "**FX**" for class of station

Class of Emission	D7W	
Bandwidth	3.5 MHz	
Transmitting antenna site name	SAINT-HIBERT	
Coordinates of the transmitting antenna site	5°22'50"E - 50°02'40"N	
Nature of service	"Public correspondence" - Preface Chapter	
	IV, Section 7	
Date of bringing into use	Max. 3 months in advance	
Address code	Preface Chapter IV, Section 3	
Antenna		
Antenna directivity	Directional	
Beamwidth	0.3°	
Azimuth of maximum radiation	112°	
Effective radiated power	31.2 dBW	
Power delivered to the antenna	-11.5 dBW	
Maximum Gain relative to a half wave dipole	26.3 dB	
Name of the location of the receiving station	BOUILLON	
Coordinates of the receiving station	5°05'28"E - 49°49'49"N	

FXM 02: Fixed service (Point-to-Multipoint) in shared bands

Prepare an electronic notice of frequency 23.0895 GHz, which falls within the bands shared on equal basis with the space services, used for the operation of two fixed links based on the information below, for its recording in the Master Register.

The two links are originating from the same transmitting station associated with two antennas.

To prepare this notice we will use the "New File" functionality of TerRaNotices and the functionality to add many antennas to a single notice. We will select the administration of **Lithuania** (LTU) as the notifying administration.

As the assigned frequency falls within the bands shared on equal basis with space services, the following fields are mandatory: Altitude of site above sea level, Height of Antenna above ground level, Elevation angle and Polarization.

Class of Emission	D7W
Bandwidth	7 MHz
Transmitting antenna site name	SIAULIAI TILZES
Coordinates of the transmitting antenna site	23°18'33"E - 55°55'44"N
Altitude of site above sea level	129 m
Nature of service	"Public correspondence" - Preface Chapter
	IV, Section 7
Date of bringing into use	Max. 3 years in advance
Address code	Preface Chapter IV, Section 3
Antenna	
Height of the Antenna above ground level	27 m
Antenna directivity	Directional
Azimuth of maximum radiation	174°
Beamwidth	3°
Polarization	Vertical
Elevation angle	0.3°
Maximum antenna gain relative to isotropic antenna	35.4 dBi
Equivalent isotropically radiated power	25.4 dBW
Power delivered to the antenna	-10 dBW
Name of the location of the receiving station	SIAULIAI ENERGETIKU
Coordinates of the receiving station	23°19'25"E - 55°51'15"N
Antenna	1 2
Height of the Antenna above ground level	27 m
Antenna directivity	Directional
Azimuth of maximum radiation	242°
Beamwidth	3°
Polarization	Horisontal
Elevation angle	-0.6°
Maximum antenna gain relative to isotropic antenna	34.8 dBi
Equivalent isotropically radiated power	24.8 dBW
Power delivered to the antenna	-10 dBW
Name of the location of the receiving station	SIAULIAI JABLOKNSKO
Coordinates of the receiving station	23°16'57"E - 55°55'16"N

FXM 03: Land mobile service (point-to-area/area-to-point)

1/ Prepare an electronic notice file of frequency 1 867.5000 MHz assigned to a base station having a circular receiving area of a radius of 25 km for the Administration of Egypt EGY, for its recording in the Master Register.

Bandwidth	5 MHz
Class of emission	G7W
Transmitting antenna site name	SHARM EL SHEIK
Location of transmitting station	34°23'37"E - 28°01'55"N
Nature of service	"Exclusively to operation traffic"- Preface
	Chapter IV, Section 7
Date of bringing into use	Max. 3 months in advance
Address code	Preface Chapter IV, Section 3
Effective radiated power	30 dBW
Maximum Gain relative to a half wave dipole	15 dB
Antenna directivity	Directional
Azimuth of maximum radiation	202°
Beamwidth	120°

2/Prepare an electronic notice file of frequency 1 772.500 MHz assigned to the associated receiving land mobile station (handset) of the above base station, for its recording in the Master Register.

Bandwidth	5 MHz
Class of emission	G7W
Name of the location of the receiving station	SHARM EL SHEIK
Coordinates of the receiving station	34°23'37"E - 28°01'55"N
Nature of service	"Exclusively to operation traffic"- Preface
	Chapter IV, Section 7
Date of bringing into use	Max. 3 months in advance
Address code	Preface Chapter IV, Section 3
Radius	25 km
Effective radiated power	10 dBW
Antenna directivity	Omnidirectional

To prepare these notices we will first use "New File" functionality of TerRaNotices and then we will use "Insert new notice". This functionality enables to have more than one notice in a file.

FXM 04: Maritime mobile Service (point-to-area)

Prepare an electronic notice, for the recording in the Master Register of frequency **156.8275 MHz** assigned to a **coast station** open exclusively to correspondence of a private agency situated in **CHINA** (**CHN**) having a circular receiving area of a radius of 25 km.

For coast stations, "Call sign" or "Station identification" is mandatory. Station identification can be composed of any printable character (max. 20). However, if Call sign is notified then it shall be in conformity with the provisions of Article 19 and Appendix 42.

To prepare this notice we will use "New File" functionality of TerRaNotices.

Bandwidth	16 kHz
Class of emission	F3E
Transmitting antenna site name	DANDONG
Coordinates of the transmitting antenna site	124°22'26"E - 40°07'04"N
Call sign	XSB33
Nature of service	"Exclusively to correspondence of a
	private agency"- Preface Chapter IV,
	Section 7
Date of bringing into use	Max. 3 months in advance
Address code	Preface Chapter IV, Section 3
Power delivered to the antenna	12 dBW
Maximum Gain relative to a half wave dipole	7 dB
Effective radiated power	19 dBW
Antenna directivity	Omnidirectional

FXM 05: Typical transmitting station

Prepare an electronic notice, for the recording in the Master Register of frequency 916 MHz used by several base stations in your country using the information below.

Frequency assignments having the same technical characteristics operating within a given area can be notified in a single notice as a typical transmitting station under (RR.11.17). This provision does not apply to all service types (see RR 11.18-11.21B)

To prepare this notice we will use the "Wizard" functionality of TerRaNotices.

Necessary Bandwidth	200 kHz
Class of emission	G7W
Transmitting geographical area	Enter the country code to notify
Nature of service	"Official correspondence exclusively" -
	Preface Chapter IV, Section 7
Date of bringing into use	Max. 3 months in advance
Address code	Preface Chapter IV, Section 3
Power to the antenna	10 dBW
Radiated Power	25 dBW

FXM 06: Modify a frequency assignment

Prepare an electronic notice to modify a frequency assignment which is already recorded in the **Master register**.

For this exercise, we will select the Administration of **France (F)** as the notifying administration, and Unique identification code given by Administration **817801** to modify the assigned frequency **445.625 MHz** to **445.475 MHz**

To prepare this notice we will use "Open a Notice from the database" functionality of TerRaNotices.

FXM07: Validating and identifying errors of a frequency assignment notice using TerRaNotices

Validate and identify the errors of the electronic notice file "FXM07" with error.txt".

To Validate and identify errors of a notice file, we will use "Open file" and "Validate Notice" functionalities of TerRaNotices.

FXM08: Validating the file with frequency assignment notices

Validate the electronic notice file "FXM 08_OnlineVal.txt" using the web online validation tool. This validation tool is accessible to **all TIES users** from the ITU web site at http://www.itu.int/ITU-R/terrestrial/OnlineValidation/Login.aspx.